

25W Wireless Power MPP Transmitter Module

Descriptions

SM232A module is a 25W wireless power transmitter which supports multiple Qi wireless power profiles. Including basic power profile (BPP) and magnetic power profile (MPP).

The module integrates a powerful Qi protocol SOC- SC96019 which integrates high resolution full bridge controller, full bridge power MOSFETs, multiple channels ASK demodulation circuit, multiple channels ADCs, multiple GPIO ports, Q value detection circuit and so on.


The module supports multiple power source, such as DC source, USB-PD and HVDCP. And integrates a Buck-boost converter 'SC8723B' for inverter voltage adjustment to meet different power requirements.

The module supports I2C interface and can be easily connected to other system as a submodule for control.


The module integrates multiple protection function, such as foreign object detection (FOD), over current protection (OCP), over temperature protection (OTP) and low voltage protection (LVP).

Features

- 5V~20V input voltage range
- Support USB PD3.0
- Support HVDCP interface
- 25W maxpower output
- Compliant WPC Qi2.2 protocol
- Support BPP/MPP 15Watt/ MPP 25Watt protocol
- Support I2C slaver interface
- Integrated Buck-boost converter
- Integrated foreign object detection (FOD)
- Over current protection (OCP)
- Integrated over temperature protection (OTP)
- Integrated low voltage protection (LVP)



Application Circuit



1.0 System parameter

1.1 Input voltage

SM232A module supports 5V/ 9V / 15V / 20V input voltage. Besides, USB-PD and HVDCP quick charge protocol adapter input can also be detected. Output mode will be decided by input capability.

For DC source, input voltage can be set to 9V~20V and for HVDCP, 15V is also the preferred voltage for this module:

Parameter	Test condition	MIN	TYP	MAX	UNIT
Input type	DC source	4.2	15	20	V
	Adapter 5V only		5		V
	HVDCP	5	15	20	V
	USB-PD	5	15	20	V

Note: The DC/DC input current is limited to 5A, 5V input is hard to support 25Watt output.

1.2 Ping parameter

SM232A module's coil type is TPT#MPP1-coil. In idle mode, it will take turns performing DIGITAL PING and foreign object detection. The inverter voltage is set to 127.8KHZ. The PING duty ramps up from 5% to 25% in 6ms and keeps operating for 70ms.

PING parameter	Test condition	MIN	TYP	MAX	UNIT
PING keeps time	Idle mode		70		ms
PING frequency	Idle mode		127.8		KHz
PING duty	Idle mode		25		%
PING bridge	Idle mode		half bridge		

1.3 Power transfer parameter

SM232A module supports Qi2.2 protocol and integrates multiple power profiles. They are BPP and MPP. The Max power is up to 25W in MPP mode. The ping frequency is 127.8Khz in BPP and MPP mode; then 360Khz in MPP mode Power transmission phase.

Parameter	Test condition	MIN	TYP	MAX	UNIT
Maxpower	BPP mode			5	W
	MPP 15Watt mode			15	W
	MPP 25Watt mode			25	W

Working frequency	BPP mode	127.8	KHz
	MPP mode	360	KHz

1.4 Protection parameter

SM232A module integrates multiple protection functions. Default configurations as below:

Parameter	Protect action	MIN	TYP	MAX	UNIT
INPUT OVP	Stop Charging		21		V
INPUT DPL	limit Output Power		4.6		V
OCP	Stop charging		3		A
OTP	Stop charging		95		°C
OTP_PING				65	°C
OTP_PING_HYS			20		°C
PRE_FOD	Stop Digital PING				
PTR_FOD	Stop Charging				

1.5 Module Pinout and connection guidance


SM232A module external Pinout definition is as below:

Pin	Name	USB-C Cable Connection	USB-C Receptacle Connection	USB-A Connection	DC Jack Connection
1	LED	NC	NC	NC	NC
2	CC2	NC	USB CC2	NC	NC
3	V-	GND	GND	GND	GND
4	CC1	USB CC1	USB CC1	NC	NC
5	DM	USB DM	USB DM	USB DP	NC
6	DP	USB DP	USB DP	USB DP	NC
7	V+	USB VBUS	USB VBUS	USB VBUS	USB VBUS
8	SCL	NC	NC	NC	NC
9	SDA	NC	NC	NC	NC

2.0 Performance


2.1 System startup

BPP mode



In BPP mode progresses through three fundamental phases: Ping, Configuration, and Power Transfer.


MPP mode



In MPP mode, the charging sequence begins with negotiation at 128kHz, followed by a subsequent series of phases at 360kHz, including Ping, Configuration, Negotiation, and Power Transfer.

2.2 Efficiency

SM232A module as power transfer, supporting modes are BPP, MPP Restricted, and MPP Full. To get more accurate wireless charging efficiency testing, this test sense input voltage and input current in full bridge of power transmitter and sense output power in VOUT of the receiver.




System efficiency curve



Note: Test result in the Southchip lab.

2.3 Charge curve diagram

Iphone16 plus charging curve (0%~100%, @25°C)



Note: Test result in the Southchip lab.

2.4 Thermal

Test conditions: room temperature 26 degrees, no air convection, rated load for 5 minutes.



25W MPP temperature rise, DCDC die temperature is 73.4 degrees (Maximum value)

3.0 Annex

3.1 User interface

SM232A module integrates IIC slaver interface. Rich interface can be used to configure the module and read working state, including the configuration of protection parameters, working state control etc. The slaver address is 0x36(7bit) and register map start address is 0x20000000.

<u>SC232A MPP Module Registers</u>						
Version		<u>V0.5</u>				
Interface		<u>SCLink-I2C</u>				
Speed		<u>100</u>				
Device Address		<u>0x36</u>				
Base Address		<u>0X2000 0000</u>				
Byte Order		<u>little-endian</u>				
Register Name	Offset	Bit Field				
		Bits	Field Name	Access	Value(hex)	Description
<u>REG00</u>	<u>0x0000</u>	<u>15:0</u>	<u>ChipID</u>	<u>R</u>	<u>0x6018</u>	Chip part number: 06018 = SC96018
		Bits	Field Name	Access	Value(hex)	Description
		<u>31:16</u>	<u>rsv0</u>	<u>W</u>	<u>0</u>	reserve
<u>REG04</u>	<u>0x0004</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>31:0</u>	<u>GitVer</u>	<u>R</u>	<u>0</u>	Gitlab revision number
<u>REG08</u>	<u>0x0008</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>15:0</u>	<u>HwRev</u>	<u>R</u>	<u>0</u>	Hardware revision number
	<u>0x0008</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>31:16</u>	<u>FwRev</u>	<u>R</u>	<u>0</u>	Gitlab revision number
<u>REG0C</u>	<u>0x000C</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>15:0</u>	<u>mCode</u>	<u>R</u>	<u>0</u>	WPC Manufacturer Code, this code will be sent to

						the Transmitter in the ID packet during the "identification and configuration" phase stated in WPC
		Bits	Field Name	Access	Value(hex)	Description
		<u>31:1</u> <u>6</u>	<u>rsv1</u>	<u>RW</u>	<u>0</u>	
<u>REG10</u>	<u>0x00</u> <u>10</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>7:0</u>	<u>max_pwr_5V</u>	<u>RW</u>	<u>0</u>	Unit:1[W]@Ordinary 5V adapter
		Bits	Field Name	Access	Value(hex)	Description
		<u>15:8</u>	<u>max_pwr_9V</u>	<u>RW</u>	<u>0</u>	Unit:1[W]@AFCP fast charging adapter, default 9V output
		Bits	Field Name	Access	Value(hex)	Description
		<u>23:1</u> <u>6</u>	<u>max_pwr_12V</u>	<u>RW</u>	<u>0</u>	Unit:1[W]@12V DC power input
		Bits	Field Name	Access	Value(hex)	Description
<u>31:2</u> <u>4</u>	<u>max_pwr_qc3p0</u>	<u>RW</u>	<u>0</u>	Unit:1[W]@QC3.0 adapter default 5V output, output voltage regulation 5V~12V		
<u>REG14</u>	<u>0x00</u> <u>14</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>15:0</u>	<u>ping_freq_5v</u>	<u>RW</u>	<u>0</u>	Unit:100[Hz]@Ping frequency, frequency range determined by Fmin and Fmax
	<u>0x00</u> <u>14</u>	Bits	Field Name	Access	Value(hex)	Description
<u>23:1</u> <u>6</u>	<u>ping_duty_5v</u>	<u>RW</u>	<u>0</u>	Ping duty cycle (half bridge)/phase (full bridge), range: 100-255		

		Bits	Field Name	Access	Value(hex)	Description
	<u>0x00</u> <u>14</u>	<u>31:2</u> <u>4</u>	<u>ping_brq_5v</u>	<u>RW</u>	<u>0</u>	Ping bridge status:<0: Half bridge><1: Full bridge>
<u>REG18</u>	<u>0x00</u> <u>18</u>	<u>15:0</u>	<u>ping_freq_9v</u>	<u>RW</u>	<u>0</u>	Unit:100[Hz]@Ping frequency, frequency range determined by Fmin and Fmax
	<u>0x00</u> <u>18</u>	<u>23:1</u> <u>6</u>	<u>ping_duty_9v</u>	<u>RW</u>	<u>0</u>	Ping duty cycle (half bridge)/phase (full bridge), range: 100-255
	<u>0x00</u> <u>18</u>	<u>31:2</u> <u>4</u>	<u>ping_brq_9v</u>	<u>RW</u>	<u>0</u>	Ping bridge status:<0: Half bridge><1: Full bridge>
	<u>0x00</u> <u>1C</u>	<u>15:0</u>	<u>ping_freq_12v</u>	<u>RW</u>	<u>0</u>	Unit:100[Hz]@Ping frequency, frequency range determined by Fmin and Fmax
<u>REG1C</u>	<u>0x00</u> <u>1C</u>	<u>23:1</u> <u>6</u>	<u>ping_duty_12v</u>	<u>RW</u>	<u>0</u>	Ping duty cycle (half bridge)/phase (full bridge), range: 100-255
	<u>0x00</u> <u>1C</u>	<u>31:2</u> <u>4</u>	<u>ping_brq_12v</u>	<u>RW</u>	<u>0</u>	Ping bridge status:<0: Half bridge><1: Full bridge>
	<u>REG20</u> <u>20</u>	Bits	Field Name	Access	Value(hex)	Description

		<u>15:0</u>	<u>ping_freq_qc3p0</u>	<u>RW</u>	<u>0</u>	Unit:100[Hz]@Ping frequency, frequency range determined by Fmin and Fmax
		Bits	Field Name	Access	Value(hex)	Description
		<u>23:1</u> <u>6</u>	<u>ping_duty_qc3p0</u>	<u>RW</u>	<u>0</u>	Ping duty cycle (half bridge)/phase (full bridge), range: 100-255
		Bits	Field Name	Access	Value(hex)	Description
		<u>31:2</u> <u>4</u>	<u>ping_brq_qc3p0</u>	<u>RW</u>	<u>0</u>	Ping bridge status:<0: Half bridge><1: Full bridge>
<u>REG24</u>	<u>0x00</u> <u>24</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>15:0</u>	<u>MinFreq</u>	<u>RW</u>	<u>0</u>	Current frequency adjustment range lower limit * 10
	<u>0x00</u> <u>24</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>31:1</u> <u>6</u>	<u>MaxFreq</u>	<u>RW</u>	<u>0</u>	Current frequency adjustment range upper limit * 10
<u>REG28</u>	<u>0x00</u> <u>28</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>7:0</u>	<u>isen_r</u>	<u>RW</u>	<u>0</u>	Selection of current sampling resistor:<0:10mR><1:20mR>
		Bits	Field Name	Access	Value(hex)	Description
		<u>15:8</u>	<u>print_en</u>	<u>RW</u>	<u>0</u>	NTC pin function selection:<0 UART><1:NTC>
		Bits	Field Name	Access	Value(hex)	Description
		<u>23:1</u> <u>6</u>	<u>ntc_cc</u>	<u>RW</u>	<u>0</u>	NTC constant current source current selection:<

		Bits	Field Name	Access	Value(hex)	Description
						0:OFF<<4:uA><20:uA><100:uA>
		<u>31:2</u> <u>4</u>	<u>t die otp en</u>	<u>RW</u>	<u>0</u>	Enable over temperature protection inside the chip:<0: off><1: on>
<u>REG2C</u>	<u>0x00</u> <u>2C</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>31:0</u>	<u>baud rate</u>	<u>RW</u>	<u>0</u>	Serial port printing baud rate
<u>REG30</u>	<u>0x00</u> <u>30</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>15:0</u>	<u>ntc min</u>	<u>RW</u>	<u>0</u>	NTC protection voltage
		Bits	Field Name	Access	Value(hex)	Description
		<u>31:1</u> <u>6</u>	<u>ntc max</u>	<u>RW</u>	<u>0</u>	NTC exit protection voltage
<u>REG34</u>	<u>0x00</u> <u>34</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>15:0</u>	<u>otp</u>	<u>RW</u>	<u>0</u>	Internal overheating protection temperature of the chip
		Bits	Field Name	Access	Value(hex)	Description
		<u>31:1</u> <u>6</u>	<u>utr</u>	<u>RW</u>	<u>0</u>	The chip exits the over temperature protection temperature inside
<u>REG38</u>	<u>0x00</u> <u>38</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>15:0</u>	<u>i ocp</u>	<u>RW</u>	<u>0</u>	Enter OCP, default 3000mA
		Bits	Field Name	Access	Value(hex)	Description
		<u>31:1</u> <u>6</u>	<u>v ovp</u>	<u>RW</u>	<u>0</u>	MV input OVP, 22V maximum
<u>REG3C</u>	<u>0x00</u> <u>3C</u>	Bits	Field Name	Access	Value(hex)	Description

		<u>7:0</u>	<u>dpl_en</u>	<u>RW</u>	<u>0</u>	Dynamic power limit function enable control:<0: off><1: on>
		Bits	Field Name	Access	Value(hex)	Description
		<u>15:8</u>	<u>rsv2</u>	<u>RW</u>	<u>0</u>	reserved
		Bits	Field Name	Access	Value(hex)	Description
		<u>31:16</u>	<u>v_dpl</u>	<u>RW</u>	<u>0</u>	Dynamic power limit triggering voltage setting
		Bits	Field Name	Access	Value(hex)	Description
		<u>7:0</u>	<u>ptr_fod_en</u>	<u>RW</u>	<u>0</u>	FOD enable switch during power transmission phase:<0: off><1: on>
		Bits	Field Name	Access	Value(hex)	Description
		<u>15:8</u>	<u>pre_fod_en</u>	<u>RW</u>	<u>0</u>	Q-value detection switch:<0: off><1: on>
		Bits	Field Name	Access	Value(hex)	Description
		<u>23:16</u>	<u>pre_fod_thr</u>	<u>RW</u>	<u>0</u>	Q-value detection threshold, below which FOD will be reported
		Bits	Field Name	Access	Value(hex)	Description
		<u>31:2</u>	<u>rsv3</u>	<u>RW</u>	<u>0</u>	reserved
		Bits	Field Name	Access	Value(hex)	Description
		<u>15:0</u>	<u>ptr_fod_ploss_thr</u>	<u>RW</u>	<u>0</u>	Ploss threshold
		Bits	Field Name	Access	Value(hex)	Description
		<u>15:0</u>	<u>die_temp_protect1</u>	<u>RW</u>	<u>0</u>	Threshold for over temperature protection recovery (75 degrees)
		Bits	Field Name	Access	Value(hex)	Description

		<u>31:1</u> <u>6</u>	<u>die temp protect2</u>	<u>RW</u>	<u>0</u>	Threshold for power limitation (default 80 degrees)
<u>REG54</u>	<u>0x00</u> <u>54</u>	Bits	Field Name	Access	<u>Value(hex)</u>	Description
		<u>15:0</u>	<u>die temp protect3</u>	<u>RW</u>	<u>0</u>	Threshold for disconnection of charging (default 95 degrees)
		Bits	Field Name	Access	<u>Value(hex)</u>	Description
		<u>31:1</u> <u>6</u>	<u>rsv0</u>	<u>RW</u>	<u>0</u>	reserved
<u>REG58</u>	<u>0x00</u> <u>58</u>	Bits	Field Name	Access	<u>Value(hex)</u>	Description
		<u>31:0</u>	<u>rsv1</u>	<u>RW</u>	<u>0</u>	reserved
<u>REG5C</u>	<u>0x00</u> <u>5C</u>	Bits	Field Name	Access	<u>Value(hex)</u>	Description
		<u>15:0</u>	<u>q_value</u>	<u>RW</u>	<u>0</u>	Q value calibrated under air conditions
		Bits	Field Name	Access	<u>Value(hex)</u>	Description
		<u>31:1</u> <u>6</u>	<u>q_ccz</u>	<u>RW</u>	<u>0</u>	The number of zero crossings for q-value calibration under air conditions
<u>Cmd</u>	<u>0x00</u> <u>60</u>	Bits	Field Name	Access	<u>Value(hex)</u>	Description
		<u>30</u>	<u>PRO_CM1</u>	<u>RW</u>	<u>0</u>	Project reservation function, implemented separately in the project
		<u>25</u>	<u>FOD_DISABLE</u>	<u>RW</u>	<u>0</u>	Disable foreign object detection function
		<u>24</u>	<u>FOD_ENABLE</u>	<u>RW</u>	<u>0</u>	Enable foreign object detection function
		<u>21</u>	<u>FPWM_CONFIG</u>	<u>RW</u>	<u>0</u>	Configure PWM operating parameters in open-loop mode

		<u>20</u>	<u>FPWM_UPDATE</u>	<u>RW</u>	<u>0</u>	Update PWM working parameters: Digital ping frequency and frequency adjustment range
		<u>19</u>	<u>FPWM_MANUAL</u>	<u>RW</u>	<u>0</u>	Full half bridge external control switching
		<u>18</u>	<u>FPWM_AUTO</u>	<u>RW</u>	<u>0</u>	Full half bridge automatic switching
		<u>17</u>	<u>OPEN_LOOP</u>	<u>RW</u>	<u>0</u>	Open-loop
		<u>12</u>	<u>RESET</u>	<u>RW</u>	<u>0</u>	Chip reset
		<u>5</u>	<u>OCP_CHANGE</u>	<u>RW</u>	<u>0</u>	Modify overvoltage protection
		<u>4</u>	<u>OVP_CHANGE</u>	<u>RW</u>	<u>0</u>	Modify overvoltage protection
		<u>2</u>	<u>CHANGE_VIN</u>	<u>RW</u>	<u>0</u>	Adjust input voltage
		<u>1</u>	<u>SEND_PPP</u>	<u>RW</u>	<u>0</u>	Sending FSK data
		<u>0</u>	<u>INT_CLR</u>	<u>RW</u>	<u>0</u>	Clear specified interrupt
<u>IntEn</u>	<u>0x0064</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>19</u>	<u>FOD</u>	<u>RW</u>	<u>0</u>	Detected foreign object
		<u>18</u>	<u>POWER_TRANS</u>	<u>RW</u>	<u>0</u>	Enter charging state
		<u>17</u>	<u>REMOVE_POWER</u>	<u>RW</u>	<u>0</u>	Exit charging state
		<u>16</u>	<u>RX_DET</u>	<u>RW</u>	<u>0</u>	RX detected, generated after receiving SS
		<u>13</u>	<u>PKT_RECV</u>	<u>RW</u>	<u>0</u>	Received private ASK data
		<u>11</u>	<u>EPP_DET</u>	<u>RW</u>	<u>0</u>	Detected RX supporting EPP
		<u>10</u>	<u>AFC_DET</u>	<u>RW</u>	<u>0</u>	Detected RX that supports wireless AFC protocol
		<u>7</u>	<u>DPL</u>	<u>RW</u>	<u>0</u>	Dynamic power protection
		<u>6</u>	<u>OTP_160c</u>	<u>RW</u>	<u>0</u>	Internal DIE 160 degrees Celsius over temperature
		<u>5</u>	<u>OTP</u>	<u>RW</u>	<u>0</u>	Over Temperature
		<u>4</u>	<u>LVP</u>	<u>RW</u>	<u>0</u>	Undervoltage
		<u>2</u>	<u>POVP</u>	<u>RW</u>	<u>0</u>	Bridge overvoltage
<u>1</u>	<u>OVP</u>	<u>RW</u>	<u>0</u>	Overvoltage		

		<u>0</u>	<u>OCP</u>	<u>RW</u>	<u>0</u>	Overcurrent
<i>IntFlag</i>	<u>0x00</u> <u>68</u>	<u>Bits</u>	<u>Field Name</u>	<u>Access</u>	<u>Value(hex)</u>	<u>Description</u>
		<u>19</u>	<u>FOD</u>	<u>RW</u>	<u>0</u>	Detected foreign object
		<u>18</u>	<u>POWER_TRANS</u>	<u>RW</u>	<u>0</u>	Enter charging state
		<u>17</u>	<u>REMOVE_POWER</u>	<u>RW</u>	<u>0</u>	Exit charging state
		<u>16</u>	<u>RX_DET</u>	<u>RW</u>	<u>0</u>	RX detected, generated after receiving SS
		<u>13</u>	<u>PKT_RECV</u>	<u>RW</u>	<u>0</u>	Received private ASK data
		<u>11</u>	<u>EPP_DET</u>	<u>RW</u>	<u>0</u>	Detected RX supporting EPP
		<u>10</u>	<u>AFC_DET</u>	<u>RW</u>	<u>0</u>	Detected RX that supports wireless AFC protocol
		<u>7</u>	<u>DPL</u>	<u>RW</u>	<u>0</u>	Dynamic power protection
		<u>6</u>	<u>OTP_160c</u>	<u>RW</u>	<u>0</u>	Internal DIE 160 degrees Celsius over temperature
		<u>5</u>	<u>OTP</u>	<u>RW</u>	<u>0</u>	Over Temperature
		<u>4</u>	<u>LVP</u>	<u>RW</u>	<u>0</u>	Undervoltage
		<u>2</u>	<u>POVP</u>	<u>RW</u>	<u>0</u>	Bridge overvoltage
		<u>1</u>	<u>OVP</u>	<u>RW</u>	<u>0</u>	Overvoltage
<u>0</u>	<u>OCP</u>	<u>RW</u>	<u>0</u>	Overcurrent		
<i>IntClr</i>	<u>0x00</u> <u>6C</u>	<u>Bits</u>	<u>Field Name</u>	<u>Access</u>	<u>Value(hex)</u>	<u>Description</u>
		<u>19</u>	<u>FOD</u>	<u>RW</u>	<u>0</u>	Detected foreign object
		<u>18</u>	<u>POWER_TRANS</u>	<u>RW</u>	<u>0</u>	Enter charging state
		<u>17</u>	<u>REMOVE_POWER</u>	<u>RW</u>	<u>0</u>	Exit charging state
		<u>16</u>	<u>RX_DET</u>	<u>RW</u>	<u>0</u>	RX detected, generated after receiving SS
		<u>13</u>	<u>PKT_RECV</u>	<u>RW</u>	<u>0</u>	Received private ASK data
		<u>11</u>	<u>EPP_DET</u>	<u>RW</u>	<u>0</u>	Detected RX supporting EPP
		<u>10</u>	<u>AFC_DET</u>	<u>RW</u>	<u>0</u>	Detected RX that supports wireless AFC protocol

		<u>7</u>	<u>DPL</u>	<u>RW</u>	<u>0</u>	Dynamic power protection
		<u>6</u>	<u>OTP 160c</u>	<u>RW</u>	<u>0</u>	Internal DIE 160 degrees Celsius over temperature
		<u>5</u>	<u>OTP</u>	<u>RW</u>	<u>0</u>	Over Temperature
		<u>4</u>	<u>LVP</u>	<u>RW</u>	<u>0</u>	Undervoltage
		<u>2</u>	<u>POVP</u>	<u>RW</u>	<u>0</u>	Bridge overvoltage
		<u>1</u>	<u>OVP</u>	<u>RW</u>	<u>0</u>	Overvoltage
		<u>0</u>	<u>OCP</u>	<u>RW</u>	<u>0</u>	Overcurrent
<u>CEPCnt</u>	<u>0x0070</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>31:0</u>	<u>Count</u>	<u>RW</u>	<u>0</u>	Received CEP count
<u>MODE</u>	<u>0x0074</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>4</u>	<u>PRIVATE</u>	<u>RW</u>	<u>0</u>	Private mode
		<u>3</u>	<u>MPP FULL MODE</u>	<u>RW</u>	<u>0</u>	mpp full mode
		<u>2</u>	<u>MPP RSTC MODE</u>	<u>RW</u>	<u>0</u>	mpp restrict mode
		<u>1</u>	<u>EPP</u>	<u>RW</u>	<u>0</u>	EPP mode
		<u>0</u>	<u>BPP</u>	<u>RW</u>	<u>0</u>	BPP mode
<u>REG78</u>	<u>0x0078</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>31:0</u>	<u>CRC CHECK</u>	<u>RW</u>	<u>0</u>	CRC value
<u>REG7C</u>	<u>0x007C</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>31:0</u>	<u>RPP</u>	<u>RW</u>	<u>0</u>	received power
<u>REG80</u>	<u>0x0080</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>15:0</u>	<u>OverPowerThreshold1</u>	<u>RW</u>	<u>0</u>	Threshold for overcharging due to excessive power
		Bits	Field Name	Access	Value(hex)	Description
		<u>31:16</u>	<u>OverPowerThreshold2</u>	<u>RW</u>	<u>0</u>	Threshold for power over limit
<u>REG84</u>	<u>0x0084</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>15:0</u>	<u>MaxPVINVoltageLimit</u>	<u>RW</u>	<u>0</u>	Maximum PVIN input voltage limit

		Bits	Field Name	Access	Value(hex)	Description
		<u>31:1</u> <u>6</u>	<u>MinPVINVoltageLimit</u>	<u>RW</u>	<u>0</u>	Minimum PVIN input voltage limit
<u>REG88</u>	<u>0x00</u> <u>88</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>15:0</u>	<u>OverPowerProtectionTempThreshold</u>	<u>RW</u>	<u>0</u>	Overpower protection temperature threshold
		Bits	Field Name	Access	Value(hex)	Description
		<u>31:1</u> <u>6</u>	<u>OverPowerProtectionRepingDelay</u>	<u>RW</u>	<u>0</u>	Overpower protection reping delay
<u>REG8C</u>	<u>0x00</u> <u>8C</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>15:0</u>	<u>AVin1 Threshold L</u>	<u>RW</u>	<u>0</u>	AVIN1 input mode low voltage threshold
		Bits	Field Name	Access	Value(hex)	Description
		<u>31:1</u> <u>6</u>	<u>AVin1 Threshold H</u>	<u>RW</u>	<u>0</u>	AVIN1 input mode high voltage threshold
<u>REG90</u>	<u>0x00</u> <u>90</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>7:0</u>	<u>ASK cstate</u>	<u>RW</u>	<u>0</u>	ASK data checksum status
		Bits	Field Name	Access	Value(hex)	Description
		<u>15:8</u>	<u>ASK chx</u>	<u>RW</u>	<u>0</u>	The demodulation channel of ASK data
		Bits	Field Name	Access	Value(hex)	Description
		<u>23:1</u> <u>6</u>	<u>ASKHDR</u>	<u>RW</u>	<u>0</u>	Received private ASK data header
		Bits	Field Name	Access	Value(hex)	Description
		<u>31:2</u> <u>4</u>	<u>ASKMSG L</u>	<u>RW</u>	<u>0</u>	Received private ASK data message
<u>REG94</u>	<u>0x00</u> <u>94</u>	Bits	Field Name	Access	Value(hex)	Description


		<u>31:0</u>	<u>ASKMSG_H[7]</u>	<u>RW</u>	<u>0</u>	Received private ASK data message
<u>REGB0</u>	<u>0x00</u> <u>B0</u>	Bits	Field Name	Access	<u>Value(hex)</u>	Description
		<u>7:0</u>	<u>FSKHDR</u>	<u>RW</u>	<u>0</u>	FSK header for sending data
	<u>0x00</u> <u>B0</u>	Bits	Field Name	Access	<u>Value(hex)</u>	Description
		<u>31:8</u>	<u>FSKMSG_L</u>	<u>RW</u>	<u>0</u>	FSK message for sending data
<u>REGB4</u>	<u>0x00</u> <u>B4</u>	Bits	Field Name	Access	<u>Value(hex)</u>	Description
		<u>31:0</u>	<u>FSKMSG_H[7]</u>	<u>RW</u>	<u>0</u>	FSK message for sending data
<u>REGD0</u>	<u>0x00</u> <u>D0</u>	Bits	Field Name	Access	<u>Value(hex)</u>	Description
		<u>15:0</u>	<u>SetVin</u>	<u>RW</u>	<u>0</u>	Modify the input voltage in mV
		Bits	Field Name	Access	<u>Value(hex)</u>	Description
		<u>31:1</u> <u>6</u>	<u>Vin</u>	<u>RW</u>	<u>0</u>	The input voltage sampled by the current ADC is mV
<u>REGD4</u>	<u>0x00</u> <u>D4</u>	Bits	Field Name	Access	<u>Value(hex)</u>	Description
		<u>15:0</u>	<u>Vbrq</u>	<u>RW</u>	<u>0</u>	The bridge voltage sampled by the current ADC is mV
		Bits	Field Name	Access	<u>Value(hex)</u>	Description
		<u>31:1</u> <u>6</u>	<u>lin</u>	<u>RW</u>	<u>0</u>	The current input current sampled by the ADC is in mA
<u>REGD8</u>	<u>0x00</u> <u>D8</u>	Bits	Field Name	Access	<u>Value(hex)</u>	Description
		<u>15:0</u>	<u>Power</u>	<u>RW</u>	<u>0</u>	Calculate the power mW based on the current received RX RPP

		Bits	Field Name	Access	Value(hex)	Description
		<u>31:1</u> <u>6</u>	<u>Frequency</u>	<u>RW</u>	<u>0</u>	Current operating frequency kHz * 10
REGDC	<u>0x00</u> <u>DC</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>15:0</u>	<u>Tdie</u>	<u>RW</u>	<u>0</u>	The internal DIE temperature of the chip sampled by the current ADC
		Bits	Field Name	Access	Value(hex)	Description
		<u>31:1</u> <u>6</u>	<u>tx_pwr</u>	<u>RW</u>	<u>0</u>	Current Tx power
REGEO	<u>0x00E</u> <u>0</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>15:0</u>	<u>fod_cnt</u>	<u>RW</u>	<u>0</u>	
		Bits	Field Name	Access	Value(hex)	Description
		<u>31:1</u> <u>6</u>	<u>fod_thr</u>	<u>RW</u>	<u>0</u>	
REGE4	<u>0x00E</u> <u>4</u>	Bits	Field Name	Access	Value(hex)	Description
		<u>7:0</u>	<u>charging_falg</u>	<u>RW</u>	<u>0</u>	
		Bits	Field Name	Access	Value(hex)	Description
		<u>15:8</u>	<u>rsv6</u>	<u>RW</u>	<u>0</u>	
		Bits	Field Name	Access	Value(hex)	Description

		<u>23:1</u> <u>6</u>	<u>TAType</u>	<u>RW</u>	<u>0</u>	<p>Adapter Type:</p> <p>0: unknow</p> <p>1: DC Source</p> <p>2: SDP 500mA</p> <p>3: CDP 1.1A</p> <p>4: DCP 1.5A</p> <p>5: QC2.0</p> <p>6: QC3.0</p> <p>7: PD</p> <p>8: PD PPS</p> <p>9: FCP</p> <p>10: SCP</p> <p>11: AFC</p>
		Bits	Field Name	Access	Value(hex)	Description
		<u>31:2</u> <u>4</u>	<u>EPTReson</u>	<u>RW</u>	<u>0</u>	<p>End Power Transfer values:</p> <p>0x00: Unknown</p> <p>0x01: Charge Complete</p> <p>0x02: Internal Fault</p> <p>0x03: Over Temperature</p> <p>0x04: Over Voltage</p> <p>0x05: Over Current</p> <p>0x06: Battery Failure</p> <p>0x07: Reserved</p> <p>0x08: No Response</p> <p>0x09: Reserved</p> <p>0x0a: Negotiation Failure(Extended Power Profile only)</p> <p>0x0b: Restart Power Transfer(Extended Power Profile only)</p> <p>0x0c to 0xff: Reserved</p>
<u>REGES</u>	<u>0x00E</u> <u>8</u>	Bits	Field Name	Access	Value(hex)	Description


		<u>7:0</u>	<u>Duty</u>	<u>RW</u>	<u>0</u>	Current PWM operating duty cycle.
		Bits	Field Name	Access	<u>Value(hex)</u>	Description
		<u>15:8</u>	<u>SS</u>	<u>RW</u>	<u>0</u>	This value will be written into the signal strength packet as stated in the WPC protocol. This value indicates the degree of coupling between the primary cell and the secondary coil
		Bits	Field Name	Access	<u>Value(hex)</u>	Description
		<u>23:16</u>	<u>CEP</u>	<u>RW</u>	<u>0</u>	The (two's complement) signed integer value contained in this field ranges between – 128...+127 (inclusive), and provides input to the Operating Point controller of the Power Transmitter
		Bits	Field Name	Access	<u>Value(hex)</u>	Description
		<u>31:28</u>	<u>RSVZ</u>	<u>RW</u>	<u>0</u>	
<u>REGECC</u>	<u>0x00EC</u>	Bits	Field Name	Access	<u>Value(hex)</u>	Description
		<u>15:0</u>	<u>AVin2 Threshold H</u>	<u>RW</u>	<u>0</u>	AVIN2 input mode high voltage threshold
		Bits	Field Name	Access	<u>Value(hex)</u>	Description
		<u>31:16</u>	<u>AVin2 Threshold L</u>	<u>RW</u>	<u>0</u>	AVIN2 input mode low voltage threshold

3.2 Schematic




3.3 PCB Layout


EVM adopts four-layer design, the outer size D=53mm or (53mm*53mm).




3D module




Silkscreen layer




Top layer




Inner gnd layer



Inner signal layer



Bottom layer



3.4 BOM

Num	Designator	Quantity	Description
1	C1, C2, C60, C61	4	680PF ±10% 50V X7R 0402 SMD ROHS
2	C3, C4, C15, C19, C25, C26, C30, C31, C49, C54, C58, C69, C70, C71	14	100NF ±10% 50V X7R 0402 SMD ROHS
3	C5, C6, C7, C8, C9, C10, C23, C24, C28, C29	10	22UF ±20% 25V X5R 0805 SMD ROHS
4	C11, C55, C59	3	1uF ±10% 25V X5R 0402 SMD ROHS
5	C12, C17, C47, C52, C56	5	10NF ±10% 25V X7R 0402 SMD ROHS
6	C16	1	CCTC 47NF ±5% 100V M3L 1206 SMD ROHS
7	C18	1	2.2UF ±10% 25V X5R 0603 SMD ROHS
8	C20, C21	2	2.2NF ±10% 50V X7R 0402 SMD ROHS
9	C27	1	CCTC 56NF ±5% 100V M3L 1206 SMD ROHS
10	C33	1	1NF ±20% 16V X7R 0402 SMD ROHS
11	C35, C37, C39, C40	4	CCTC 100NF ±5% 100V M3L 1206 SMD ROHS
12	C36, C38	2	2.2UF ±10% 16V X5R 0603 SMD ROHS
13	C42, C44	2	22PF ±5% 50V NPO 0402 SMD ROHS
14	C43	1	CCTC 33NF ±5% 100V M3L 1206 SMD ROHS
15	C45	1	4.7NF ±10% 50V X7R 0402 SMD ROHS
16	C46, C57	2	3.3NF ±10% 50V X7R 0402 SMD ROHS
17	C51	1	100PF ±5% 50V NPO 0402 SMD ROHS
18	D1, D7	2	JUXINTONG 1N4148WS SOD-323 SMD ROHS
19	D2, D3, D4, D5, D8, D9, D10	7	GTW ESD-5V-DS_GESD0501CM_C DFN1006 SMD ROHS
20	D6	1	GTW TVS 22V SMF22A SOD-123FL SMD ROHS
21	IC1	1	LMV358 TSSOP8_L
22	L1	1	JKZ PSPMAA1040-3R3M-ANP 3.3UH± 20%11A 11MΩ SMD RHOS
23	Q1	1	AD100K20D3 PDFN-8_L3.2-W3.1-P0.65- LS3.4-BL-EP2
24	Q2	1	AD100N40D3 DFN8P330x330
25	R1, R2, R10, R16, R17, R18, R19, R21, R22, R23, R36, R39, R41, R42, R45	15	0Ω 5% 1/16W 0402 SMD ROHS

26	R3, R5	2	51KΩ 1% 1/16W 0402 SMD ROHS
27	R4, R11, R24, R31, R40	5	10KΩ 5% 1/16W 0402 SMD ROHS
28	R6	1	68KΩ 1% 1/16W 0402 SMD ROHS
29	R7	1	510KΩ 1% 1/16W 0402 SMD ROHS
30	R8	1	91KΩ 1% 1/16W 0402 SMD ROHS
31	R9	1	47KΩ 1% 1/16W 0402 SMD ROHS
32	R12	1	33KΩ 1% 1/16W 0402 SMD ROHS
33	R14, R15	2	2Ω 1% 1/10W 0603 SMD ROHS
34	R20	1	GOLDEN-WAVE 0.01Ω 1% 1W 1206 SMD ROHS ±50PPM ALLOY
35	R25, R26	2	51KΩ 1% 1/16W 0402 SMD ROHS
36	R27	1	100Ω 1% 1/16W 0402 SMD ROHS
37	R28, R30, R38	3	5.1KΩ 5% 1/16W 0402 SMD ROHS
38	R29	1	150KΩ 1% 1/16W 0402 SMD ROHS
39	R32	1	30KΩ 5% 1/16W 0402 SMD ROHS
40	R34, R35	2	2.2KΩ 5% 1/16W 0402 SMD ROHS
41	R37	1	1MΩ 5% 1/16W 0402 SMD ROHS
42	R43	1	200KΩ 5% 1/16W 0402 SMD ROHS
43	U1	1	SC8723B/D
44	U2	1	SC96019
45	U4	1	T91-206-Q
46	X1	1	16MHz 9pf 10ppm 3225_4 SMD ROHS
47	MPP coil	1	MPP Coil with Magnet
48	PCB	1	PCB

4.0 CONTACT INFORMATION

Shanghai office

Tel: 021-58309616

Email: sales@southchip.com

Website: www.southchip.com

Address: 16F, Building D, No. 54, Lane 565, Shengxia Road, Pudong New Area, Shanghai