


**BENDER
+ WIRTH**

LED HALTER SERIE 430 + 630
LED HOLDER SERIES 430 + 630

Katalog der Standardhalter
für **LEDiL** Optiken
Catalogue of standard
holders for **LEDiL** Optics



**UNSER KONZEPT
FÜR IHRE
INDIVIDUELLE
LED MONTAGE**

**OUR CONCEPT
FOR YOUR
INDIVIDUAL
LED MOUNTING**

LEDiL[®]



Hersteller / Supplier	Optik / Optics	Halter Typ / holder type	Seite / Page
COB Halter Hybrid 630 / COB Holder Hybrid 630			
Lowprofile		6xxz LowProfile	4
Bayonet50	Ledil "B50"- Optics	6xxz Bayonet50	9
Hekla	Ledil Hekla System	6xxz Hekla	14
Bayonet35	Ledil Amy-B, Yasmeen-B	6xxz Bayonet35	20
3Hook	Ledil Angela, Molly, Ronda	6xxz 3Hook	23
Lena	Ledil Lena	6xxz Lena	28
LED Halter 430 / LED Holder 430			
Basishalter / Standard holders		4xx Typ xx	33
Ledil	2x2MX	4xx Typ 2x2MX HV	39
	Clamp System	Angela, Angelette, Angelina, Molly, Ronda	4xx Typ L1 / L2 / L3 43
	Hekla System	Barbara-G2, Mirella-G2, Brooke-G2, Carmen, Ronda, Winnie, Zorya	4xx Typ L8 49
	Lena		4xx Typ L1 / L2 / L3 55
	PF-System	Barbara, Mirella	4xx Typ L1 / L2 60
	Saga		4xx Typ L6 65
	Stella L1	Stella A	4xx Typ L1 70
	Stella L4	Stella HB, HB WWW, Fresnel,RS, G2-VSM	4xx Typ L4 74
	Stella Z1	Stella T4, VSM, DWC2, G2-T2, G2-T3, G2-T4	4xx Typ Z1 77
	Winnie		4xx Typ L5 82
	Zorya		4xx Typ L7 87
Zhaga	Book 3		4xx Typ Z1 92

Ist Ihre COB oder die gewünschte Bauform nicht aufgeführt?

Bitte sprechen Sie uns an.

If your COB or requested shape is not listed, please contact us.

Die dargestellten Halter / Reflektor Kombinationen zeigen lediglich die technische Machbarkeit. Technische Daten und Montagehinweise sind in unserem Technical Guide LED Halter Serie 430 und 630 aufgeführt.

Die Kabelaustritte an den Haltern sind abhängig vom verwendeten COB. Optische Daten und Datenblätter gibt es auf Anfrage nach Verfügbarkeit beim Reflektorhersteller.

The illustrated holder / reflector combinations only show the technical feasibility.




Technical data and mounting instructions are listed in our Technical Guide LED holder series 430 and 630.

The cable exits of the holders are pending on the COB.

Optical data and datasheets are available upon request and availability by the reflector manufacturer.

Die Informationen in diesem Dokument sind ohne Gewähr und können ohne Vorankündigung geändert werden.

The information in this document is provided without liability and subject to change without notice.




Gehäusotyp: Housing:		LowProfile		Größe / Size : 44/50 mm Höhe / Height : 3,4 mm	
Beispiele für passende Optiken examples of suitable optics		LEDiL STELLA-T4, -VSM LEDiL STELLA-DWC2 LEDiL STELLA-G2-T2, -T3, -T4			
Version 1: 633x, 634x, 637x, 638x, 641x, 652x, 660x					
					
Version 2: 631x, 632x, 639x, 663x					
					
Bemessungsspannung rated voltage		Standard 250V DC optional 450V DC		Zulässige COB Abmessungen Permissible COB dimensions	
Bemessungsstrom rated current		5 A			
Bemessungstemperatur rated operating temperature		T 120		siehe Einzeldatenblätter im Online Katalog	
Befestigung fixing		2 Schrauben M3 2 screws M3		see data sheets at our web catalogue	
max. Drehmoment max. torque		0,5 Nm			
Material des Halters material of the holder		PBT / Mikanit PBT / Mica		Zertifikate / certificates	
Kontaktmaterial contactmaterial		CuSn CuSn		 Ausweis-Nr.  File E4729	
Weitere technische Daten und Montagehinweise sind im Technical Guide COB Halterserie 630 enthalten. Further technical details and mounting instructions are part of the Technical Guide COB holder series 630 .					

Teilumhüllter Halter für folgende COBs / unenclosed holder for the following COBs:			
Hersteller supplier	COB Typ COB Type	Teile-Nr. part no.	Haltervariante variant of holder
Bridgelux	V3 HD / V4 HD Gen 7,8	47954	COB Holder Hybrid 660a LowProfile
Bridgelux	V6 HD Gen 7,8	47870	COB Holder Hybrid 634c LowProfile
Bridgelux	V9 HD / V11 HD Gen 7,8	47862	COB Holder Hybrid 633d LowProfile
Bridgelux	V6 Gen 8,9 (just 2 pads!)	47954	COB Holder Hybrid 660a LowProfile
Bridgelux	V8 Gen 7,8,9 (4 pads)	47954	COB Holder Hybrid 660a LowProfile
Bridgelux	V10 Gen 7,8,9	47866	COB Holder Hybrid 634b LowProfile
Bridgelux	V13 Gen 7,8,9	47861	COB Holder Hybrid 633c LowProfile
Bridgelux	V18 Gen 7,8,9	47884	COB Holder Hybrid 639b LowProfile
Bridgelux	V22 Gen 7,8,9	47856	COB Holder Hybrid 631b LowProfile
Bridgelux	Vesta DTW 6/9mm Gen 1,2	47894	COB Holder Hybrid 652b LowProfile
Bridgelux	Vesta DTW 13/15mm Gen 1,2	47860	COB Holder Hybrid 632b LowProfile
Bridgelux	Vesta DTW 18mm Gen 1	on request	COB Holder Hybrid 639c LowProfile
Bridgelux	Vesta Tunable 9mm Gen 2	on request	Werkzeug fehlt / Tooling required
Bridgelux	Vesta Tunable 13mm Gen 2	on request	Werkzeug fehlt / Tooling required
Citizen	CLU 028 / 02J / 02Q	47659	COB Holder Hybrid 634a LowProfile
Citizen	CLU 038 / 03H / 03J / 03Q	47590	COB Holder Hybrid 633a LowProfile
Citizen	CLU 048 / 04H / 04J / 04Q	47584	COB Holder Hybrid 631a LowProfile
Citizen	CLU 7L3 / 7S3	on request	Werkzeug fehlt / Tooling required
Citizen	CLU 702 / 703 / 7A2 / 7A3 / 7B2	47659	COB Holder Hybrid 634a LowProfile
Citizen	CLU 712 / 713	47861	COB Holder Hybrid 633c LowProfile
Citizen	CLU 723	47861	COB Holder Hybrid 633c LowProfile
Citizen	CLU 733	47856	COB Holder Hybrid 631b LowProfile
CREE	CHA 0304 / 0410 / 0612	47659	COB Holder Hybrid 634a LowProfile
CREE	CHA 0825	47590	COB Holder Hybrid 633a LowProfile
CREE	CMA 1303 / 1306	47870	COB Holder Hybrid 634c LowProfile
CREE	CMA 1516	47462	COB Holder Hybrid 641a LowProfile
CREE	CMA 1825 / 1840	47471	COB Holder Hybrid 637a LowProfile
CREE	CMA 2550	47586	COB Holder Hybrid 639a LowProfile
CREE	CMB 1304 / 1306	47870	COB Holder Hybrid 634c LowProfile
CREE	CMB 1507 / 1510 / 1516	47462	COB Holder Hybrid 641a LowProfile
CREE	CMB 1818 / 1825	47471	COB Holder Hybrid 637a LowProfile
CREE	CMB 1840	47874	COB Holder Hybrid 637b LowProfile
CREE	CMB 2550	47586	COB Holder Hybrid 639a LowProfile
CREE	CMT 1407 / 1412 / 1420	47659	COB Holder Hybrid 634a LowProfile
CREE	CMT 1922 / 1925 / 1930 / 1945	47861	COB Holder Hybrid 633c LowProfile
CREE	CMT 2850 / 2870 / 2890	47856	COB Holder Hybrid 631b LowProfile
CREE	CMU 1003 / 1006 / 1010 / 1013	47659	COB Holder Hybrid 634a LowProfile
CREE	CMU 1516 / 1519 / 1526 / 1532	47590	COB Holder Hybrid 633a LowProfile
CREE	CMU 2236 / 2239 / 2258 / 2287	47856	COB Holder Hybrid 631b LowProfile
CREE	CXB 1304 / 1310	47870	COB Holder Hybrid 634c LowProfile

CREE	CXB 1507 / 1512 / 1520	47462	COB Holder Hybrid 641a	LowProfile
CREE	CXB 1816 / 1820	47471	COB Holder Hybrid 637a	LowProfile
CREE	CXB 1830	47874	COB Holder Hybrid 637b	LowProfile
CREE	CXB 2530 / 2540	47586	COB Holder Hybrid 639a	LowProfile
Edison	2PHE 03 / 06 / 09 / 13	47659	COB Holder Hybrid 634a	LowProfile
Edison	2PHE 15 / 18 / 24 / 30	47590	COB Holder Hybrid 633a	LowProfile
Edison	2PHE 55 / 60 / 83	47584	COB Holder Hybrid 631a	LowProfile
Lextar	PB 06 / 09 / 13	47659	COB Holder Hybrid 634a	LowProfile
Lextar	PB 16 / 19 / 26	47590	COB Holder Hybrid 633a	LowProfile
Lextar	PB 38 / 54	47584	COB Holder Hybrid 631a	LowProfile
Lumileds	Luxeon 1202s / 1202HD	47455	COB Holder Hybrid 652a	LowProfile
Lumileds	Luxeon 1202 / 1203 / 1204HD	47880	COB Holder Hybrid 638b	LowProfile
Lumileds	Luxeon 1205HD	47880	COB Holder Hybrid 638b	LowProfile
Lumileds	Luxeon 1204 / 1205	47581	COB Holder Hybrid 632a	LowProfile
Lumileds	Luxeon 1208 / 1210	47581	COB Holder Hybrid 632a	LowProfile
Lumileds	Luxeon 1211	47856	COB Holder Hybrid 631b	LowProfile
Lumileds	Luxeon 1213 / 1216 / 1812 / 1816	47856	COB Holder Hybrid 631b	LowProfile
Lumileds	CS COB L02 / L04	47659	COB Holder Hybrid 634a	LowProfile
Lumileds	CS COB L06 / L08 / L10	47590	COB Holder Hybrid 633a	LowProfile
Lumileds	CS COB L11 / L13 / L16	47584	COB Holder Hybrid 631a	LowProfile
Lumileds	CS COB R12 / R18	47584	COB Holder Hybrid 631a	LowProfile
Lumileds	CX Plus HD S01H4, S0xH6	47870	COB Holder Hybrid 634c	LowProfile
Lumileds	CX Plus HD S04H9	47866	COB Holder Hybrid 634b	LowProfile
Lumileds	CX Plus S01Fx / S02Fx	47870	COB Holder Hybrid 634c	LowProfile
Lumileds	CX Plus M02Fx / M03Fx	47462	COB Holder Hybrid 641a	LowProfile
Lumileds	CX Plus L04Fx / L05Fx / L08Fx	47471	COB Holder Hybrid 637a	LowProfile
Luminus	CXM-3-xC	47659	COB Holder Hybrid 634a	LowProfile
Luminus	CHM-4-BH / CXM-4-xC	47659	COB Holder Hybrid 634a	LowProfile
Luminus	CHM-6-BH / CXM-6-xC	47659	COB Holder Hybrid 634a	LowProfile
Luminus	CIM/CLM/CXM-9-xC	47659	COB Holder Hybrid 634a	LowProfile
Luminus	CHM-9-BH	47590	COB Holder Hybrid 633a	LowProfile
Luminus	CXM-11-xC	47590	COB Holder Hybrid 633a	LowProfile
Luminus	CGM/CIM/CLM/CXM-14-xC	47590	COB Holder Hybrid 633a	LowProfile
Luminus	CXM-18 Gen6	47584	COB Holder Hybrid 631a	LowProfile
Luminus	CGM/CIM/CLM/CXM-22-xC	47584	COB Holder Hybrid 631a	LowProfile
Luminus	CDM-6 / CDM-9Gen1 DtW	47894	COB Holder Hybrid 652b	LowProfile
Luminus	CDM-9 Gen2 DtW	47860	COB Holder Hybrid 632b	LowProfile
Luminus	CDM-14/CDM-18 DtW	47860	COB Holder Hybrid 632b	LowProfile
Luxtech	COB-WD-10-1512	47455	COB Holder Hybrid 652a	LowProfile
Luxtech	COB-WD-17-2420	47581	COB Holder Hybrid 632a	LowProfile
Nichia	NV..S007Z / NF..T012B	47455	COB Holder Hybrid 652a	LowProfile
Nichia	NF..S024B / NT..S024B	47455	COB Holder Hybrid 652a	LowProfile
Nichia	NJ..S024Z	47455	COB Holder Hybrid 652a	LowProfile

Nichia	NV..L016Z / NV..L024Z	47465	COB Holder Hybrid 638a	LowProfile
Nichia	NF..L036B / NF..L048B	47465	COB Holder Hybrid 638a	LowProfile
Nichia	NF..L060B	47465	COB Holder Hybrid 638a	LowProfile
Nichia	NV..J048Z / NF..J108B	47953	COB Holder Hybrid 663a	LowProfile
Nichia	NF..J130B	47953	COB Holder Hybrid 663a	LowProfile
Philips	Fortimo SLM12xx .. 1215 G7	47455	COB Holder Hybrid 652a	LowProfile
Philips	Fortimo SLM12xx .. 1619 G7	47880	COB Holder Hybrid 638b	LowProfile
Philips	Fortimo SLM12xx .. 2024 G7	47581	COB Holder Hybrid 632a	LowProfile
Philips	Fortimo SLM12xx .. 2828 G7	47856	COB Holder Hybrid 631b	LowProfile
Philips	Fortimo SLM12xx .. 1313 G7N	47659	COB Holder Hybrid 634a	LowProfile
Philips	Fortimo SLM12xx .. 1919 G7N	47590	COB Holder Hybrid 633a	LowProfile
Philips	Fortimo SLM12xx .. 2828 G7N	47856	COB Holder Hybrid 631b	LowProfile
Philips	Fortimo SLM13xx .. 2024 G8 UHE	47581	COB Holder Hybrid 632a	LowProfile
Philips	Fortimo SLM13xx .. 2828 G8 UHE	47856	COB Holder Hybrid 631b	LowProfile
Prolight Opto	PASB	47659	COB Holder Hybrid 634a	LowProfile
Prolight Opto	PASQ/PAPQ DimToWarm	47659	COB Holder Hybrid 634a	LowProfile
Prolight Opto	PDSQ DimToWarm	47894	COB Holder Hybrid 652b	LowProfile
Prolight Opto	PDSR DimToWarm	47860	COB Holder Hybrid 632b	LowProfile
Samsung	LC 010C	47659	COB Holder Hybrid 634a	LowProfile
Samsung	LC 020C / 030C / 040C	47861	COB Holder Hybrid 633c	LowProfile
Samsung	LC 003D / 006D	47659	COB Holder Hybrid 634a	LowProfile
Samsung	LC 009D / 013D	47659	COB Holder Hybrid 634a	LowProfile
Samsung	LC 016D / 019D	47861	COB Holder Hybrid 633c	LowProfile
Samsung	LC 026D / 033D	47861	COB Holder Hybrid 633c	LowProfile
Samsung	LC 040D / 060D / 080D	47856	COB Holder Hybrid 631b	LowProfile
Seoul	SAW* 0661	47866	COB Holder Hybrid 634b	LowProfile
Seoul	SAW* 1062 / 1063	47866	COB Holder Hybrid 634b	LowProfile
Seoul	SAW* 1564 / 1565 / 1566	47861	COB Holder Hybrid 633c	LowProfile
Seoul	SAW* 22AA / 2296	47584	COB Holder Hybrid 631a	LowProfile
Seoul	SAW* 2298 / 226A	47584	COB Holder Hybrid 631a	LowProfile
Tridonic	SLE ADV8 LES 04 / 06	47659	COB Holder Hybrid 634a	LowProfile
Tridonic	SLE ADV8 LES 09	47659	COB Holder Hybrid 634a	LowProfile
Tridonic	SLE ADV8 LES 13	47861	COB Holder Hybrid 633c	LowProfile
Tridonic	SLE ADV8 LES 15	47861	COB Holder Hybrid 633c	LowProfile
Tridonic	SLE ADV8 LES 17	47856	COB Holder Hybrid 631b	LowProfile
Tridonic	SLE ADV8 LES 21	47856	COB Holder Hybrid 631b	LowProfile
Tridonic	SLE SNC8 LES 06	47659	COB Holder Hybrid 634a	LowProfile
Tridonic	SLE SNC8 LES 09	47659	COB Holder Hybrid 634a	LowProfile
Tridonic	SLE SNC8 LES 15	47861	COB Holder Hybrid 633c	LowProfile
VS Lighting	DMS 102 ***W	47659	COB Holder Hybrid 634a	LowProfile
VS Lighting	DMS 124 ***W	47659	COB Holder Hybrid 634a	LowProfile
VS Lighting	DMS 125 / 126 / 128 ***W	47590	COB Holder Hybrid 633a	LowProfile
VS Lighting	DMS 120 ***W	47584	COB Holder Hybrid 631a	LowProfile

VS Lighting	DMS 12C / 18B ***W	47584	COB Holder Hybrid 631a	LowProfile
VS Lighting	DMS 1208J	47590	COB Holder Hybrid 633a	LowProfile
VS Lighting	DMS 1212J / 1812J	47584	COB Holder Hybrid 631a	LowProfile
VS Lighting	VCA 042	47866	COB Holder Hybrid 634b	LowProfile
VS Lighting	VCA2 122 / 123 / 124	47866	COB Holder Hybrid 634b	LowProfile
VS Lighting	VCA2 126 / 128	47861	COB Holder Hybrid 633c	LowProfile
VS Lighting	VCA2 1211 / 1213	47856	COB Holder Hybrid 631b	LowProfile
VS Lighting	WU-M-618 DimToWarm	47659	COB Holder Hybrid 634a	LowProfile
Xicato	XOB 04	47866	COB Holder Hybrid 634b	LowProfile
Xicato	XOB 06 (B)	47866	COB Holder Hybrid 634b	LowProfile
Xicato	XOB 09	47659	COB Holder Hybrid 634a	LowProfile
Xicato	XOB 14	47590	COB Holder Hybrid 633a	LowProfile
Xicato	XOB 23	47584	COB Holder Hybrid 631a	LowProfile

Gehäusetyp: Housing:		Bayonet50		Größe / Size : 50 mm Höhe / Height : 4,9 mm	
Beispiele für passende Optiken examples of suitable optics		LEDiL ANGELA-B, ANGELINA-B, ANGELETTE-B LEDiL ZORYA-B LEDiL ADELIA-B 50/70/110			
633a/47420 (2 + 1) Version 1: 633x, 634x, 637x, 638x, 641x, 652x, 660x  631a/47512 (2 + 1) Version 2: 631x, 632x, 639x, 663x   					
Bemessungsspannung rated voltage		Standard 250V DC optional 450V DC		Zulässige COB Abmessungen Permissible COB dimensions	
Bemessungsstrom rated current		5 A			
Bemessungstemperatur rated operating temperature		T 120		siehe Einzeldatenblätter im Online Katalog	
Befestigung fixing		2 Schrauben M3 2 screws M3		see data sheets at our web catalogue	
max. Drehmoment max. torque		0,5 Nm			
Material des Halters material of the holder		PBT / Mikanit PBT / Mica		Zertifikate / certificates	
Kontaktmaterial contactmaterial		CuSn CuSn		 Ausweis-Nr.  File E4729	
Weitere technische Daten und Montagehinweise sind im Technical Guide COB Halterserie 630 enthalten. Further technical details and mounting instructions are part of the Technical Guide COB holder series 630 .					

Teilumhüllter Halter für folgende COBs / unenclosed holder for the following COBs:				
Hersteller supplier	COB Typ COB Type	Teile-Nr. part no.	Haltervariante variant of holder	
Bridgelux	V3 HD / V4 HD Gen 7,8	47955	COB Holder Hybrid 660a	Bayonet50
Bridgelux	V6 HD Gen 7,8	47414	COB Holder Hybrid 634c	Bayonet50
Bridgelux	V9 HD / V11 HD Gen 7,8	47423	COB Holder Hybrid 633d	Bayonet50
Bridgelux	V6 Gen 8,9 (just 2 pads!)	47955	COB Holder Hybrid 660a	Bayonet50
Bridgelux	V8 Gen 7,8,9 (4 pads)	47955	COB Holder Hybrid 660a	Bayonet50
Bridgelux	V10 Gen 7,8,9	47413	COB Holder Hybrid 634b	Bayonet50
Bridgelux	V13 Gen 7,8,9	47422	COB Holder Hybrid 633c	Bayonet50
Bridgelux	V18 Gen 7,8,9	47539	COB Holder Hybrid 639b	Bayonet50
Bridgelux	V22 Gen 7,8,9	47528	COB Holder Hybrid 631b	Bayonet50
Bridgelux	Vesta DTW 6/9mm Gen 1,2	47890	COB Holder Hybrid 652b	Bayonet50
Bridgelux	Vesta DTW 13/15mm Gen 1,2	47857	COB Holder Hybrid 632b	Bayonet50
Bridgelux	Vesta DTW 18mm Gen 1	on request	COB Holder Hybrid 639c	Bayonet50
Bridgelux	Vesta Tunable 9mm Gen 2	on request	Werkzeug fehlt / Tooling required	
Bridgelux	Vesta Tunable 13mm Gen 2	on request	Werkzeug fehlt / Tooling required	
Citizen	CLU 028 / 02J / 02Q	47412	COB Holder Hybrid 634a	Bayonet50
Citizen	CLU 038 / 03H / 03J / 03Q	47420	COB Holder Hybrid 633a	Bayonet50
Citizen	CLU 048 / 04H / 04J / 04Q	47512	COB Holder Hybrid 631a	Bayonet50
Citizen	CLU 7L3 / 7S3	on request	Werkzeug fehlt / Tooling required	
Citizen	CLU 702 / 703 / 7A2 / 7A3 / 7B2	47412	COB Holder Hybrid 634a	Bayonet50
Citizen	CLU 712 / 713	47422	COB Holder Hybrid 633c	Bayonet50
Citizen	CLU 723	47422	COB Holder Hybrid 633c	Bayonet50
Citizen	CLU 733	47528	COB Holder Hybrid 631b	Bayonet50
CREE	CHA 0304 / 0410 / 0612	47412	COB Holder Hybrid 634a	Bayonet50
CREE	CHA 0825	47420	COB Holder Hybrid 633a	Bayonet50
CREE	CMA 1303 / 1306	47414	COB Holder Hybrid 634c	Bayonet50
CREE	CMA 1516	47458	COB Holder Hybrid 641a	Bayonet50
CREE	CMA 1825 / 1840	47468	COB Holder Hybrid 637a	Bayonet50
CREE	CMA 2550	47538	COB Holder Hybrid 639a	Bayonet50
CREE	CMB 1304 / 1306	47414	COB Holder Hybrid 634c	Bayonet50
CREE	CMB 1507 / 1510 / 1516	47458	COB Holder Hybrid 641a	Bayonet50
CREE	CMB 1818 / 1825	47468	COB Holder Hybrid 637a	Bayonet50
CREE	CMB 1840	47534	COB Holder Hybrid 637b	Bayonet50
CREE	CMB 2550	47538	COB Holder Hybrid 639a	Bayonet50
CREE	CMT 1407 / 1412 / 1420	47412	COB Holder Hybrid 634a	Bayonet50
CREE	CMT 1922 / 1925 / 1930 / 1945	47422	COB Holder Hybrid 633c	Bayonet50
CREE	CMT 2850 / 2870 / 2890	47528	COB Holder Hybrid 631b	Bayonet50
CREE	CMU 1003 / 1006 / 1010 / 1013	47412	COB Holder Hybrid 634a	Bayonet50
CREE	CMU 1516 / 1519 / 1526 / 1532	47420	COB Holder Hybrid 633a	Bayonet50
CREE	CMU 2236 / 2239 / 2258 / 2287	47528	COB Holder Hybrid 631b	Bayonet50
CREE	CXB 1304 / 1310	47414	COB Holder Hybrid 634c	Bayonet50

CREE	CXB 1507 / 1512 / 1520	47458	COB Holder Hybrid 641a	Bayonet50
CREE	CXB 1816 / 1820	47468	COB Holder Hybrid 637a	Bayonet50
CREE	CXB 1830	47534	COB Holder Hybrid 637b	Bayonet50
CREE	CXB 2530 / 2540	47538	COB Holder Hybrid 639a	Bayonet50
Edison	2PHE 03 / 06 / 09 / 13	47412	COB Holder Hybrid 634a	Bayonet50
Edison	2PHE 15 / 18 / 24 / 30	47420	COB Holder Hybrid 633a	Bayonet50
Edison	2PHE 55 / 60 / 83	47512	COB Holder Hybrid 631a	Bayonet50
Lextar	PB 06 / 09 / 13	47412	COB Holder Hybrid 634a	Bayonet50
Lextar	PB 16 / 19 / 26	47420	COB Holder Hybrid 633a	Bayonet50
Lextar	PB 38 / 54	47512	COB Holder Hybrid 631a	Bayonet50
Lumileds	Luxeon 1202s / 1202HD	47453	COB Holder Hybrid 652a	Bayonet50
Lumileds	Luxeon 1202 / 1203 / 1204HD	47876	COB Holder Hybrid 638b	Bayonet50
Lumileds	Luxeon 1205HD	47876	COB Holder Hybrid 638b	Bayonet50
Lumileds	Luxeon 1204 / 1205	47449	COB Holder Hybrid 632a	Bayonet50
Lumileds	Luxeon 1208 / 1210	47449	COB Holder Hybrid 632a	Bayonet50
Lumileds	Luxeon 1211	47528	COB Holder Hybrid 631b	Bayonet50
Lumileds	Luxeon 1213 / 1216 / 1812 / 1816	47528	COB Holder Hybrid 631b	Bayonet50
Lumileds	CS COB L02 / L04	47412	COB Holder Hybrid 634a	Bayonet50
Lumileds	CS COB L06 / L08 / L10	47420	COB Holder Hybrid 633a	Bayonet50
Lumileds	CS COB L11 / L13 / L16	47512	COB Holder Hybrid 631a	Bayonet50
Lumileds	CS COB R12 / R18	47512	COB Holder Hybrid 631a	Bayonet50
Lumileds	CX Plus HD S01H4, S0xH6	47414	COB Holder Hybrid 634c	Bayonet50
Lumileds	CX Plus HD S04H9	47413	COB Holder Hybrid 634b	Bayonet50
Lumileds	CX Plus S01Fx / S02Fx	47414	COB Holder Hybrid 634c	Bayonet50
Lumileds	CX Plus M02Fx / M03Fx	47458	COB Holder Hybrid 641a	Bayonet50
Lumileds	CX Plus L04Fx / L05Fx / L08Fx	47468	COB Holder Hybrid 637a	Bayonet50
Luminus	CXM-3-xC	47412	COB Holder Hybrid 634a	Bayonet50
Luminus	CHM-4-BH / CXM-4-xC	47412	COB Holder Hybrid 634a	Bayonet50
Luminus	CHM-6-BH / CXM-6-xC	47412	COB Holder Hybrid 634a	Bayonet50
Luminus	CIM/CLM/CXM-9-xC	47412	COB Holder Hybrid 634a	Bayonet50
Luminus	CHM-9-BH	47420	COB Holder Hybrid 633a	Bayonet50
Luminus	CXM-11-xC	47420	COB Holder Hybrid 633a	Bayonet50
Luminus	CGM/CIM/CLM/CXM-14-xC	47420	COB Holder Hybrid 633a	Bayonet50
Luminus	CXM-18 Gen6	47512	COB Holder Hybrid 631a	Bayonet50
Luminus	CGM/CIM/CLM/CXM-22-xC	47512	COB Holder Hybrid 631a	Bayonet50
Luminus	CDM-6 / CDM-9Gen1 DtW	47890	COB Holder Hybrid 652b	Bayonet50
Luminus	CDM-9 Gen2 DtW	47857	COB Holder Hybrid 632b	Bayonet50
Luminus	CDM-14/CDM-18 DtW	47857	COB Holder Hybrid 632b	Bayonet50
Luxtech	COB-WD-10-1512	47453	COB Holder Hybrid 652a	Bayonet50
Luxtech	COB-WD-17-2420	47449	COB Holder Hybrid 632a	Bayonet50
Nichia	NV..S007Z / NF..T012B	47453	COB Holder Hybrid 652a	Bayonet50
Nichia	NF..S024B / NT..S024B	47453	COB Holder Hybrid 652a	Bayonet50
Nichia	NJ..S024Z	47453	COB Holder Hybrid 652a	Bayonet50

Nichia	NV..L016Z / NV..L024Z	47463	COB Holder Hybrid 638a	Bayonet50
Nichia	NF..L036B / NF..L048B	47463	COB Holder Hybrid 638a	Bayonet50
Nichia	NF..L060B	47463	COB Holder Hybrid 638a	Bayonet50
Nichia	NV..J048Z / NF..J108B	47932	COB Holder Hybrid 663a	Bayonet50
Nichia	NF..J130B	47932	COB Holder Hybrid 663a	Bayonet50
Philips	Fortimo SLM12xx .. 1215 G7	47453	COB Holder Hybrid 652a	Bayonet50
Philips	Fortimo SLM12xx .. 1619 G7	47876	COB Holder Hybrid 638b	Bayonet50
Philips	Fortimo SLM12xx .. 2024 G7	47449	COB Holder Hybrid 632a	Bayonet50
Philips	Fortimo SLM12xx .. 2828 G7	47528	COB Holder Hybrid 631b	Bayonet50
Philips	Fortimo SLM12xx .. 1313 G7N	47412	COB Holder Hybrid 634a	Bayonet50
Philips	Fortimo SLM12xx .. 1919 G7N	47420	COB Holder Hybrid 633a	Bayonet50
Philips	Fortimo SLM12xx .. 2828 G7N	47528	COB Holder Hybrid 631b	Bayonet50
Philips	Fortimo SLM13xx .. 2024 G8 UHE	47449	COB Holder Hybrid 632a	Bayonet50
Philips	Fortimo SLM13xx .. 2828 G8 UHE	47528	COB Holder Hybrid 631b	Bayonet50
Prolight Opto	PASB	47412	COB Holder Hybrid 634a	Bayonet50
Prolight Opto	PASQ/PAPQ DimToWarm	47412	COB Holder Hybrid 634a	Bayonet50
Prolight Opto	PDSQ DimToWarm	47890	COB Holder Hybrid 652b	Bayonet50
Prolight Opto	PDSR DimToWarm	47857	COB Holder Hybrid 632b	Bayonet50
Samsung	LC 010C	47412	COB Holder Hybrid 634a	Bayonet50
Samsung	LC 020C / 030C / 040C	47422	COB Holder Hybrid 633c	Bayonet50
Samsung	LC 003D / 006D	47412	COB Holder Hybrid 634a	Bayonet50
Samsung	LC 009D / 013D	47412	COB Holder Hybrid 634a	Bayonet50
Samsung	LC 016D / 019D	47422	COB Holder Hybrid 633c	Bayonet50
Samsung	LC 026D / 033D	47422	COB Holder Hybrid 633c	Bayonet50
Samsung	LC 040D / 060D / 080D	47528	COB Holder Hybrid 631b	Bayonet50
Seoul	SAW* 0661	47413	COB Holder Hybrid 634b	Bayonet50
Seoul	SAW* 1062 / 1063	47413	COB Holder Hybrid 634b	Bayonet50
Seoul	SAW* 1564 / 1565 / 1566	47422	COB Holder Hybrid 633c	Bayonet50
Seoul	SAW* 22AA / 2296	47512	COB Holder Hybrid 631a	Bayonet50
Seoul	SAW* 2298 / 226A	47512	COB Holder Hybrid 631a	Bayonet50
Tridonic	SLE ADV8 LES 04 / 06	47412	COB Holder Hybrid 634a	Bayonet50
Tridonic	SLE ADV8 LES 09	47412	COB Holder Hybrid 634a	Bayonet50
Tridonic	SLE ADV8 LES 13	47422	COB Holder Hybrid 633c	Bayonet50
Tridonic	SLE ADV8 LES 15	47422	COB Holder Hybrid 633c	Bayonet50
Tridonic	SLE ADV8 LES 17	47528	COB Holder Hybrid 631b	Bayonet50
Tridonic	SLE ADV8 LES 21	47528	COB Holder Hybrid 631b	Bayonet50
Tridonic	SLE SNC8 LES 06	47412	COB Holder Hybrid 634a	Bayonet50
Tridonic	SLE SNC8 LES 09	47412	COB Holder Hybrid 634a	Bayonet50
Tridonic	SLE SNC8 LES 15	47422	COB Holder Hybrid 633c	Bayonet50
VS Lighting	DMS 102 ***W	47412	COB Holder Hybrid 634a	Bayonet50
VS Lighting	DMS 124 ***W	47412	COB Holder Hybrid 634a	Bayonet50
VS Lighting	DMS 125 / 126 / 128 ***W	47420	COB Holder Hybrid 633a	Bayonet50
VS Lighting	DMS 120 ***W	47512	COB Holder Hybrid 631a	Bayonet50

VS Lighting	DMS 12C / 18B ***W	47512	COB Holder Hybrid 631a	Bayonet50
VS Lighting	DMS 1208J	47420	COB Holder Hybrid 633a	Bayonet50
VS Lighting	DMS 1212J / 1812J	47512	COB Holder Hybrid 631a	Bayonet50
VS Lighting	VCA 042	47413	COB Holder Hybrid 634b	Bayonet50
VS Lighting	VCA2 122 / 123 / 124	47413	COB Holder Hybrid 634b	Bayonet50
VS Lighting	VCA2 126 / 128	47422	COB Holder Hybrid 633c	Bayonet50
VS Lighting	VCA2 1211 / 1213	47528	COB Holder Hybrid 631b	Bayonet50
VS Lighting	WU-M-618 DimToWarm	47412	COB Holder Hybrid 634a	Bayonet50
Xicato	XOB 04	47413	COB Holder Hybrid 634b	Bayonet50
Xicato	XOB 06 (B)	47413	COB Holder Hybrid 634b	Bayonet50
Xicato	XOB 09	47412	COB Holder Hybrid 634a	Bayonet50
Xicato	XOB 14	47420	COB Holder Hybrid 633a	Bayonet50
Xicato	XOB 23	47512	COB Holder Hybrid 631a	Bayonet50

Teilumhüllter Halter für folgende COBs / unenclosed holder for the following COBs:			
Hersteller supplier	COB Typ COB Type	Teile-Nr. part no.	Haltervariante variant of holder
Bridgelux	V3 HD / V4 HD Gen 7,8	47928	COB Holder Hybrid 660a Hekla
Bridgelux	V6 HD Gen 7,8	47868	COB Holder Hybrid 634c Hekla
Bridgelux	V9 HD / V11 HD Gen 7,8	47561	COB Holder Hybrid 633d Hekla
Bridgelux	V6 Gen 8,9 (just 2 pads!)	47928	COB Holder Hybrid 660a Hekla
Bridgelux	V8 Gen 7,8,9 (4 pads)	47928	COB Holder Hybrid 660a Hekla
Bridgelux	V10 Gen 7,8,9	47864	COB Holder Hybrid 634b Hekla
Bridgelux	V13 Gen 7,8,9	47560	COB Holder Hybrid 633c Hekla
Bridgelux	V18 Gen 7,8,9	48218	COB Holder Hybrid 639b Hekla XL
Bridgelux	V22 Gen 7,8,9	48220	COB Holder Hybrid 631b Hekla XL
Bridgelux	Vesta DTW 6/9mm Gen 1,2	47892	COB Holder Hybrid 652b Hekla
Bridgelux	Vesta DTW 13/15mm Gen 1,2	48184	COB Holder Hybrid 632b Hekla XL
Bridgelux	Vesta DTW 18mm Gen 1	on request	COB Holder Hybrid 639c Hekla XL
Bridgelux	Vesta Tunable 9mm Gen 2	50063	COB Holder Hybrid 689a Hekla Tunable
Bridgelux	Vesta Tunable 13mm Gen 2	50060	COB Holder Hybrid 692a Hekla Tunable
Citizen	CLU 028 / 02J / 02Q	47505	COB Holder Hybrid 634a Hekla
Citizen	CLU 038 / 03H / 03J / 03Q	47495	COB Holder Hybrid 633a Hekla
Citizen	CLU 048 / 04H / 04J / 04Q	48219	COB Holder Hybrid 631a Hekla XL
Citizen	CLU 7L3 / 7S3	on request	Werkzeug fehlt / Tooling required
Citizen	CLU 702 / 703 / 7A2 / 7A3 / 7B2	47505	COB Holder Hybrid 634a Hekla
Citizen	CLU 712 / 713	47560	COB Holder Hybrid 633c Hekla
Citizen	CLU 723	47560	COB Holder Hybrid 633c Hekla
Citizen	CLU 733	48220	COB Holder Hybrid 631b Hekla XL
CREE	CHA 0304 / 0410 / 0612	47505	COB Holder Hybrid 634a Hekla
CREE	CHA 0825	47495	COB Holder Hybrid 633a Hekla
CREE	CMA 1303 / 1306	47868	COB Holder Hybrid 634c Hekla
CREE	CMA 1516	47510	COB Holder Hybrid 641a Hekla
CREE	CMA 1825 / 1840	47509	COB Holder Hybrid 637a Hekla
CREE	CMA 2550	48180	COB Holder Hybrid 639a Hekla XL
CREE	CMB 1304 / 1306	47868	COB Holder Hybrid 634c Hekla
CREE	CMB 1507 / 1510 / 1516	47510	COB Holder Hybrid 641a Hekla
CREE	CMB 1818 / 1825	47509	COB Holder Hybrid 637a Hekla
CREE	CMB 1840	47872	COB Holder Hybrid 637b Hekla
CREE	CMB 2550	48180	COB Holder Hybrid 639a Hekla XL
CREE	CMT 1407 / 1412 / 1420	47505	COB Holder Hybrid 634a Hekla
CREE	CMT 1922 / 1925 / 1930 / 1945	47560	COB Holder Hybrid 633c Hekla
CREE	CMT 2850 / 2870 / 2890	48220	COB Holder Hybrid 631b Hekla XL
CREE	CMU 1003 / 1006 / 1010 / 1013	47505	COB Holder Hybrid 634a Hekla
CREE	CMU 1516 / 1519 / 1526 / 1532	47495	COB Holder Hybrid 633a Hekla
CREE	CMU 2236 / 2239 / 2258 / 2287	48220	COB Holder Hybrid 631b Hekla XL
CREE	CXB 1304 / 1310	47868	COB Holder Hybrid 634c Hekla



CREE	CXB 1507 / 1512 / 1520	47510	COB Holder Hybrid 641a	Hekla
CREE	CXB 1816 / 1820	47509	COB Holder Hybrid 637a	Hekla
CREE	CXB 1830	47872	COB Holder Hybrid 637b	Hekla
CREE	CXB 2530 / 2540	48180	COB Holder Hybrid 639a	Hekla XL
Edison	2PHE 03 / 06 / 09 / 13	47505	COB Holder Hybrid 634a	Hekla
Edison	2PHE 15 / 18 / 24 / 30	47495	COB Holder Hybrid 633a	Hekla
Edison	2PHE 55 / 60 / 83	48219	COB Holder Hybrid 631a	Hekla XL
Lextar	PB 06 / 09 / 13	47505	COB Holder Hybrid 634a	Hekla
Lextar	PB 16 / 19 / 26	47495	COB Holder Hybrid 633a	Hekla
Lextar	PB 38 / 54	48219	COB Holder Hybrid 631a	Hekla XL
Lumileds	Luxeon 1202s / 1202HD	47889	COB Holder Hybrid 652a	Hekla
Lumileds	Luxeon 1202 / 1203 / 1204HD	47878	COB Holder Hybrid 638b	Hekla
Lumileds	Luxeon 1205HD	47878	COB Holder Hybrid 638b	Hekla
Lumileds	Luxeon 1204 / 1205	48217	COB Holder Hybrid 632a	Hekla XL
Lumileds	Luxeon 1208 / 1210	48217	COB Holder Hybrid 632a	Hekla XL
Lumileds	Luxeon 1211	48220	COB Holder Hybrid 631b	Hekla XL
Lumileds	Luxeon 1213 / 1216 / 1812 / 1816	48220	COB Holder Hybrid 631b	Hekla XL
Lumileds	CS COB L02 / L04	47505	COB Holder Hybrid 634a	Hekla
Lumileds	CS COB L06 / L08 / L10	47495	COB Holder Hybrid 633a	Hekla
Lumileds	CS COB L11 / L13 / L16	48219	COB Holder Hybrid 631a	Hekla XL
Lumileds	CS COB R12 / R18	48219	COB Holder Hybrid 631a	Hekla XL
Lumileds	CX Plus HD S01H4, S0xH6	47868	COB Holder Hybrid 634c	Hekla
Lumileds	CX Plus HD S04H9	47864	COB Holder Hybrid 634b	Hekla
Lumileds	CX Plus S01Fx / S02Fx	47868	COB Holder Hybrid 634c	Hekla
Lumileds	CX Plus M02Fx / M03Fx	47510	COB Holder Hybrid 641a	Hekla
Lumileds	CX Plus L04Fx / L05Fx / L08Fx	47509	COB Holder Hybrid 637a	Hekla
Luminus	CXM-3-xC	47505	COB Holder Hybrid 634a	Hekla
Luminus	CHM-4-BH / CXM-4-xC	47505	COB Holder Hybrid 634a	Hekla
Luminus	CHM-6-BH / CXM-6-xC	47505	COB Holder Hybrid 634a	Hekla
Luminus	CIM/CLM/CXM-9-xC	47505	COB Holder Hybrid 634a	Hekla
Luminus	CHM-9-BH	47495	COB Holder Hybrid 633a	Hekla
Luminus	CXM-11-xC	47495	COB Holder Hybrid 633a	Hekla
Luminus	CGM/CIM/CLM/CXM-14-xC	47495	COB Holder Hybrid 633a	Hekla
Luminus	CXM-18 Gen6	48219	COB Holder Hybrid 631a	Hekla XL
Luminus	CGM/CIM/CLM/CXM-22-xC	48219	COB Holder Hybrid 631a	Hekla XL
Luminus	CDM-6 / CDM-9Gen1 DtW	47892	COB Holder Hybrid 652b	Hekla
Luminus	CDM-9 Gen2 DtW	48184	COB Holder Hybrid 632b	Hekla XL
Luminus	CDM-14/CDM-18 DtW	48184	COB Holder Hybrid 632b	Hekla XL
Luxtech	COB-WD-10-1512	47889	COB Holder Hybrid 652a	Hekla
Luxtech	COB-WD-17-2420	48217	COB Holder Hybrid 632a	Hekla XL
Nichia	NV..S007Z / NF..T012B	47889	COB Holder Hybrid 652a	Hekla
Nichia	NF..S024B / NT..S024B	47889	COB Holder Hybrid 652a	Hekla
Nichia	NJ..S024Z	47889	COB Holder Hybrid 652a	Hekla

Nichia	NV..L016Z / NV..L024Z	47875	COB Holder Hybrid 638a	Hekla
Nichia	NF..L036B / NF..L048B	47875	COB Holder Hybrid 638a	Hekla
Nichia	NF..L060B	47875	COB Holder Hybrid 638a	Hekla
Nichia	NV..J048Z / NF..J108B	48366	COB Holder Hybrid 663a	Hekla XL
Nichia	NF..J130B	48366	COB Holder Hybrid 663a	Hekla XL
Philips	Fortimo SLM12xx .. 1215 G7	47889	COB Holder Hybrid 652a	Hekla
Philips	Fortimo SLM12xx .. 1619 G7	47878	COB Holder Hybrid 638b	Hekla
Philips	Fortimo SLM12xx .. 2024 G7	48217	COB Holder Hybrid 632a	Hekla XL
Philips	Fortimo SLM12xx .. 2828 G7	48220	COB Holder Hybrid 631b	Hekla XL
Philips	Fortimo SLM12xx .. 1313 G7N	47505	COB Holder Hybrid 634a	Hekla
Philips	Fortimo SLM12xx .. 1919 G7N	47495	COB Holder Hybrid 633a	Hekla
Philips	Fortimo SLM12xx .. 2828 G7N	48220	COB Holder Hybrid 631b	Hekla XL
Philips	Fortimo SLM13xx .. 2024 G8 UHE	48217	COB Holder Hybrid 632a	Hekla XL
Philips	Fortimo SLM13xx .. 2828 G8 UHE	48220	COB Holder Hybrid 631b	Hekla XL
Prolight Opto	PASB	47505	COB Holder Hybrid 634a	Hekla
Prolight Opto	PASQ/PAPQ DimToWarm	47505	COB Holder Hybrid 634a	Hekla
Prolight Opto	PDSQ DimToWarm	47892	COB Holder Hybrid 652b	Hekla
Prolight Opto	PDSR DimToWarm	48184	COB Holder Hybrid 632b	Hekla XL
Samsung	LC 010C	47505	COB Holder Hybrid 634a	Hekla
Samsung	LC 020C / 030C / 040C	47560	COB Holder Hybrid 633c	Hekla
Samsung	LC 003D / 006D	47505	COB Holder Hybrid 634a	Hekla
Samsung	LC 009D / 013D	47505	COB Holder Hybrid 634a	Hekla
Samsung	LC 016D / 019D	47560	COB Holder Hybrid 633c	Hekla
Samsung	LC 026D / 033D	47560	COB Holder Hybrid 633c	Hekla
Samsung	LC 040D / 060D / 080D	48220	COB Holder Hybrid 631b	Hekla XL
Seoul	SAW* 0661	47864	COB Holder Hybrid 634b	Hekla
Seoul	SAW* 1062 / 1063	47864	COB Holder Hybrid 634b	Hekla
Seoul	SAW* 1564 / 1565 / 1566	47560	COB Holder Hybrid 633c	Hekla
Seoul	SAW* 22AA / 2296	48219	COB Holder Hybrid 631a	Hekla XL
Seoul	SAW* 2298 / 226A	48219	COB Holder Hybrid 631a	Hekla XL
Tridonic	SLE ADV8 LES 04 / 06	47505	COB Holder Hybrid 634a	Hekla
Tridonic	SLE ADV8 LES 09	47505	COB Holder Hybrid 634a	Hekla
Tridonic	SLE ADV8 LES 13	47560	COB Holder Hybrid 633c	Hekla
Tridonic	SLE ADV8 LES 15	47560	COB Holder Hybrid 633c	Hekla
Tridonic	SLE ADV8 LES 17	48220	COB Holder Hybrid 631b	Hekla XL
Tridonic	SLE ADV8 LES 21	48220	COB Holder Hybrid 631b	Hekla XL
Tridonic	SLE SNC8 LES 06	47505	COB Holder Hybrid 634a	Hekla
Tridonic	SLE SNC8 LES 09	47505	COB Holder Hybrid 634a	Hekla
Tridonic	SLE SNC8 LES 15	47560	COB Holder Hybrid 633c	Hekla
VS Lighting	DMS 102 ***W	47505	COB Holder Hybrid 634a	Hekla
VS Lighting	DMS 124 ***W	47505	COB Holder Hybrid 634a	Hekla
VS Lighting	DMS 125 / 126 / 128 ***W	47495	COB Holder Hybrid 633a	Hekla
VS Lighting	DMS 120 ***W	48219	COB Holder Hybrid 631a	Hekla XL

VS Lighting	DMS 12C / 18B ***W	48219	COB Holder Hybrid 631a	Hekla XL
VS Lighting	DMS 1208J	47495	COB Holder Hybrid 633a	Hekla
VS Lighting	DMS 1212J / 1812J	48219	COB Holder Hybrid 631a	Hekla XL
VS Lighting	VCA 042	47864	COB Holder Hybrid 634b	Hekla
VS Lighting	VCA2 122 / 123 / 124	47864	COB Holder Hybrid 634b	Hekla
VS Lighting	VCA2 126 / 128	47560	COB Holder Hybrid 633c	Hekla
VS Lighting	VCA2 1211 / 1213	48220	COB Holder Hybrid 631b	Hekla XL
VS Lighting	WU-M-618 DimToWarm	47505	COB Holder Hybrid 634a	Hekla
Xicato	XOB 04	47864	COB Holder Hybrid 634b	Hekla
Xicato	XOB 06 (B)	47864	COB Holder Hybrid 634b	Hekla
Xicato	XOB 09	47505	COB Holder Hybrid 634a	Hekla
Xicato	XOB 14	47495	COB Holder Hybrid 633a	Hekla
Xicato	XOB 23	48219	COB Holder Hybrid 631a	Hekla XL




Gehäusotyp: Housing:	Hekla	Größe / Size : 44/50 mm Höhe / Height : 5,5 mm
Beispiele für passende Optiken examples of suitable optics	LEDiL BARBARA-G2, MIRELLA-G2, BROOKE-G2, CARMEN 50/70, ZORYA-C LEDiL ADELIA 50/70/110, ILONA/ILONA ZOOM, RONDA-C, WINNIE-C LEDiL AMY/AMY ZOOM (-C) 50/70, YASMEEN/YASMEEN ZOOM (-C) 50/70	



Gehäusotyp: Housing:		Bayonet35		Größe / Size : 32mm Höhe / Height : 5,3 / 3,6 mm	
Beispiele für passende Optiken examples of suitable optics		LEDiL AMY/ AMY ZOOM (-B) 35/50/70 LEDiL YASMEEN / YASMEEN ZOOM (-B) 35/50/70			
<u>Version 1 Bayonet35/20 : 634x, 652x, 660x, 667x</u>   Spezielle Schraube mit flachem Kopf erforderlich Special flat head screw required e.g. 48279 M3 x 8mm 					
Bemessungsspannung rated voltage		Standard 250V DC optional 450V DC		Zulässige COB Abmessungen Permissible COB dimensions	
Bemessungsstrom rated current		5 A		 siehe Einzeldatenblätter im Online Katalog	
Bemessungstemperatur rated operating temperature		T 120		see data sheets at our web catalogue	
Befestigung fixing		2 Schrauben M3 2 screws M3			
max. Drehmoment max. torque		0,3 Nm			
Material des Halters material of the holder		PBT / Mikanit PBT / Mica			
Kontaktmaterial contactmaterial		CuSn CuSn		 Ausweis- Nr.  File E4729	
Weitere technische Daten und Montagehinweise sind im Technical Guide COB Halterserie 630 enthalten. Further technical details and mounting instructions are part of the Technical Guide COB holder series 630.					

Teilumhüllter Halter für folgende COBs / unenclosed holder for the following COBs:				
Hersteller supplier	COB Typ COB Type	Teile-Nr. part no.	Haltervariante variant of holder	
Bridgelux	V3 HD / V4 HD Gen 7,8	49692	COB Holder Hybrid 660a	Bayonet35/20
Bridgelux	V6 HD Gen 7,8	49046	COB Holder Hybrid 634c	Bayonet35/20
Bridgelux	V6 Gen 8,9 (just 2 pads!)	49692	COB Holder Hybrid 660a	Bayonet35/20
Bridgelux	V8 Gen 7,8,9 (4 pads)	49692	COB Holder Hybrid 660a	Bayonet35/20
Bridgelux	V10 Gen 7,8,9	49047	COB Holder Hybrid 634b	Bayonet35/20
Bridgelux	Vesta DTW 6/9mm Gen 1,2	49040	COB Holder Hybrid 652b	Bayonet35/20
Citizen	CLU 028 / 02J / 02Q	49039	COB Holder Hybrid 634a	Bayonet35/20
Citizen	CLU 7L3 / 7S3	49355	COB Holder Hybrid 667a	Bayonet35/20
Citizen	CLU 702 / 703 / 7A2 / 7A3 / 7B2	49039	COB Holder Hybrid 634a	Bayonet35/20
CREE	CHA 0304 / 0410 / 0612	49039	COB Holder Hybrid 634a	Bayonet35/20
CREE	CMA 1303 / 1306	49046	COB Holder Hybrid 634c	Bayonet35/20
CREE	CMB 1304 / 1306	49046	COB Holder Hybrid 634c	Bayonet35/20
CREE	CMT 1407 / 1412 / 1420	49039	COB Holder Hybrid 634a	Bayonet35/20
CREE	CMU 1003 / 1006 / 1010 / 1013	49039	COB Holder Hybrid 634a	Bayonet35/20
CREE	CXB 1304 / 1310	49046	COB Holder Hybrid 634c	Bayonet35/20
Edison	2PHE 03 / 06 / 09 / 13	49039	COB Holder Hybrid 634a	Bayonet35/20
Lextar	PB 06 / 09 / 13	49039	COB Holder Hybrid 634a	Bayonet35/20
Lumileds	Luxeon 1202s / 1202HD	49049	COB Holder Hybrid 652a	Bayonet35/20
Lumileds	CS COB L02 / L04	49039	COB Holder Hybrid 634a	Bayonet35/20
Lumileds	CX Plus HD S01H4, S0xH6	49046	COB Holder Hybrid 634c	Bayonet35/20
Lumileds	CX Plus HD S04H9	49047	COB Holder Hybrid 634b	Bayonet35/20
Lumileds	CX Plus S01Fx / S02Fx	49046	COB Holder Hybrid 634c	Bayonet35/20
Luminus	CXM-3-xC	49039	COB Holder Hybrid 634a	Bayonet35/20
Luminus	CHM-4-BH / CXM-4-xC	49039	COB Holder Hybrid 634a	Bayonet35/20
Luminus	CHM-6-BH / CXM-6-xC	49039	COB Holder Hybrid 634a	Bayonet35/20
Luminus	CIM/CLM/CXM-9-xC	49039	COB Holder Hybrid 634a	Bayonet35/20
Luminus	CDM-6 / CDM-9Gen1 DtW	49040	COB Holder Hybrid 652b	Bayonet35/20
Luxtech	COB-WD-10-1512	49049	COB Holder Hybrid 652a	Bayonet35/20
Nichia	NV..S007Z / NF..T012B	49049	COB Holder Hybrid 652a	Bayonet35/20
Nichia	NF..S024B / NT..S024B	49049	COB Holder Hybrid 652a	Bayonet35/20
Nichia	NJ..S024Z	49049	COB Holder Hybrid 652a	Bayonet35/20
Philips	Fortimo SLM12xx .. 1215 G7	49049	COB Holder Hybrid 652a	Bayonet35/20
Philips	Fortimo SLM12xx .. 1313 G7N	49039	COB Holder Hybrid 634a	Bayonet35/20
Prolight Opto	PASB	49039	COB Holder Hybrid 634a	Bayonet35/20
Prolight Opto	PASQ/PAPQ DimToWarm	49039	COB Holder Hybrid 634a	Bayonet35/20
Prolight Opto	PDSQ DimToWarm	49040	COB Holder Hybrid 652b	Bayonet35/20
Samsung	LC 010C	49039	COB Holder Hybrid 634a	Bayonet35/20
Samsung	LC 003D / 006D	49039	COB Holder Hybrid 634a	Bayonet35/20
Samsung	LC 009D / 013D	49039	COB Holder Hybrid 634a	Bayonet35/20
Seoul	SAW* 0661	49047	COB Holder Hybrid 634b	Bayonet35/20

Seoul	SAW* 1062 / 1063	49047	COB Holder Hybrid 634b	Bayonet35/20
Tridonic	SLE ADV8 LES 04 / 06	49039	COB Holder Hybrid 634a	Bayonet35/20
Tridonic	SLE ADV8 LES 09	49039	COB Holder Hybrid 634a	Bayonet35/20
Tridonic	SLE SNC8 LES 06	49039	COB Holder Hybrid 634a	Bayonet35/20
Tridonic	SLE SNC8 LES 09	49039	COB Holder Hybrid 634a	Bayonet35/20
VS Lighting	DMS 102 ***W	49039	COB Holder Hybrid 634a	Bayonet35/20
VS Lighting	DMS 124 ***W	49039	COB Holder Hybrid 634a	Bayonet35/20
VS Lighting	VCA 042	49047	COB Holder Hybrid 634b	Bayonet35/20
VS Lighting	VCA2 122 / 123 / 124	49047	COB Holder Hybrid 634b	Bayonet35/20
VS Lighting	WU-M-618 DimToWarm	49039	COB Holder Hybrid 634a	Bayonet35/20
Xicato	XOB 04	49047	COB Holder Hybrid 634b	Bayonet35/20
Xicato	XOB 06 (B)	49047	COB Holder Hybrid 634b	Bayonet35/20
Xicato	XOB 09	49039	COB Holder Hybrid 634a	Bayonet35/20

Gehäusetypp: Housing:		3Hook		Größe / Size : 50 mm Höhe / Height : 5,9 mm	
Beispiele für passende Optiken examples of suitable optics		LEDiL ANGELA, ANGELINA, ANGELETTE LEDiL MOLLY, RONDA (HOLDER A)			
Version 1: 633x, 634x, 637x, 638x, 641x, 652x, 660x					
					
Version 2: 631x, 632x, 639x, 663x					
					
Bemessungsspannung rated voltage		Standard 250V DC optional 450V DC		Zulässige COB Abmessungen Permissible COB dimensions	
Bemessungsstrom rated current		5 A		 siehe Einzeldatenblätter im Online Katalog see data sheets at our web catalogue	
Bemessungstemperatur rated operating temperature		T 120			
Befestigung fixing		2 Schrauben M3 2 screws M3		Zertifikate / certificates  Ausweis-Nr.  File E4729	
max. Drehmoment max. torque		0,5 Nm			
Material des Halters material of the holder		PBT / Mikanit PBT / Mica			
Kontaktmaterial contactmaterial		CuSn CuSn			
Weitere technische Daten und Montagehinweise sind im Technical Guide COB Halterserie 630 enthalten. Further technical details and mounting instructions are part of the Technical Guide COB holder series 630 .					

Teilumhüllter Halter für folgende COBs / unenclosed holder for the following COBs:			
Hersteller supplier	COB Typ COB Type	Teile-Nr. part no.	Haltervariante variant of holder
Bridgelux	V3 HD / V4 HD Gen 7,8	47957	COB Holder Hybrid 660a 3Hook
Bridgelux	V6 HD Gen 7,8	47867	COB Holder Hybrid 634c 3Hook
Bridgelux	V9 HD / V11 HD Gen 7,8	47565	COB Holder Hybrid 633d 3Hook
Bridgelux	V6 Gen 8,9 (just 2 pads!)	47957	COB Holder Hybrid 660a 3Hook
Bridgelux	V8 Gen 7,8,9 (4 pads)	47957	COB Holder Hybrid 660a 3Hook
Bridgelux	V10 Gen 7,8,9	47863	COB Holder Hybrid 634b 3Hook
Bridgelux	V13 Gen 7,8,9	47564	COB Holder Hybrid 633c 3Hook
Bridgelux	V18 Gen 7,8,9	47882	COB Holder Hybrid 639b 3Hook
Bridgelux	V22 Gen 7,8,9	47583	COB Holder Hybrid 631b 3Hook
Bridgelux	Vesta DTW 6/9mm Gen 1,2	47891	COB Holder Hybrid 652b 3Hook
Bridgelux	Vesta DTW 13/15mm Gen 1,2	47858	COB Holder Hybrid 632b 3Hook
Bridgelux	Vesta DTW 18mm Gen 1	on request	COB Holder Hybrid 639c 3Hook
Bridgelux	Vesta Tunable 9mm Gen 2	on request	Werkzeug fehlt / Tooling required
Bridgelux	Vesta Tunable 13mm Gen 2	on request	Werkzeug fehlt / Tooling required
Citizen	CLU 028 / 02J / 02Q	47441	COB Holder Hybrid 634a 3Hook
Citizen	CLU 038 / 03H / 03J / 03Q	47562	COB Holder Hybrid 633a 3Hook
Citizen	CLU 048 / 04H / 04J / 04Q	47582	COB Holder Hybrid 631a 3Hook
Citizen	CLU 7L3 / 7S3	on request	Werkzeug fehlt / Tooling required
Citizen	CLU 702 / 703 / 7A2 / 7A3 / 7B2	47441	COB Holder Hybrid 634a 3Hook
Citizen	CLU 712 / 713	47564	COB Holder Hybrid 633c 3Hook
Citizen	CLU 723	47564	COB Holder Hybrid 633c 3Hook
Citizen	CLU 733	47583	COB Holder Hybrid 631b 3Hook
CREE	CHA 0304 / 0410 / 0612	47441	COB Holder Hybrid 634a 3Hook
CREE	CHA 0825	47562	COB Holder Hybrid 633a 3Hook
CREE	CMA 1303 / 1306	47867	COB Holder Hybrid 634c 3Hook
CREE	CMA 1516	47460	COB Holder Hybrid 641a 3Hook
CREE	CMA 1825 / 1840	47472	COB Holder Hybrid 637a 3Hook
CREE	CMA 2550	47585	COB Holder Hybrid 639a 3Hook
CREE	CMB 1304 / 1306	47867	COB Holder Hybrid 634c 3Hook
CREE	CMB 1507 / 1510 / 1516	47460	COB Holder Hybrid 641a 3Hook
CREE	CMB 1818 / 1825	47472	COB Holder Hybrid 637a 3Hook
CREE	CMB 1840	47871	COB Holder Hybrid 637b 3Hook
CREE	CMB 2550	47585	COB Holder Hybrid 639a 3Hook
CREE	CMT 1407 / 1412 / 1420	47441	COB Holder Hybrid 634a 3Hook
CREE	CMT 1922 / 1925 / 1930 / 1945	47564	COB Holder Hybrid 633c 3Hook
CREE	CMT 2850 / 2870 / 2890	47583	COB Holder Hybrid 631b 3Hook
CREE	CMU 1003 / 1006 / 1010 / 1013	47441	COB Holder Hybrid 634a 3Hook
CREE	CMU 1516 / 1519 / 1526 / 1532	47562	COB Holder Hybrid 633a 3Hook
CREE	CMU 2236 / 2239 / 2258 / 2287	47583	COB Holder Hybrid 631b 3Hook
CREE	CXB 1304 / 1310	47867	COB Holder Hybrid 634c 3Hook

CREE	CXB 1507 / 1512 / 1520	47460	COB Holder Hybrid 641a	3Hook
CREE	CXB 1816 / 1820	47472	COB Holder Hybrid 637a	3Hook
CREE	CXB 1830	47871	COB Holder Hybrid 637b	3Hook
CREE	CXB 2530 / 2540	47585	COB Holder Hybrid 639a	3Hook
Edison	2PHE 03 / 06 / 09 / 13	47441	COB Holder Hybrid 634a	3Hook
Edison	2PHE 15 / 18 / 24 / 30	47562	COB Holder Hybrid 633a	3Hook
Edison	2PHE 55 / 60 / 83	47582	COB Holder Hybrid 631a	3Hook
Lextar	PB 06 / 09 / 13	47441	COB Holder Hybrid 634a	3Hook
Lextar	PB 16 / 19 / 26	47562	COB Holder Hybrid 633a	3Hook
Lextar	PB 38 / 54	47582	COB Holder Hybrid 631a	3Hook
Lumileds	Luxeon 1202s / 1202HD	47456	COB Holder Hybrid 652a	3Hook
Lumileds	Luxeon 1202 / 1203 / 1204HD	47877	COB Holder Hybrid 638b	3Hook
Lumileds	Luxeon 1205HD	47877	COB Holder Hybrid 638b	3Hook
Lumileds	Luxeon 1204 / 1205	47580	COB Holder Hybrid 632a	3Hook
Lumileds	Luxeon 1208 / 1210	47580	COB Holder Hybrid 632a	3Hook
Lumileds	Luxeon 1211	47583	COB Holder Hybrid 631b	3Hook
Lumileds	Luxeon 1213 / 1216 / 1812 / 1816	47583	COB Holder Hybrid 631b	3Hook
Lumileds	CS COB L02 / L04	47441	COB Holder Hybrid 634a	3Hook
Lumileds	CS COB L06 / L08 / L10	47562	COB Holder Hybrid 633a	3Hook
Lumileds	CS COB L11 / L13 / L16	47582	COB Holder Hybrid 631a	3Hook
Lumileds	CS COB R12 / R18	47582	COB Holder Hybrid 631a	3Hook
Lumileds	CX Plus HD S01H4, S0xH6	47867	COB Holder Hybrid 634c	3Hook
Lumileds	CX Plus HD S04H9	47863	COB Holder Hybrid 634b	3Hook
Lumileds	CX Plus S01Fx / S02Fx	47867	COB Holder Hybrid 634c	3Hook
Lumileds	CX Plus M02Fx / M03Fx	47460	COB Holder Hybrid 641a	3Hook
Lumileds	CX Plus L04Fx / L05Fx / L08Fx	47472	COB Holder Hybrid 637a	3Hook
Luminus	CXM-3-xC	47441	COB Holder Hybrid 634a	3Hook
Luminus	CHM-4-BH / CXM-4-xC	47441	COB Holder Hybrid 634a	3Hook
Luminus	CHM-6-BH / CXM-6-xC	47441	COB Holder Hybrid 634a	3Hook
Luminus	CIM/CLM/CXM-9-xC	47441	COB Holder Hybrid 634a	3Hook
Luminus	CHM-9-BH	47562	COB Holder Hybrid 633a	3Hook
Luminus	CXM-11-xC	47562	COB Holder Hybrid 633a	3Hook
Luminus	CGM/CIM/CLM/CXM-14-xC	47562	COB Holder Hybrid 633a	3Hook
Luminus	CXM-18 Gen6	47582	COB Holder Hybrid 631a	3Hook
Luminus	CGM/CIM/CLM/CXM-22-xC	47582	COB Holder Hybrid 631a	3Hook
Luminus	CDM-6 / CDM-9Gen1 DtW	47891	COB Holder Hybrid 652b	3Hook
Luminus	CDM-9 Gen2 DtW	47858	COB Holder Hybrid 632b	3Hook
Luminus	CDM-14/CDM-18 DtW	47858	COB Holder Hybrid 632b	3Hook
Luxtech	COB-WD-10-1512	47456	COB Holder Hybrid 652a	3Hook
Luxtech	COB-WD-17-2420	47580	COB Holder Hybrid 632a	3Hook
Nichia	NV..S007Z / NF..T012B	47456	COB Holder Hybrid 652a	3Hook
Nichia	NF..S024B / NT..S024B	47456	COB Holder Hybrid 652a	3Hook
Nichia	NJ..S024Z	47456	COB Holder Hybrid 652a	3Hook

Nichia	NV..L016Z / NV..L024Z	47466	COB Holder Hybrid 638a	3Hook
Nichia	NF..L036B / NF..L048B	47466	COB Holder Hybrid 638a	3Hook
Nichia	NF..L060B	47466	COB Holder Hybrid 638a	3Hook
Nichia	NV..J048Z / NF..J108B	47947	COB Holder Hybrid 663a	3Hook
Nichia	NF..J130B	47947	COB Holder Hybrid 663a	3Hook
Philips	Fortimo SLM12xx .. 1215 G7	47456	COB Holder Hybrid 652a	3Hook
Philips	Fortimo SLM12xx .. 1619 G7	47877	COB Holder Hybrid 638b	3Hook
Philips	Fortimo SLM12xx .. 2024 G7	47580	COB Holder Hybrid 632a	3Hook
Philips	Fortimo SLM12xx .. 2828 G7	47583	COB Holder Hybrid 631b	3Hook
Philips	Fortimo SLM12xx .. 1313 G7N	47441	COB Holder Hybrid 634a	3Hook
Philips	Fortimo SLM12xx .. 1919 G7N	47562	COB Holder Hybrid 633a	3Hook
Philips	Fortimo SLM12xx .. 2828 G7N	47583	COB Holder Hybrid 631b	3Hook
Philips	Fortimo SLM13xx .. 2024 G8 UHE	47580	COB Holder Hybrid 632a	3Hook
Philips	Fortimo SLM13xx .. 2828 G8 UHE	47583	COB Holder Hybrid 631b	3Hook
Prolight Opto	PASB	47441	COB Holder Hybrid 634a	3Hook
Prolight Opto	PASQ/PAPQ DimToWarm	47441	COB Holder Hybrid 634a	3Hook
Prolight Opto	PDSQ DimToWarm	47891	COB Holder Hybrid 652b	3Hook
Prolight Opto	PDSR DimToWarm	47858	COB Holder Hybrid 632b	3Hook
Samsung	LC 010C	47441	COB Holder Hybrid 634a	3Hook
Samsung	LC 020C / 030C / 040C	47564	COB Holder Hybrid 633c	3Hook
Samsung	LC 003D / 006D	47441	COB Holder Hybrid 634a	3Hook
Samsung	LC 009D / 013D	47441	COB Holder Hybrid 634a	3Hook
Samsung	LC 016D / 019D	47564	COB Holder Hybrid 633c	3Hook
Samsung	LC 026D / 033D	47564	COB Holder Hybrid 633c	3Hook
Samsung	LC 040D / 060D / 080D	47583	COB Holder Hybrid 631b	3Hook
Seoul	SAW* 0661	47863	COB Holder Hybrid 634b	3Hook
Seoul	SAW* 1062 / 1063	47863	COB Holder Hybrid 634b	3Hook
Seoul	SAW* 1564 / 1565 / 1566	47564	COB Holder Hybrid 633c	3Hook
Seoul	SAW* 22AA / 2296	47582	COB Holder Hybrid 631a	3Hook
Seoul	SAW* 2298 / 226A	47582	COB Holder Hybrid 631a	3Hook
Tridonic	SLE ADV8 LES 04 / 06	47441	COB Holder Hybrid 634a	3Hook
Tridonic	SLE ADV8 LES 09	47441	COB Holder Hybrid 634a	3Hook
Tridonic	SLE ADV8 LES 13	47564	COB Holder Hybrid 633c	3Hook
Tridonic	SLE ADV8 LES 15	47564	COB Holder Hybrid 633c	3Hook
Tridonic	SLE ADV8 LES 17	47583	COB Holder Hybrid 631b	3Hook
Tridonic	SLE ADV8 LES 21	47583	COB Holder Hybrid 631b	3Hook
Tridonic	SLE SNC8 LES 06	47441	COB Holder Hybrid 634a	3Hook
Tridonic	SLE SNC8 LES 09	47441	COB Holder Hybrid 634a	3Hook
Tridonic	SLE SNC8 LES 15	47564	COB Holder Hybrid 633c	3Hook
VS Lighting	DMS 102 ***W	47441	COB Holder Hybrid 634a	3Hook
VS Lighting	DMS 124 ***W	47441	COB Holder Hybrid 634a	3Hook
VS Lighting	DMS 125 / 126 / 128 ***W	47562	COB Holder Hybrid 633a	3Hook
VS Lighting	DMS 120 ***W	47582	COB Holder Hybrid 631a	3Hook

VS Lighting	DMS 12C / 18B ***W	47582	COB Holder Hybrid 631a	3Hook
VS Lighting	DMS 1208J	47562	COB Holder Hybrid 633a	3Hook
VS Lighting	DMS 1212J / 1812J	47582	COB Holder Hybrid 631a	3Hook
VS Lighting	VCA 042	47863	COB Holder Hybrid 634b	3Hook
VS Lighting	VCA2 122 / 123 / 124	47863	COB Holder Hybrid 634b	3Hook
VS Lighting	VCA2 126 / 128	47564	COB Holder Hybrid 633c	3Hook
VS Lighting	VCA2 1211 / 1213	47583	COB Holder Hybrid 631b	3Hook
VS Lighting	WU-M-618 DimToWarm	47441	COB Holder Hybrid 634a	3Hook
Xicato	XOB 04	47863	COB Holder Hybrid 634b	3Hook
Xicato	XOB 06 (B)	47863	COB Holder Hybrid 634b	3Hook
Xicato	XOB 09	47441	COB Holder Hybrid 634a	3Hook
Xicato	XOB 14	47562	COB Holder Hybrid 633a	3Hook
Xicato	XOB 23	47582	COB Holder Hybrid 631a	3Hook

Teilumhüllter Halter für folgende COBs / unenclosed holder for the following COBs:			
Hersteller supplier	COB Typ COB Type	Teile-Nr. part no.	Haltervariante variant of holder
Bridgelux	V3 HD / V4 HD Gen 7,8	47956	COB Holder Hybrid 660a Lena
Bridgelux	V6 HD Gen 7,8	47869	COB Holder Hybrid 634c Lena
Bridgelux	V9 HD / V11 HD Gen 7,8	47577	COB Holder Hybrid 633d Lena
Bridgelux	V6 Gen 8,9 (just 2 pads!)	47956	COB Holder Hybrid 660a Lena
Bridgelux	V8 Gen 7,8,9 (4 pads)	47956	COB Holder Hybrid 660a Lena
Bridgelux	V10 Gen 7,8,9	47865	COB Holder Hybrid 634b Lena
Bridgelux	V13 Gen 7,8,9	47576	COB Holder Hybrid 633c Lena
Bridgelux	V18 Gen 7,8,9	47883	COB Holder Hybrid 639b Lena
Bridgelux	V22 Gen 7,8,9	47855	COB Holder Hybrid 631b Lena
Bridgelux	Vesta DTW 6/9mm Gen 1,2	47893	COB Holder Hybrid 652b Lena
Bridgelux	Vesta DTW 13/15mm Gen 1,2	47859	COB Holder Hybrid 632b Lena
Bridgelux	Vesta DTW 18mm Gen 1	on request	COB Holder Hybrid 639c Lena
Bridgelux	Vesta Tunable 9mm Gen 2	on request	Werkzeug fehlt / Tooling required
Bridgelux	Vesta Tunable 13mm Gen 2	on request	Werkzeug fehlt / Tooling required
Citizen	CLU 028 / 02J / 02Q	47444	COB Holder Hybrid 634a Lena
Citizen	CLU 038 / 03H / 03J / 03Q	47566	COB Holder Hybrid 633a Lena
Citizen	CLU 048 / 04H / 04J / 04Q	47446	COB Holder Hybrid 631a Lena
Citizen	CLU 7L3 / 7S3	on request	Werkzeug fehlt / Tooling required
Citizen	CLU 702 / 703 / 7A2 / 7A3 / 7B2	47444	COB Holder Hybrid 634a Lena
Citizen	CLU 712 / 713	47576	COB Holder Hybrid 633c Lena
Citizen	CLU 723	47576	COB Holder Hybrid 633c Lena
Citizen	CLU 733	47855	COB Holder Hybrid 631b Lena
CREE	CHA 0304 / 0410 / 0612	47444	COB Holder Hybrid 634a Lena
CREE	CHA 0825	47566	COB Holder Hybrid 633a Lena
CREE	CMA 1303 / 1306	47869	COB Holder Hybrid 634c Lena
CREE	CMA 1516	47461	COB Holder Hybrid 641a Lena
CREE	CMA 1825 / 1840	47473	COB Holder Hybrid 637a Lena
CREE	CMA 2550	47447	COB Holder Hybrid 639a Lena
CREE	CMB 1304 / 1306	47869	COB Holder Hybrid 634c Lena
CREE	CMB 1507 / 1510 / 1516	47461	COB Holder Hybrid 641a Lena
CREE	CMB 1818 / 1825	47473	COB Holder Hybrid 637a Lena
CREE	CMB 1840	47873	COB Holder Hybrid 637b Lena
CREE	CMB 2550	47447	COB Holder Hybrid 639a Lena
CREE	CMT 1407 / 1412 / 1420	47444	COB Holder Hybrid 634a Lena
CREE	CMT 1922 / 1925 / 1930 / 1945	47576	COB Holder Hybrid 633c Lena
CREE	CMT 2850 / 2870 / 2890	47855	COB Holder Hybrid 631b Lena
CREE	CMU 1003 / 1006 / 1010 / 1013	47444	COB Holder Hybrid 634a Lena
CREE	CMU 1516 / 1519 / 1526 / 1532	47566	COB Holder Hybrid 633a Lena
CREE	CMU 2236 / 2239 / 2258 / 2287	47855	COB Holder Hybrid 631b Lena
CREE	CXB 1304 / 1310	47869	COB Holder Hybrid 634c Lena

CREE	CXB 1507 / 1512 / 1520	47461	COB Holder Hybrid 641a	Lena
CREE	CXB 1816 / 1820	47473	COB Holder Hybrid 637a	Lena
CREE	CXB 1830	47873	COB Holder Hybrid 637b	Lena
CREE	CXB 2530 / 2540	47447	COB Holder Hybrid 639a	Lena
Edison	2PHE 03 / 06 / 09 / 13	47444	COB Holder Hybrid 634a	Lena
Edison	2PHE 15 / 18 / 24 / 30	47566	COB Holder Hybrid 633a	Lena
Edison	2PHE 55 / 60 / 83	47446	COB Holder Hybrid 631a	Lena
Lextar	PB 06 / 09 / 13	47444	COB Holder Hybrid 634a	Lena
Lextar	PB 16 / 19 / 26	47566	COB Holder Hybrid 633a	Lena
Lextar	PB 38 / 54	47446	COB Holder Hybrid 631a	Lena
Lumileds	Luxeon 1202s / 1202HD	47457	COB Holder Hybrid 652a	Lena
Lumileds	Luxeon 1202 / 1203 / 1204HD	47879	COB Holder Hybrid 638b	Lena
Lumileds	Luxeon 1205HD	47879	COB Holder Hybrid 638b	Lena
Lumileds	Luxeon 1204 / 1205	47450	COB Holder Hybrid 632a	Lena
Lumileds	Luxeon 1208 / 1210	47450	COB Holder Hybrid 632a	Lena
Lumileds	Luxeon 1211	47855	COB Holder Hybrid 631b	Lena
Lumileds	Luxeon 1213 / 1216 / 1812 / 1816	47855	COB Holder Hybrid 631b	Lena
Lumileds	CS COB L02 / L04	47444	COB Holder Hybrid 634a	Lena
Lumileds	CS COB L06 / L08 / L10	47566	COB Holder Hybrid 633a	Lena
Lumileds	CS COB L11 / L13 / L16	47446	COB Holder Hybrid 631a	Lena
Lumileds	CS COB R12 / R18	47446	COB Holder Hybrid 631a	Lena
Lumileds	CX Plus HD S01H4, S0xH6	47869	COB Holder Hybrid 634c	Lena
Lumileds	CX Plus HD S04H9	47865	COB Holder Hybrid 634b	Lena
Lumileds	CX Plus S01Fx / S02Fx	47869	COB Holder Hybrid 634c	Lena
Lumileds	CX Plus M02Fx / M03Fx	47461	COB Holder Hybrid 641a	Lena
Lumileds	CX Plus L04Fx / L05Fx / L08Fx	47473	COB Holder Hybrid 637a	Lena
Luminus	CXM-3-xC	47444	COB Holder Hybrid 634a	Lena
Luminus	CHM-4-BH / CXM-4-xC	47444	COB Holder Hybrid 634a	Lena
Luminus	CHM-6-BH / CXM-6-xC	47444	COB Holder Hybrid 634a	Lena
Luminus	CIM/CLM/CXM-9-xC	47444	COB Holder Hybrid 634a	Lena
Luminus	CHM-9-BH	47566	COB Holder Hybrid 633a	Lena
Luminus	CXM-11-xC	47566	COB Holder Hybrid 633a	Lena
Luminus	CGM/CIM/CLM/CXM-14-xC	47566	COB Holder Hybrid 633a	Lena
Luminus	CXM-18 Gen6	47446	COB Holder Hybrid 631a	Lena
Luminus	CGM/CIM/CLM/CXM-22-xC	47446	COB Holder Hybrid 631a	Lena
Luminus	CDM-6 / CDM-9Gen1 DtW	47893	COB Holder Hybrid 652b	Lena
Luminus	CDM-9 Gen2 DtW	47859	COB Holder Hybrid 632b	Lena
Luminus	CDM-14/CDM-18 DtW	47859	COB Holder Hybrid 632b	Lena
Luxtech	COB-WD-10-1512	47457	COB Holder Hybrid 652a	Lena
Luxtech	COB-WD-17-2420	47450	COB Holder Hybrid 632a	Lena
Nichia	NV..S007Z / NF..T012B	47457	COB Holder Hybrid 652a	Lena
Nichia	NF..S024B / NT..S024B	47457	COB Holder Hybrid 652a	Lena
Nichia	NJ..S024Z	47457	COB Holder Hybrid 652a	Lena

Nichia	NV..L016Z / NV..L024Z	47467	COB Holder Hybrid 638a	Lena
Nichia	NF..L036B / NF..L048B	47467	COB Holder Hybrid 638a	Lena
Nichia	NF..L060B	47467	COB Holder Hybrid 638a	Lena
Nichia	NV..J048Z / NF..J108B	47951	COB Holder Hybrid 663a	Lena
Nichia	NF..J130B	47951	COB Holder Hybrid 663a	Lena
Philips	Fortimo SLM12xx .. 1215 G7	47457	COB Holder Hybrid 652a	Lena
Philips	Fortimo SLM12xx .. 1619 G7	47879	COB Holder Hybrid 638b	Lena
Philips	Fortimo SLM12xx .. 2024 G7	47450	COB Holder Hybrid 632a	Lena
Philips	Fortimo SLM12xx .. 2828 G7	47855	COB Holder Hybrid 631b	Lena
Philips	Fortimo SLM12xx .. 1313 G7N	47444	COB Holder Hybrid 634a	Lena
Philips	Fortimo SLM12xx .. 1919 G7N	47566	COB Holder Hybrid 633a	Lena
Philips	Fortimo SLM12xx .. 2828 G7N	47855	COB Holder Hybrid 631b	Lena
Philips	Fortimo SLM13xx .. 2024 G8 UHE	47450	COB Holder Hybrid 632a	Lena
Philips	Fortimo SLM13xx .. 2828 G8 UHE	47855	COB Holder Hybrid 631b	Lena
Prolight Opto	PASB	47444	COB Holder Hybrid 634a	Lena
Prolight Opto	PASQ/PAPQ DimToWarm	47444	COB Holder Hybrid 634a	Lena
Prolight Opto	PDSQ DimToWarm	47893	COB Holder Hybrid 652b	Lena
Prolight Opto	PDSR DimToWarm	47859	COB Holder Hybrid 632b	Lena
Samsung	LC 010C	47444	COB Holder Hybrid 634a	Lena
Samsung	LC 020C / 030C / 040C	47576	COB Holder Hybrid 633c	Lena
Samsung	LC 003D / 006D	47444	COB Holder Hybrid 634a	Lena
Samsung	LC 009D / 013D	47444	COB Holder Hybrid 634a	Lena
Samsung	LC 016D / 019D	47576	COB Holder Hybrid 633c	Lena
Samsung	LC 026D / 033D	47576	COB Holder Hybrid 633c	Lena
Samsung	LC 040D / 060D / 080D	47855	COB Holder Hybrid 631b	Lena
Seoul	SAW* 0661	47865	COB Holder Hybrid 634b	Lena
Seoul	SAW* 1062 / 1063	47865	COB Holder Hybrid 634b	Lena
Seoul	SAW* 1564 / 1565 / 1566	47576	COB Holder Hybrid 633c	Lena
Seoul	SAW* 22AA / 2296	47446	COB Holder Hybrid 631a	Lena
Seoul	SAW* 2298 / 226A	47446	COB Holder Hybrid 631a	Lena
Tridonic	SLE ADV8 LES 04 / 06	47444	COB Holder Hybrid 634a	Lena
Tridonic	SLE ADV8 LES 09	47444	COB Holder Hybrid 634a	Lena
Tridonic	SLE ADV8 LES 13	47576	COB Holder Hybrid 633c	Lena
Tridonic	SLE ADV8 LES 15	47576	COB Holder Hybrid 633c	Lena
Tridonic	SLE ADV8 LES 17	47855	COB Holder Hybrid 631b	Lena
Tridonic	SLE ADV8 LES 21	47855	COB Holder Hybrid 631b	Lena
Tridonic	SLE SNC8 LES 06	47444	COB Holder Hybrid 634a	Lena
Tridonic	SLE SNC8 LES 09	47444	COB Holder Hybrid 634a	Lena
Tridonic	SLE SNC8 LES 15	47576	COB Holder Hybrid 633c	Lena
VS Lighting	DMS 102 ***W	47444	COB Holder Hybrid 634a	Lena
VS Lighting	DMS 124 ***W	47444	COB Holder Hybrid 634a	Lena
VS Lighting	DMS 125 / 126 / 128 ***W	47566	COB Holder Hybrid 633a	Lena
VS Lighting	DMS 120 ***W	47446	COB Holder Hybrid 631a	Lena

VS Lighting	DMS 12C / 18B ***W	47446	COB Holder Hybrid 631a	Lena
VS Lighting	DMS 1208J	47566	COB Holder Hybrid 633a	Lena
VS Lighting	DMS 1212J / 1812J	47446	COB Holder Hybrid 631a	Lena
VS Lighting	VCA 042	47865	COB Holder Hybrid 634b	Lena
VS Lighting	VCA2 122 / 123 / 124	47865	COB Holder Hybrid 634b	Lena
VS Lighting	VCA2 126 / 128	47576	COB Holder Hybrid 633c	Lena
VS Lighting	VCA2 1211 / 1213	47855	COB Holder Hybrid 631b	Lena
VS Lighting	WU-M-618 DimToWarm	47444	COB Holder Hybrid 634a	Lena
Xicato	XOB 04	47865	COB Holder Hybrid 634b	Lena
Xicato	XOB 06 (B)	47865	COB Holder Hybrid 634b	Lena
Xicato	XOB 09	47444	COB Holder Hybrid 634a	Lena
Xicato	XOB 14	47566	COB Holder Hybrid 633a	Lena
Xicato	XOB 23	47446	COB Holder Hybrid 631a	Lena

Basishalter für Anwendungen, in denen keine besondere Anbindung zur Optik erforderlich ist.

Basic holders for applications without specific connection requirements to the optical system

Weitere Details unter
More details at

www.bender-wirth.de

Zertifikate / certificates

LED Halter B+W
LED Holder B+W

4xx / Typ xx


Ausweis-Nr.
40041342



File
E472943



4xx / Typ xx



Mögliche Halter / COB Kombinationen / Holder / COB combinations

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Abmessungen Dimensions
Bridgelux	V3 HD / V4 HD Gen 7,8	460 Typ 1	29 x 27 / 21
Bridgelux	V6 HD Gen 7,8	464 Typ 1	Ø 35 / 25
Bridgelux	V9 HD / V11 HD Gen 7,8	496 Typ Z1	Ø 49 / 35
Bridgelux	V6 Gen 8,9 (just 2 pads!)	460 Typ 1	29 x 27 / 21
Bridgelux	V8 Gen 7,8,9 (4 pads)	460 Typ 1	29 x 27 / 21
Bridgelux	V10 Gen 7,8,9	486 Typ Z4	Ø 35 / 25
Bridgelux	V13 Gen 7,8,9	477 Typ 1	Ø 40 / 30
Bridgelux	V15 Gen 7,8,9	456 Typ L1-4	Ø 36,2 / 26,9
Bridgelux	V18 Gen 7,8,9	462 Typ 1	Ø 50 / 35
Bridgelux	V22 Gen 7,8,9	431 Typ 2	Ø 50 / 35
Bridgelux	Vesta DTW 6/9mm Gen 1,2	490 Typ L8	Ø 44 / 35
Bridgelux	Vesta DTW 13/15mm Gen 1,2	491 Typ L8	Ø 44 / 35
Bridgelux	Vesta DTW 18mm Gen 1	505 Typ Z1	Ø 49 / 35
Bridgelux	Vesta DTW 29mm Gen 1	506 Typ 1	Ø 55 / 43
Bridgelux	Vesta Tunable 6mm Gen 2	504 Typ L8	Ø 44 / 35
Bridgelux	Vesta Tunable 9mm Gen 2	489 Typ L8	Ø 44 / 35

Mögliche Halter / COB Kombinationen / Holder / COB combinations

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Abmessungen Dimensions
Bridgelux	Vesta Tunable 13mm Gen 2	492 Typ L8	Ø 44 / 35
Bridgelux	Vesta Tunable 15mm Gen 2	482 Typ L8	Ø 44 / 35
Bridgelux	Vesta Tunable 18mm Gen 2	483 Typ Z1	Ø 49 / 35
Bridgelux	Vesta Tunable 22mm Gen 2	494 Typ Z1	Ø 49 / 35
Bridgelux	Vesta Tunable 29mm Gen 2	503 Typ 1	Ø 55 / 43
Citizen	CLU 028 / 02J / 02Q	434 Typ 2	Ø 35 / 25
Citizen	CLU 038 / 03H / 03J / 03Q	433 Typ 2	Ø 40 / 30
Citizen	CLU 048 / 04H / 04J / 04Q	431 Typ 2	Ø 50 / 35
Citizen	CLU 058 / 05Q ..1825	458 Typ 1	Ø 65 / 50
Citizen	CLU 058 / 05H / 05Q ..3618	458 Typ 1 HV	Ø 65 / 50
Citizen	CLU 550 / 551	476 Typ 1 HV	Ø 65 / 50
Citizen	CLU 7L3 / 7S3	467 Typ 1	Ø 27 / 17
Citizen	CLU 7R3	485 Typ 1	Ø 27 / 17
Citizen	CLU 702 / 703 / 7A2 / 7A3 / 7B2	434 Typ 2	Ø 35 / 25
Citizen	CLU 712 / 713	477 Typ 2	Ø 40 / 30
Citizen	CLU 723	477 Typ 2	Ø 40 / 30
Citizen	CLU 733	471 Typ 1	Ø 50 / 35
Citizen	LCN-C01B2 / C02B2 Tunable	481 Typ Z1	Ø 49 / 35
Citizen	LCN-C04B2 / C05B2 Tunable	481 Typ Z1	Ø 49 / 35
Citizen	LCN-C07A2 Tunable	507 Typ 1	
Citizen	LCN-C08A2 / C09A2 Tunable	508 Typ 1	
CREE	CHA 0304 / 0410 / 0612	434 Typ 2	Ø 35 / 25
CREE	CHA 0825	433 Typ 2	Ø 40 / 30
CREE	CMA 1303 / 1306	448 Typ 1	Ø 30 / 20
CREE	CMA 1516	441 Typ 2	Ø 35 / 25
CREE	CMA 1825 / 1840	437 Typ 2	Ø 40 / 30
CREE	CMA 2550	439 Typ 1	Ø 50 / 35
CREE	CMA 3090	447 Typ 1	Ø 50 / 35
CREE	CMB 1304 / 1306	448 Typ 1	Ø 30 / 20
CREE	CMB 1507 / 1510 / 1516	441 Typ 2	Ø 35 / 25
CREE	CMB 1818 / 1825	437 Typ 2	Ø 40 / 30
CREE	CMB 1840	457 Typ 1	Ø 40 / 30
CREE	CMB 2550	439 Typ 1	Ø 50 / 35
CREE	CMB 3090	447 Typ 1	Ø 50 / 35
CREE	CMT 1407 / 1412 / 1420	434 Typ 2	Ø 35 / 25

Mögliche Halter / COB Kombinationen / Holder / COB combinations

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Abmessungen Dimensions
CREE	CMT 1922 / 1925 / 1930 / 1945	477 Typ 2	Ø 40 / 30
CREE	CMT 2850 / 2870 / 2890	471 Typ 1	Ø 50 / 35
CREE	CMU 1003 / 1006 / 1010 / 1013	434 Typ 2	Ø 35 / 25
CREE	CMU 1516 / 1519 / 1526 / 1532	433 Typ 2	Ø 40 / 30
CREE	CMU 2236 / 2239 / 2258 / 2287	471 Typ 1	Ø 50 / 35
CREE	CXB 1304 / 1310	448 Typ 1	Ø 30 / 20
CREE	CXB 1507 / 1512 / 1520	441 Typ 2	Ø 35 / 25
CREE	CXB 1816 / 1820	437 Typ 2	Ø 40 / 30
CREE	CXB 1830	457 Typ 1	Ø 40 / 30
CREE	CXB 2530 / 2540	439 Typ 1	Ø 50 / 35
CREE	CXB 3050 / 3070	447 Typ 1	Ø 50 / 35
CREE	CXB 3590	449 Typ 1	Ø 60 / 45
Edison	2PHE 03 / 06 / 09 / 13	434 Typ 2	Ø 35 / 25
Edison	2PHE 15 / 18 / 24 / 30	433 Typ 2	Ø 40 / 30
Edison	2PHE 55 / 60 / 83	431 Typ 2	Ø 50 / 35
Lextar	PB 06 / 09 / 13	434 Typ 2	Ø 35 / 25
Lextar	PB 16 / 19 / 26	433 Typ 2	Ø 40 / 30
Lextar	PB 38 / 54	431 Typ 2	Ø 50 / 35
Lumileds	Luxeon 1202s / 1202HD	452 Typ 1	Ø 30 / 20
Lumileds	Luxeon 1202 / 1203 / 1204HD	480 Typ 1	33 x 27 / 28
Lumileds	Luxeon 1205HD	480 Typ 1	33 x 27 / 28
Lumileds	Luxeon 1204 / 1205	432 Typ 2	Ø 50 / 35
Lumileds	Luxeon 1208 / 1210	432 Typ 2	Ø 50 / 35
Lumileds	Luxeon 1211	431 Typ 2	Ø 50 / 35
Lumileds	Luxeon 1213 / 1216 / 1812 / 1816	431 Typ 2	Ø 50 / 35
Lumileds	Luxeon 1321 / 1825	458 Typ 1	Ø 65 / 50
Lumileds	CS COB L02 / L04	434 Typ 2	Ø 35 / 25
Lumileds	CS COB L06 / L08 / L10	433 Typ 2	Ø 40 / 30
Lumileds	CS COB L11 / L13 / L16	431 Typ 2	Ø 50 / 35
Lumileds	CS COB R12 / R18	431 Typ 2	Ø 50 / 35
Lumileds	CX Plus HD S01H4, S0xH6	448 Typ 1	Ø 30 / 20
Lumileds	CX Plus HD S04H9	4xx Typ 1	Ø 30 / 20
Lumileds	CX Plus S01Fx / S02Fx	448 Typ 1	Ø 30 / 20
Lumileds	CX Plus M02Fx / M03Fx	441 Typ 2	Ø 35 / 25

Mögliche Halter / COB Kombinationen / Holder / COB combinations


COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Abmessungen Dimensions
Lumileds	CX Plus L04Fx / L05Fx / L08Fx	437 Typ 2	Ø 40 / 30
Luminus	CXM-3-xC	434 Typ 2	Ø 35 / 25
Luminus	CHM-4-BH / CXM-4-xC	434 Typ 2	Ø 35 / 25
Luminus	CHM-6-BH / CXM-6-xC	434 Typ 2	Ø 35 / 25
Luminus	CIM/CLM/CXM-9-xC	434 Typ 2	Ø 35 / 25
Luminus	CLM/CXM-9-xA	461 Typ 1	Ø 35 / 25
Luminus	CHM-9-BH	433 Typ 2	Ø 40 / 30
Luminus	CXM-11-xC	433 Typ 2	Ø 40 / 30
Luminus	CGM/CIM/CLM/CXM-14-xC	433 Typ 2	Ø 40 / 30
Luminus	CVM/CXM-18	453 Typ 1	Ø 40 / 30
Luminus	CXM-18 Gen6	431 Typ 1	Ø 40 / 30
Luminus	CGM/CIM/CLM/CXM-22-xC	431 Typ 2	Ø 50 / 35
Luminus	CVM/CXM-27	454 Typ 1	Ø 55 / 40
Luminus	CVM/CXM-32	458 Typ 1	Ø 65 / 50
Luminus	CVM-45	435 Typ 1	Ø 65 / 50
Luminus	CDM-6 / CDM-9Gen1 DtW	490 Typ L8	Ø 44 / 35
Luminus	CDM-9 Gen2 DtW	491 Typ L8	Ø 44 / 35
Luminus	CDM-14/CDM-18 DtW	491 Typ L8	Ø 44 / 35
Luminus	CTM-6 / CTM-9 TW	495 Typ L8	Ø 44 / 35
Luminus	CTM-14 TW	442 Typ L8	Ø 44 / 35
Luminus	CTM-14 RGBW	500 Typ L8-1	Ø 44 / 35
Luminus	CTM-18 Gen1 TW	442 Typ L8	Ø 44 / 35
Luminus	CTM-18 Gen2 TW	483 Typ L8	Ø 44 / 35
Luminus	CTM-22 TW	494 Typ Z1	Ø 49 / 35
Luxtech	COB-WD-10-1512	479 Typ 1	Ø 30 / 20
Luxtech	COB-WD-17-2420	491 Typ L8	Ø 44 / 35
Luxtech	COB-DN-16-2420	442 Typ L8	Ø 44 / 35
Nichia	NV..S007Z / NF..T012B	452 Typ 1	Ø 30 / 20
Nichia	NF..S024B / NT..S024B	452 Typ 1	Ø 30 / 20
Nichia	NJ..S024Z	452 Typ 1	Ø 30 / 20
Nichia	NV..L016Z / NV..L024Z	438 Typ 1	33 x 27 / 28
Nichia	NF..L036B / NF..L048B	438 Typ 1	33 x 27 / 28
Nichia	NF..L060B	438 Typ 1	33 x 27 / 28
Nichia	NV..J048Z / NF..J108B	463 Typ 1	Ø 50 / 35



Mögliche Halter / COB Kombinationen / Holder / COB combinations

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Abmessungen Dimensions
Nichia	NF..J130B	463 Typ 1	Ø 50 / 35
Nichia	NF..H306B	488 Typ 1 HV	Ø 65 / 50
Nichia	NJNWS012Z Tunable	495 Typ L8 HV	Ø 44 / 35
Nichia	NJCWL024Z Tunable	497 Typ L8 HV	Ø 44 / 35
Nichia	NVCWJ024Z Tunable	498 Typ L8 HV	Ø 44 / 35
Philips	Fortimo SLM12xx .. 1215 G7	452 Typ 1	Ø 30 / 20
Philips	Fortimo SLM12xx .. 1619 G7	480 Typ 1	33 x 27 / 28
Philips	Fortimo SLM12xx .. 2024 G7	432 Typ 2	Ø 50 / 35
Philips	Fortimo SLM12xx .. 2828 G7	431 Typ 2	Ø 50 / 35
Philips	Fortimo SLM12xx .. 1313 G7N	434 Typ 2	Ø 35 / 25
Philips	Fortimo SLM12xx .. 1919 G7N	433 Typ 2	Ø 40 / 30
Philips	Fortimo SLM12xx .. 2828 G7N	431 Typ 2	Ø 50 / 35
Philips	Fortimo SLM13xx .. 2024 G8	432 Typ 2	Ø 50 / 35
Philips	Fortimo SLM13xx .. 2828 G8 UHE	431 Typ 2	Ø 50 / 35
Philips	Fortimo L06A 1313 G7N Tunable	509 Typ L8	Ø 44 / 35
Philips	Fortimo L09A 1919 G7N Tunable	501 Typ L8	Ø 44 / 35
Prolight Opto	PASB	434 Typ 2	Ø 35 / 25
Prolight Opto	PASQ/PAPQ DimToWarm	434 Typ 2	Ø 35 / 25
Prolight Opto	PDSQ DimToWarm	490 Typ L8	Ø 44 / 35
Prolight Opto	PDSR DimToWarm	432 Typ 2	Ø 50 / 35
Prolight Opto	PDSJ Tunable	442 Typ L8	Ø 44 / 35
Samsung	LC 010C	434 Typ 1	Ø 40 / 30
Samsung	LC 020C / 030C / 040C	477 Typ 1	Ø 40 / 30
Samsung	LC 003D / 006D	434 Typ 2	Ø 35 / 25
Samsung	LC 009D / 013D	434 Typ 2	Ø 35 / 25
Samsung	LC 016D / 019D	477 Typ 1	Ø 40 / 30
Samsung	LC 026D / 033D	477 Typ 1	Ø 40 / 30
Samsung	LC 040D / 060D / 080D	431 Typ 2	Ø 50 / 35
Samsung	LC010T Tunable	501 Typ L8	Ø 44 / 35
Samsung	LC020T Tunable	501 Typ L8	Ø 44 / 35
Samsung	LC035T Tunable	502 Typ 1	Ø 50 / 35
Seoul	SAW* 0661	434 Typ 2	Ø 35 / 25
Seoul	SAW* 1062 / 1063	434 Typ 2	Ø 35 / 25

Mögliche Halter / COB Kombinationen / Holder / COB combinations

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Abmessungen Dimensions
Seoul	SAW* 1564 / 1565 / 1566	477 Typ 1	Ø 40 / 30
Seoul	SAW* 22AA / 2296	431 Typ 2	Ø 50 / 35
Seoul	SAW* 2298 / 226A	431 Typ 2	Ø 50 / 35
Seoul	SAW* 33EA / 33GC	458 Typ 1 HV	Ø 65 / 50
Tridonic	SLE ADV8 LES 04 / 06	434 Typ 2	Ø 35 / 25
Tridonic	SLE ADV8 LES 09	434 Typ 2	Ø 35 / 25
Tridonic	SLE ADV8 LES 13	433 Typ 2	Ø 40 / 30
Tridonic	SLE ADV8 LES 15	433 Typ 2	Ø 40 / 30
Tridonic	SLE ADV8 LES 17	431 Typ 1	Ø 50 / 35
Tridonic	SLE ADV8 LES 21	431 Typ 1	Ø 50 / 35
Tridonic	SLE SNC8 LES 06	434 Typ 2	Ø 35 / 25
Tridonic	SLE SNC8 LES 09	434 Typ 2	Ø 35 / 25
Tridonic	SLE SNC8 LES 15	433 Typ 2	Ø 40 / 30
VS Lighting	DMS 102 ***W	434 Typ 2	Ø 35 / 25
VS Lighting	DMS 124 ***W	434 Typ 2	Ø 35 / 25
VS Lighting	DMS 125 / 126 / 128 ***W	433 Typ 2	Ø 40 / 30
VS Lighting	DMS 120 ***W	431 Typ 2	Ø 50 / 35
VS Lighting	DMS 12C / 18B ***W	431 Typ 2	Ø 50 / 35
VS Lighting	DMS 1208J	433 Typ 2	Ø 40 / 30
VS Lighting	DMS 1212J / 1812J	431 Typ 2	Ø 50 / 35
VS Lighting	VCA 042	486 Typ Z4	Ø 35 / 25
VS Lighting	VCA2 122 / 123 / 124	486 Typ Z4	Ø 35 / 25
VS Lighting	VCA2 126 / 128	477 Typ 2	Ø 40 / 30
VS Lighting	VCA2 1211 / 1213	471 Typ 2	Ø 50 / 35
VS Lighting	TW 1914 Tunable	493 Typ L8	Ø 44 / 35
VS Lighting	TW 2820 Tunable	494 Typ Z1	Ø 49 / 35
VS Lighting	WU-M-618 DimToWarm	434 Typ 2	Ø 35 / 25
Xicato	XOB 04	486 Typ Z4	Ø 35 / 25
Xicato	XOB 06 (B)	486 Typ Z4	Ø 35 / 25
Xicato	XOB 09	434 Typ 2	Ø 35 / 25
Xicato	XOB 14	433 Typ 2	Ø 40 / 30
Xicato	XOB 23	431 Typ 2	Ø 50 / 35
Xicato	XOB 32	458 Typ 1	Ø 65 / 50

LEDiL®	2x2mx 2x2MX System	
LEDiL® and 2X2MX are registered trademarks of Ledil Oy in the European Union, the U.S.A and certain other countries.		
LEDiL Optik LEDiL optics	STRADA 2x2MX STRADA 2x2MXS	
Hersteller Webseite Manufacturer website	www.ledil.com	
LED Halter B+W LED Holder B+W	4xx / Typ 2x2MX HV	

Holder 4xx Type 2x2MX HV	e.g. LEDiL Strada 2x2MXS DWC2
	

Passende Kühlkörper / Suitable heat sinks:		
	CoolBlock SQ CoolBeam SQ	
MechaTronix Cooler MechaTronix Cooler	CoolBlock SQ-01	
Hersteller Webseite Manufacturer website	www.led-heatsink.com	

Die dargestellten Halterlösungen sind Mehrfachhalter, bei denen die COBs im Halter in Serie geschaltet werden. Daher muss bei Serienschaltungen von mehreren Modulen die gesamte Vorwärtsspannung betrachtet werden.
 The described holder solution is a multiple COB holder where all COBs are prewired in a serial connection. Therefore the total forward voltage maybe critical if holders are connected in series.

COB forward Voltage 36 V (Standard)		COB forward Voltage 18 V (special versions like Citizen CLU028 0604 or CREE 1512 available)	
holder rated voltage 150V DC	holder rated voltage 450V DC by using insulating TIM	holder rated voltage 150V DC	holder rated voltage 450V DC by using insulating TIM
single use only	up to 2 holders in series	up to 2 holders in series	up to 4 holders in series

Die max. Ausgangsspannung des LED Treibers kann eine Veränderung der o.g. Anordnung zur Folge haben und muss daher überprüft werden.

The max output voltage may have an influence on the proposal above and need to be checked.

Mögliche Halter / COB Kombinationen / Holder / COB combinations 2x2MX System

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Adapter Base part
Bridgelux	V3 HD / V4 HD Gen 7,8	460 Typ 2x2MX HV	see LEDiL website
Bridgelux	V6 HD Gen 7,8	464 Typ 2x2MX HV	see LEDiL website
Bridgelux	V6 Gen 8,9 (just 2 pads!)	460 Typ 2x2MX HV	see LEDiL website
Bridgelux	V8 Gen 7,8,9 (4 pads)	460 Typ 2x2MX HV	see LEDiL website
Bridgelux	V10 Gen 7,8,9	486 Typ 2x2MX HV	see LEDiL website
Bridgelux	Vesta DTW 6/9mm Gen 1,2	490 Typ 2x2MX HV	see LEDiL website
Bridgelux	Vesta Tunable 6mm Gen 2	504 Typ 2x2MX HV	see LEDiL website
Bridgelux	Vesta Tunable 9mm Gen 2	489 Typ 2x2MX HV	see LEDiL website
Citizen	CLU 028 / 02J / 02Q	434 Typ 2x2MX HV	see LEDiL website
Citizen	CLU 7R3	485 Typ 2x2MX HV	see LEDiL website
Citizen	CLU 702 / 703 / 7A2 / 7A3 / 7B2	434 Typ 2x2MX HV	see LEDiL website
CREE	CHA 0304 / 0410 / 0612	434 Typ 2x2MX HV	see LEDiL website
CREE	CMA 1303 / 1306	448 Typ 2x2MX HV	see LEDiL website
CREE	CMA 1516	441 Typ 2x2MX HV	see LEDiL website
CREE	CMB 1304 / 1306	448 Typ 2x2MX HV	see LEDiL website
CREE	CMB 1507 / 1510 / 1516	441 Typ 2x2MX HV	see LEDiL website
CREE	CMT 1407 / 1412 / 1420	434 Typ 2x2MX HV	see LEDiL website
CREE	CMU 1003 / 1006 / 1010 / 1013	434 Typ 2x2MX HV	see LEDiL website
CREE	CXB 1304 / 1310	448 Typ 2x2MX HV	see LEDiL website
CREE	CXB 1507 / 1512 / 1520	441 Typ 2x2MX HV	see LEDiL website

Mögliche Halter / COB Kombinationen / Holder / COB combinations 2x2MX System

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Adapter Base part
Edison	2PHE 03 / 06 / 09 / 13	434 Typ 2x2MX HV	see LEDiL website
Lextar	PB 06 / 09 / 13	434 Typ 2x2MX HV	see LEDiL website
Lumileds	Luxeon 1202s / 1202HD	452 Typ 2x2MX HV	see LEDiL website
Lumileds	CS COB L02 / L04	434 Typ 2x2MX HV	see LEDiL website
Lumileds	CX Plus HD S01H4, S0xH6	448 Typ 2x2MX HV	see LEDiL website
Lumileds	CX Plus HD S04H9	4xx Typ 2x2MX HV	see LEDiL website
Lumileds	CX Plus S01Fx / S02Fx	448 Typ 2x2MX HV	see LEDiL website
Lumileds	CX Plus M02Fx / M03Fx	441 Typ 2x2MX HV	see LEDiL website
Luminus	CXM-3-xC	434 Typ 2x2MX HV	see LEDiL website
Luminus	CHM-4-BH / CXM-4-xC	434 Typ 2x2MX HV	see LEDiL website
Luminus	CHM-6-BH / CXM-6-xC	434 Typ 2x2MX HV	see LEDiL website
Luminus	CIM/CLM/CXM-9-xC	434 Typ 2x2MX HV	see LEDiL website
Luminus	CLM/CXM-9-xA	461 Typ 2x2MX HV	see LEDiL website
Luminus	CDM-6 / CDM-9Gen1 DtW	490 Typ 2x2MX HV	see LEDiL website
Luminus	CTM-6 / CTM-9 TW	495 Typ 2x2MX HV	see LEDiL website
Luxtech	COB-WD-10-1512	479 Typ 2x2MX HV	see LEDiL website
Nichia	NV..S007Z / NF..T012B	452 Typ 2x2MX HV	see LEDiL website
Nichia	NF..S024B / NT..S024B	452 Typ 2x2MX HV	see LEDiL website
Nichia	NJ..S024Z	452 Typ 2x2MX HV	see LEDiL website
Nichia	NJNWS012Z Tunable	495 Typ 2x2MX HV HV	see LEDiL website
Philips	Fortimo SLM12xx .. 1215 G7	452 Typ 2x2MX HV	see LEDiL website
Philips	Fortimo SLM12xx .. 1313 G7N	434 Typ 2x2MX HV	see LEDiL website
Philips	Fortimo L06A 1313 G7N Tunable	509 Typ 2x2MX HV	see LEDiL website
Prolight Opto	PASB	434 Typ 2x2MX HV	see LEDiL website
Prolight Opto	PASQ/PAPQ DimToWarm	434 Typ 2x2MX HV	see LEDiL website
Prolight Opto	PDSQ DimToWarm	490 Typ 2x2MX HV	see LEDiL website
Samsung	LC 010C	434 Typ 2x2MX HV	see LEDiL website
Samsung	LC 003D / 006D	434 Typ 2x2MX HV	see LEDiL website

Mögliche Halter / COB Kombinationen / Holder / COB combinations **2x2MX System**

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Adapter Base part
Samsung	LC 009D / 013D	434 Typ 2x2MX HV	see LEDiL website
Seoul	SAW* 0661	434 Typ 2x2MX HV	see LEDiL website
Seoul	SAW* 1062 / 1063	434 Typ 2x2MX HV	see LEDiL website
Tridonic	SLE ADV8 LES 04 / 06	434 Typ 2x2MX HV	see LEDiL website
Tridonic	SLE ADV8 LES 09	434 Typ 2x2MX HV	see LEDiL website
Tridonic	SLE SNC8 LES 06	434 Typ 2x2MX HV	see LEDiL website
Tridonic	SLE SNC8 LES 09	434 Typ 2x2MX HV	see LEDiL website
VS Lighting	DMS 102 ***W	434 Typ 2x2MX HV	see LEDiL website
VS Lighting	DMS 124 ***W	434 Typ 2x2MX HV	see LEDiL website
VS Lighting	VCA 042	486 Typ 2x2MX HV	see LEDiL website
VS Lighting	VCA2 122 / 123 / 124	486 Typ 2x2MX HV	see LEDiL website
VS Lighting	WU-M-618 DimToWarm	434 Typ 2x2MX HV	see LEDiL website
Xicato	XOB 04	486 Typ 2x2MX HV	see LEDiL website
Xicato	XOB 06 (B)	486 Typ 2x2MX HV	see LEDiL website
Xicato	XOB 09	434 Typ 2x2MX HV	see LEDiL website

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL Clamp System**

COB Hersteller COB Supplier	COB Typ COB Type	LES LES	Halter Holder	Adapter Base part
Bridgelux	V9 HD / V11 HD Gen 7,8	9 mm	496 Typ L1	C13658_CLAMP-VERO13-18
Bridgelux	V6 Gen 8,9 (just 2 pads!)	9 mm	460 Typ L1	C13658_CLAMP-VERO13-18
Bridgelux	V8 Gen 7,8,9 (4 pads)	9 mm	460 Typ L1	C13658_CLAMP-VERO13-18
Bridgelux	V10 Gen 7,8,9	10 mm	486 Typ L1	C13658_CLAMP-VERO13-18
Bridgelux	V13 Gen 7,8,9	15 mm	477 Typ L1	C13658_CLAMP-VERO13-18
Bridgelux	V15 Gen 7,8,9	15 mm	456 Typ L2	C13658_CLAMP-VERO13-18
Bridgelux	V18 Gen 7,8,9	20 mm	462 Typ L3	C13584_CLAMP-VERO29
Bridgelux	V22 Gen 7,8,9	23 mm	431 Typ L3	C13584_CLAMP-VERO29
Bridgelux	Vesta DTW 6/9mm Gen 1,2	9 mm	490 Typ L1	C13658_CLAMP-VERO13-18
Bridgelux	Vesta DTW 13/15mm Gen 1,2	16 mm	491 Typ L2	C13658_CLAMP-VERO13-18
Bridgelux	Vesta DTW 18mm Gen 1	18 mm	505 Typ L3	C13584_CLAMP-VERO29
Bridgelux	Vesta Tunable 9mm Gen 2	10 mm	489 Typ L1	C13658_CLAMP-VERO13-18
Bridgelux	Vesta Tunable 13mm Gen 2	15 mm	492 Typ L1	C13658_CLAMP-VERO13-18
Bridgelux	Vesta Tunable 15mm Gen 2	16 mm	482 Typ L2	C13658_CLAMP-VERO13-18
Bridgelux	Vesta Tunable 18mm Gen 2	20 mm	483 Typ L3	C13584_CLAMP-VERO29
Bridgelux	Vesta Tunable 22mm Gen 2	23 mm	494 Typ L3	C13584_CLAMP-VERO29
Citizen	CLU 028 / 02J / 02Q	10 mm	434 Typ L1	C13658_CLAMP-VERO13-18
Citizen	CLU 038 / 03H / 03J / 03Q	15 mm	433 Typ L1	C13658_CLAMP-VERO13-18
Citizen	CLU 048 / 04H / 04J / 04Q	22 mm	431 Typ L3	C13584_CLAMP-VERO29
Citizen	CLU 712 / 713	9 mm	477 Typ L1	C13658_CLAMP-VERO13-18
Citizen	CLU 723	11 mm	477 Typ L1	C13658_CLAMP-VERO13-18
Citizen	CLU 733	13 mm	471 Typ L3	C13584_CLAMP-VERO29
Citizen	LCN-C01B2 / C02B2 Tunable	15 mm	481 Typ L2	C13658_CLAMP-VERO13-18
Citizen	LCN-C04B2 / C05B2 Tunable	15 mm	481 Typ L2	C13658_CLAMP-VERO13-18
CREE	CHA 0825	9 mm	433 Typ L1	C13658_CLAMP-VERO13-18
CREE	CMA 1516	9 mm	441 Typ L1	C13658_CLAMP-VERO13-18
CREE	CMA 1825 / 1840	14 mm	437 Typ L1	C13658_CLAMP-VERO13-18
CREE	CMA 2550	19 mm	439 Typ L3	C13584_CLAMP-VERO29
CREE	CMA 3090	23 mm	447 Typ L3	C13584_CLAMP-VERO29
CREE	CMB 1507 / 1510 / 1516	9 mm	441 Typ L1	C13658_CLAMP-VERO13-18
CREE	CMB 1818 / 1825	12 mm	437 Typ L1	C13658_CLAMP-VERO13-18
CREE	CMB 1840	14 mm	457 Typ L1	C13658_CLAMP-VERO13-18
CREE	CMB 2550	19 mm	439 Typ L3	C13584_CLAMP-VERO29
CREE	CMB 3090	23 mm	447 Typ L3	C13584_CLAMP-VERO29
CREE	CMT 1407 / 1412 / 1420	10 mm	434 Typ L1	C13658_CLAMP-VERO13-18

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL Clamp System**

COB Hersteller COB Supplier	COB Typ COB Type	LES LES	Halter Holder	Adapter Base part
CREE	CMT 1922 / 1925 / 1930 / 1945	15 mm	477 Typ L1	C13658_CLAMP-VERO13-18
CREE	CMT 2850 / 2870 / 2890	22 mm	471 Typ L3	C13584_CLAMP-VERO29
CREE	CMU 1003 / 1006 / 1010 / 1013	10 mm	434 Typ L1	C13658_CLAMP-VERO13-18
CREE	CMU 1516 / 1519 / 1526 / 1532	15 mm	433 Typ L1	C13658_CLAMP-VERO13-18
CREE	CMU 2236 / 2239 / 2258 / 2287	22 mm	471 Typ L3	C13584_CLAMP-VERO29
CREE	CXB 1507 / 1512 / 1520	9 mm	441 Typ L1	C13658_CLAMP-VERO13-18
CREE	CXB 1816 / 1820	12 mm	437 Typ L1	C13658_CLAMP-VERO13-18
CREE	CXB 1830	14 mm	457 Typ L1	C13658_CLAMP-VERO13-18
CREE	CXB 2530 / 2540	19 mm	439 Typ L3	C13584_CLAMP-VERO29
CREE	CXB 3050 / 3070	23 mm	447 Typ L3	C13584_CLAMP-VERO29
Edison	2PHE 03 / 06 / 09 / 13	10 mm	434 Typ L1	C13658_CLAMP-VERO13-18
Edison	2PHE 15 / 18 / 24 / 30	16 mm	433 Typ L1	C13658_CLAMP-VERO13-18
Edison	2PHE 55 / 60 / 83	23 mm	431 Typ L3	C13584_CLAMP-VERO29
Lextar	PB 06 / 09 / 13	10 mm	434 Typ L1	C13658_CLAMP-VERO13-18
Lextar	PB 16 / 19 / 26	15 mm	433 Typ L1	C13658_CLAMP-VERO13-18
Lextar	PB 38 / 54	22 mm	431 Typ L3	C13584_CLAMP-VERO29
Lumileds	Luxeon 1202 / 1203 / 1204HD	9 mm	480 Typ L1	C13658_CLAMP-VERO13-18
Lumileds	Luxeon 1205HD	11 mm	480 Typ L1	C13658_CLAMP-VERO13-18
Lumileds	Luxeon 1204 / 1205	13 mm	432 Typ L2	C13658_CLAMP-VERO13-18
Lumileds	Luxeon 1208 / 1210	15 mm	432 Typ L2	C13658_CLAMP-VERO13-18
Lumileds	Luxeon 1211	19 mm	431 Typ L3	C13584_CLAMP-VERO29
Lumileds	Luxeon 1213 / 1216 / 1812 / 1816	23 mm	431 Typ L3	C13584_CLAMP-VERO29
Lumileds	CS COB L02 / L04	10 mm	434 Typ L1	C13658_CLAMP-VERO13-18
Lumileds	CS COB L06 / L08 / L10	15 mm	433 Typ L1	C13658_CLAMP-VERO13-18
Lumileds	CS COB L11 / L13 / L16	22 mm	431 Typ L3	C13584_CLAMP-VERO29
Lumileds	CS COB R12 / R18	22 mm	431 Typ L3	C13584_CLAMP-VERO29
Lumileds	CX Plus HD S04H9	9 mm	4xx Typ L1	C13658_CLAMP-VERO13-18
Lumileds	CX Plus M02Fx / M03Fx	9 mm	441 Typ L1	C13658_CLAMP-VERO13-18
Lumileds	CX Plus L04Fx / L05Fx / L08Fx	14 mm	437 Typ L1	C13658_CLAMP-VERO13-18
Luminus	CIM/CLM/CXM-9-xC	9 mm	434 Typ L1	C13658_CLAMP-VERO13-18
Luminus	CLM/CXM-9-xA	10 mm	461 Typ L1	C13658_CLAMP-VERO13-18
Luminus	CHM-9-BH	9 mm	433 Typ L1	C13658_CLAMP-VERO13-18
Luminus	CXM-11-xC	12 mm	433 Typ L1	C13658_CLAMP-VERO13-18

Mögliche Halter / COB Kombinationen / Holder / COB combinations LEDiL Clamp System

COB Hersteller COB Supplier	COB Typ COB Type	LES LES	Halter Holder	Adapter Base part
Luminus	CGM/CIM/CLM/CXM-14-xC	15 mm	433 Typ L1	C13658_CLAMP-VERO13-18
Luminus	CVM/CXM-18	18 mm	453 Typ L2	C13658_CLAMP-VERO13-18
Luminus	CXM-18 Gen6	18 mm	431 Typ L3	C13584_CLAMP-VERO29
Luminus	CGM/CIM/CLM/CXM-22-xC	22 mm	431 Typ L3	C13584_CLAMP-VERO29
Luminus	CDM-6 / CDM-9Gen1 DtW	10 mm	490 Typ L1	C13658_CLAMP-VERO13-18
Luminus	CDM-9 Gen2 DtW	9 mm	491 Typ L2	C13658_CLAMP-VERO13-18
Luminus	CDM-14/CDM-18 DtW	17 mm	491 Typ L2	C13658_CLAMP-VERO13-18
Luminus	CTM-6 / CTM-9 TW	10 mm	495 Typ L1	C13658_CLAMP-VERO13-18
Luminus	CTM-14 TW	18 mm	442 Typ L2	C13658_CLAMP-VERO13-18
Luminus	CTM-18 Gen1 TW	18 mm	442 Typ L2	C13658_CLAMP-VERO13-18
Luminus	CTM-18 Gen2 TW	20 mm	483 Typ L3	C13584_CLAMP-VERO29
Luminus	CTM-22 TW	22 mm	494 Typ L3	C13584_CLAMP-VERO29
Luxtech	COB-WD-17-2420	15 mm	491 Typ L2	C13658_CLAMP-VERO13-18
Nichia	NV..L016Z / NV..L024Z	9 mm	438 Typ L1	C13658_CLAMP-VERO13-18
Nichia	NF..L036B / NF..L048B	12 mm	438 Typ L1	C13658_CLAMP-VERO13-18
Nichia	NF..L060B	12 mm	438 Typ L1	C13658_CLAMP-VERO13-18
Nichia	NV..J048Z / NF..J108B	15 mm	463 Typ L2	C13658_CLAMP-VERO13-18
Nichia	NF..J130B	15 mm	463 Typ L2	C13658_CLAMP-VERO13-18
Nichia	NVCWJ024Z Tunable	11 mm	498 Typ L2 HV	C13658_CLAMP-VERO13-18
Philips	Fortimo SLM12xx .. 1619 G7	9 mm	480 Typ L1	C13658_CLAMP-VERO13-18
Philips	Fortimo SLM12xx .. 2024 G7	15 mm	432 Typ L2	C13658_CLAMP-VERO13-18
Philips	Fortimo SLM12xx .. 2828 G7	23 mm	431 Typ L3	C13584_CLAMP-VERO29
Philips	Fortimo SLM12xx .. 1313 G7N	10 mm	434 Typ L1	C13658_CLAMP-VERO13-18
Philips	Fortimo SLM12xx .. 1919 G7N	15 mm	433 Typ L1	C13658_CLAMP-VERO13-18
Philips	Fortimo SLM12xx .. 2828 G7N	22 mm	431 Typ L3	C13584_CLAMP-VERO29
Philips	Fortimo SLM13xx .. 2024 G8 UHE	15 mm	432 Typ L2	C13658_CLAMP-VERO13-18
Philips	Fortimo SLM13xx .. 2828 G8 UHE	23 mm	431 Typ L3	C13584_CLAMP-VERO29
Philips	Fortimo L09A 1919 G7N Tunable	9 mm	501 Typ L1	C13658_CLAMP-VERO13-18
Prolight Opto	PASB	10 mm	434 Typ L1	C13658_CLAMP-VERO13-18
Prolight Opto	PASQ/PAPQ DimToWarm	10 mm	434 Typ L1	C13658_CLAMP-VERO13-18
Prolight Opto	PDSR DimToWarm	15 mm	432 Typ L2	C13658_CLAMP-VERO13-18
Samsung	LC 020C / 030C / 040C	12 mm	477 Typ L1	C13658_CLAMP-VERO13-18


Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL Clamp System**


COB Hersteller COB Supplier	COB Typ COB Type	LES LES	Halter Holder	Adapter Base part
Samsung	LC 003D / 006D	10 mm	434 Typ L1	C13658_CLAMP-VERO13-18
Samsung	LC 009D / 013D	10 mm	434 Typ L1	C13658_CLAMP-VERO13-18
Samsung	LC 016D / 019D	16 mm	477 Typ L1	C13658_CLAMP-VERO13-18
Samsung	LC 026D / 033D	16 mm	477 Typ L1	C13658_CLAMP-VERO13-18
Samsung	LC 040D / 060D / 080D	23 mm	431 Typ L3	C13584_CLAMP-VERO29
Samsung	LC010T Tunable	10 mm	501 Typ L1	C13658_CLAMP-VERO13-18
Samsung	LC020T Tunable	13 mm	501 Typ L1	C13658_CLAMP-VERO13-18
Samsung	LC035T Tunable	22 mm	502 Typ L3	C13584_CLAMP-VERO29
Seoul	SAW* 1062 / 1063	10 mm	434 Typ L1	C13658_CLAMP-VERO13-18
Seoul	SAW* 1564 / 1565 / 1566	15 mm	477 Typ L1	C13658_CLAMP-VERO13-18
Seoul	SAW* 22AA / 2296	22 mm	431 Typ L3	C13584_CLAMP-VERO29
Seoul	SAW* 2298 / 226A	22 mm	431 Typ L3	C13584_CLAMP-VERO29
Tridonic	SLE ADV8 LES 04 / 06	9 mm	434 Typ L1	C13658_CLAMP-VERO13-18
Tridonic	SLE ADV8 LES 09	9 mm	434 Typ L1	C13658_CLAMP-VERO13-18
Tridonic	SLE ADV8 LES 13	13 mm	433 Typ L1	C13658_CLAMP-VERO13-18
Tridonic	SLE ADV8 LES 15	15 mm	433 Typ L1	C13658_CLAMP-VERO13-18
Tridonic	SLE ADV8 LES 17	17 mm	431 Typ L3	C13584_CLAMP-VERO29
Tridonic	SLE ADV8 LES 21	21 mm	431 Typ L3	C13584_CLAMP-VERO29
Tridonic	SLE SNC8 LES 09	10 mm	434 Typ L1	C13658_CLAMP-VERO13-18
Tridonic	SLE SNC8 LES 15	15 mm	433 Typ L1	C13658_CLAMP-VERO13-18
VS Lighting	DMS 124 ***W	9 mm	434 Typ L1	C13658_CLAMP-VERO13-18
VS Lighting	DMS 125 / 126 / 128 ***W	14 mm	433 Typ L1	C13658_CLAMP-VERO13-18
VS Lighting	DMS 120 ***W	17 mm	431 Typ L3	C13584_CLAMP-VERO29
VS Lighting	DMS 12C / 18B ***W	20 mm	431 Typ L3	C13584_CLAMP-VERO29
VS Lighting	DMS 1208J	15 mm	433 Typ L1	C13658_CLAMP-VERO13-18
VS Lighting	DMS 1212J / 1812J	22 mm	431 Typ L3	C13584_CLAMP-VERO29
VS Lighting	VCA2 122 / 123 / 124	9 mm	486 Typ L1	C13658_CLAMP-VERO13-18
VS Lighting	VCA2 126 / 128	14 mm	477 Typ L1	C13658_CLAMP-VERO13-18
VS Lighting	VCA2 1211 / 1213	20 mm	471 Typ L3	C13584_CLAMP-VERO29
VS Lighting	TW 1914 Tunable	14 mm	493 Typ L1	C13658_CLAMP-VERO13-18
VS Lighting	TW 2820 Tunable	20 mm	494 Typ L3	C13584_CLAMP-VERO29
VS Lighting	WU-M-618 DimToWarm	10 mm	434 Typ L1	C13658_CLAMP-VERO13-18
Xicato	XOB 09	10 mm	434 Typ L1	C13658_CLAMP-VERO13-18

Mögliche Halter / COB Kombinationen / Holder / COB combinations	LEDiL Clamp System
---	--------------------

COB Hersteller COB Supplier	COB Typ COB Type	LES LES	Halter Holder	Adapter Base part
Xicato	XOB 14	15 mm	433 Typ L1	C13658_CLAMP-VERO13-18
Xicato	XOB 23	23 mm	431 Typ L3	C13584_CLAMP-VERO29

LEDiL®	HEKLA System	
Passende LEDiL Optik Suitable LEDiL optics	BARBARA-G2 BROOKE / MIRELLA -G2 ADELIA 50/70/110 CARMEN 50/70 ZORYA, RONDA, WINNIE AMY / AMY ZOOM 50/70 YASMEEN / Y.ZOOM 50/70 ILONA / ILONA ZOOM	
LEDiL Adapter LEDiL adaptor Hersteller Webseite Manufacturer website LED Halter B+W LED Holder B+W	C16142 HEKLA-SOCKET-K www.ledil.com 4xx / Typ L8	

4xx Type L8 (eg. 489 Type L8 for Tunable COBs) 	 BARBARA-G2 Ø 70 mm BROOKE-G2 Ø 45 mm Ø 55 mm incl. ZORYA-ADAPTER-HEKL ZORYA RONDA incl. RONDA-HLD-C WINNIE incl. WINNIE-HLD-C AMY & AMY-ZOOM incl. AMY-HLD-C YASMEEN & YASMEEN-ZOOM incl. YASMEEN-HLD-C ILONA & ILONA-ZOOM ADELIA Ø 70 mm, Ø 70 mm, Ø 70 mm, Ø 110 mm, Ø 50 mm, Ø 50 mm, Ø 50 mm, Ø 75 mm CARMEN Ø 50 mm, Ø 70 mm (incl. CARMEN-HLD-C)
---	---

C16142 Hekla Socket K 	
---	--

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL Hekla System**

COB Hersteller COB Supplier	COB Typ COB Type	LES LES	Halter Holder	Adapter Base part
Bridgelux	V3 HD / V4 HD Gen 7,8	5 mm	460 Typ L8	C16142_HEKLA-SOCKET-K
Bridgelux	V6 HD Gen 7,8	7 mm	464 Typ L8	C16142_HEKLA-SOCKET-K
Bridgelux	V9 HD / V11 HD Gen 7,8	9 mm	496 Typ L8	C16142_HEKLA-SOCKET-K
Bridgelux	V6 Gen 8,9 (just 2 pads!)	9 mm	460 Typ L8	C16142_HEKLA-SOCKET-K
Bridgelux	V8 Gen 7,8,9 (4 pads)	9 mm	460 Typ L8	C16142_HEKLA-SOCKET-K
Bridgelux	V10 Gen 7,8,9	10 mm	486 Typ L8	C16142_HEKLA-SOCKET-K
Bridgelux	V13 Gen 7,8,9	15 mm	477 Typ L8	C16142_HEKLA-SOCKET-K
Bridgelux	V15 Gen 7,8,9	15 mm	456 Typ L8	C16142_HEKLA-SOCKET-K
Bridgelux	V18 Gen 7,8,9	20 mm	462 Typ L8	C16142_HEKLA-SOCKET-K
Bridgelux	Vesta DTW 6/9mm Gen 1,2	9 mm	490 Typ L8	C16142_HEKLA-SOCKET-K
Bridgelux	Vesta DTW 13/15mm Gen 1,2	16 mm	491 Typ L8	C16142_HEKLA-SOCKET-K
Bridgelux	Vesta DTW 18mm Gen 1	18 mm	505 Typ L8	C16142_HEKLA-SOCKET-K
Bridgelux	Vesta Tunable 6mm Gen 2	6 mm	504 Typ L8	C16142_HEKLA-SOCKET-K
Bridgelux	Vesta Tunable 9mm Gen 2	10 mm	489 Typ L8	C16142_HEKLA-SOCKET-K
Bridgelux	Vesta Tunable 13mm Gen 2	15 mm	492 Typ L8	C16142_HEKLA-SOCKET-K
Bridgelux	Vesta Tunable 15mm Gen 2	16 mm	482 Typ L8	C16142_HEKLA-SOCKET-K
Bridgelux	Vesta Tunable 18mm Gen 2	20 mm	483 Typ L8	C16142_HEKLA-SOCKET-K
Citizen	CLU 028 / 02J / 02Q	10 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
Citizen	CLU 038 / 03H / 03J / 03Q	15 mm	433 Typ L8	C16142_HEKLA-SOCKET-K
Citizen	CLU 7L3 / 7S3	4 mm	467 Typ L8	C16142_HEKLA-SOCKET-K
Citizen	CLU 7R3	4 mm	485 Typ L8	C16142_HEKLA-SOCKET-K
Citizen	CLU 702 / 703 / 7A2 / 7A3 / 7B2	6 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
Citizen	CLU 712 / 713	9 mm	477 Typ L8	C16142_HEKLA-SOCKET-K
Citizen	CLU 723	11 mm	477 Typ L8	C16142_HEKLA-SOCKET-K
Citizen	LCN-C01B2 / C02B2 Tunable	15 mm	481 Typ L8	C16142_HEKLA-SOCKET-K
Citizen	LCN-C04B2 / C05B2 Tunable	15 mm	481 Typ L8	C16142_HEKLA-SOCKET-K
CREE	CHA 0304 / 0410 / 0612	3 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
CREE	CHA 0825	9 mm	433 Typ L8	C16142_HEKLA-SOCKET-K
CREE	CMA 1303 / 1306	6 mm	448 Typ L8	C16142_HEKLA-SOCKET-K
CREE	CMA 1516	9 mm	441 Typ L8	C16142_HEKLA-SOCKET-K
CREE	CMA 1825 / 1840	14 mm	437 Typ L8	C16142_HEKLA-SOCKET-K
CREE	CMA 2550	19 mm	439 Typ L8	C16142_HEKLA-SOCKET-K
CREE	CMB 1304 / 1306	6 mm	448 Typ L8	C16142_HEKLA-SOCKET-K
CREE	CMB 1507 / 1510 / 1516	9 mm	441 Typ L8	C16142_HEKLA-SOCKET-K
CREE	CMB 1818 / 1825	12 mm	437 Typ L8	C16142_HEKLA-SOCKET-K

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL Hekla System**

COB Hersteller COB Supplier	COB Typ COB Type	LES LES	Halter Holder	Adapter Base part
CREE	CMB 1840	14 mm	457 Typ L8	C16142_HEKLA-SOCKET-K
CREE	CMB 2550	19 mm	439 Typ L8	C16142_HEKLA-SOCKET-K
CREE	CMT 1407 / 1412 / 1420	10 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
CREE	CMT 1922 / 1925 / 1930 / 1945	15 mm	477 Typ L8	C16142_HEKLA-SOCKET-K
CREE	CMU 1003 / 1006 / 1010 / 1013	10 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
CREE	CMU 1516 / 1519 / 1526 / 1532	15 mm	433 Typ L8	C16142_HEKLA-SOCKET-K
CREE	CXB 1304 / 1310	6 mm	448 Typ L8	C16142_HEKLA-SOCKET-K
CREE	CXB 1507 / 1512 / 1520	9 mm	441 Typ L8	C16142_HEKLA-SOCKET-K
CREE	CXB 1816 / 1820	12 mm	437 Typ L8	C16142_HEKLA-SOCKET-K
CREE	CXB 1830	14 mm	457 Typ L8	C16142_HEKLA-SOCKET-K
CREE	CXB 2530 / 2540	19 mm	439 Typ L8	C16142_HEKLA-SOCKET-K
Edison	2PHE 03 / 06 / 09 / 13	10 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
Edison	2PHE 15 / 18 / 24 / 30	16 mm	433 Typ L8	C16142_HEKLA-SOCKET-K
Lextar	PB 06 / 09 / 13	10 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
Lextar	PB 16 / 19 / 26	15 mm	433 Typ L8	C16142_HEKLA-SOCKET-K
Lumileds	Luxeon 1202s / 1202HD	7 mm	452 Typ L8	C16142_HEKLA-SOCKET-K
Lumileds	Luxeon 1202 / 1203 / 1204HD	9 mm	480 Typ L8	C16142_HEKLA-SOCKET-K
Lumileds	Luxeon 1205HD	11 mm	480 Typ L8	C16142_HEKLA-SOCKET-K
Lumileds	Luxeon 1204 / 1205	13 mm	432 Typ L8	C16142_HEKLA-SOCKET-K
Lumileds	Luxeon 1208 / 1210	15 mm	432 Typ L8	C16142_HEKLA-SOCKET-K
Lumileds	CS COB L02 / L04	10 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
Lumileds	CS COB L06 / L08 / L10	15 mm	433 Typ L8	C16142_HEKLA-SOCKET-K
Lumileds	CX Plus HD S01H4, S0xH6	6 mm	448 Typ L8	C16142_HEKLA-SOCKET-K
Lumileds	CX Plus HD S04H9	9 mm	4xx Typ L8	C16142_HEKLA-SOCKET-K
Lumileds	CX Plus S01Fx / S02Fx	5 mm	448 Typ L8	C16142_HEKLA-SOCKET-K
Lumileds	CX Plus M02Fx / M03Fx	9 mm	441 Typ L8	C16142_HEKLA-SOCKET-K
Lumileds	CX Plus L04Fx / L05Fx / L08Fx	14 mm	437 Typ L8	C16142_HEKLA-SOCKET-K
Luminus	CXM-3-xC	4 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
Luminus	CHM-4-BH / CXM-4-xC	5 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
Luminus	CHM-6-BH / CXM-6-xC	6 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
Luminus	CIM/CLM/CXM-9-xC	9 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
Luminus	CLM/CXM-9-xA	10 mm	461 Typ L8	C16142_HEKLA-SOCKET-K
Luminus	CHM-9-BH	9 mm	433 Typ L8	C16142_HEKLA-SOCKET-K

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL Hekla System**

COB Hersteller COB Supplier	COB Typ COB Type	LES LES	Halter Holder	Adapter Base part
Luminus	CXM-11-xC	12 mm	433 Typ L8	C16142_HEKLA-SOCKET-K
Luminus	CGM/CIM/CLM/CXM-14-xC	15 mm	433 Typ L8	C16142_HEKLA-SOCKET-K
Luminus	CVM/CXM-18	18 mm	453 Typ L8	C16142_HEKLA-SOCKET-K
Luminus	CDM-6 / CDM-9Gen1 DtW	10 mm	490 Typ L8	C16142_HEKLA-SOCKET-K
Luminus	CDM-9 Gen2 DtW	9 mm	491 Typ L8	C16142_HEKLA-SOCKET-K
Luminus	CDM-14/CDM-18 DtW	17 mm	491 Typ L8	C16142_HEKLA-SOCKET-K
Luminus	CTM-6 / CTM-9 TW	10 mm	495 Typ L8	C16142_HEKLA-SOCKET-K
Luminus	CTM-14 TW	18 mm	442 Typ L8	C16142_HEKLA-SOCKET-K
Luminus	CTM-14 RGBW	14 mm	500 Typ L8	C16142_HEKLA-SOCKET-K
Luminus	CTM-18 Gen1 TW	18 mm	442 Typ L8	C16142_HEKLA-SOCKET-K
Luminus	CTM-18 Gen2 TW	20 mm	483 Typ L8	C16142_HEKLA-SOCKET-K
Luxtech	COB-WD-10-1512	8 mm	479 Typ L8	C16142_HEKLA-SOCKET-K
Luxtech	COB-WD-17-2420	15 mm	491 Typ L8	C16142_HEKLA-SOCKET-K
Luxtech	COB-DN-16-2420	15 mm	442 Typ L8	C16142_HEKLA-SOCKET-K
Nichia	NV..S007Z / NF..T012B	7,0 mm	452 Typ L8	C16142_HEKLA-SOCKET-K
Nichia	NF..S024B / NT..S024B	7,0 mm	452 Typ L8	C16142_HEKLA-SOCKET-K
Nichia	NJ..S024Z	7,0 mm	452 Typ L8	C16142_HEKLA-SOCKET-K
Nichia	NV..L016Z / NV..L024Z	8,9 mm	438 Typ L8	C16142_HEKLA-SOCKET-K
Nichia	NF..L036B / NF..L048B	11,5 mm	438 Typ L8	C16142_HEKLA-SOCKET-K
Nichia	NF..L060B	11,5 mm	438 Typ L8	C16142_HEKLA-SOCKET-K
Nichia	NV..J048Z / NF..J108B	14,6 mm	463 Typ L8	C16142_HEKLA-SOCKET-K
Nichia	NF..J130B	14,6 mm	463 Typ L8	C16142_HEKLA-SOCKET-K
Nichia	NJNWS012Z Tunable	5,9 mm	495 Typ L8 HV	C16142_HEKLA-SOCKET-K
Nichia	NJCWL024Z Tunable	7,0 mm	497 Typ L8 HV	C16142_HEKLA-SOCKET-K
Nichia	NVCWJ024Z Tunable	11,0 mm	498 Typ L8 HV	C16142_HEKLA-SOCKET-K
Philips	Fortimo SLM12xx .. 1215 G7	6,5 mm	452 Typ L8	C16142_HEKLA-SOCKET-K
Philips	Fortimo SLM12xx .. 1619 G7	9,0 mm	480 Typ L8	C16142_HEKLA-SOCKET-K
Philips	Fortimo SLM12xx .. 2024 G7	15,0 mm	432 Typ L8	C16142_HEKLA-SOCKET-K
Philips	Fortimo SLM12xx .. 1313 G7N	9,8 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
Philips	Fortimo SLM12xx .. 1919 G7N	14,5 mm	433 Typ L8	C16142_HEKLA-SOCKET-K
Philips	Fortimo SLM13xx .. 2024 G8 UHE	15,0 mm	432 Typ L8	C16142_HEKLA-SOCKET-K
Philips	Fortimo L06A 1313 G7N Tunable	6,5 mm	509 Typ L8	C16142_HEKLA-SOCKET-K
Philips	Fortimo L09A 1919 G7N Tunable	9,3 mm	501 Typ L8	C16142_HEKLA-SOCKET-K

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL Hekla System**

COB Hersteller COB Supplier	COB Typ COB Type	LES LES	Halter Holder	Adapter Base part
Prolight Opto	PASB	9,8 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
Prolight Opto	PASQ/PAPQ DimToWarm	9,8 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
Prolight Opto	PDSQ DimToWarm	8,0 mm	490 Typ L8	C16142_HEKLA-SOCKET-K
Prolight Opto	PDSR DimToWarm	15,0 mm	432 Typ L8	C16142_HEKLA-SOCKET-K
Prolight Opto	PDSJ Tunable	15,0 mm	442 Typ L8	C16142_HEKLA-SOCKET-K
Samsung	LC 010C	6,0 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
Samsung	LC 020C / 030C / 040C	11,5 mm	477 Typ L8	C16142_HEKLA-SOCKET-K
Samsung	LC 003D / 006D	9,8 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
Samsung	LC 009D / 013D	9,8 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
Samsung	LC 016D / 019D	15,5 mm	477 Typ L8	C16142_HEKLA-SOCKET-K
Samsung	LC 026D / 033D	15,5 mm	477 Typ L8	C16142_HEKLA-SOCKET-K
Samsung	LC010T Tunable	9,8 mm	501 Typ L8	C16142_HEKLA-SOCKET-K
Samsung	LC020T Tunable	13,0 mm	501 Typ L8	C16142_HEKLA-SOCKET-K
Seoul	SAW* 0661	6,0 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
Seoul	SAW* 1062 / 1063	9,8 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
Seoul	SAW* 1564 / 1565 / 1566	14,5 mm	477 Typ L8	C16142_HEKLA-SOCKET-K
Tridonic	SLE ADV8 LES 04 / 06	9,0 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
Tridonic	SLE ADV8 LES 09	9,0 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
Tridonic	SLE ADV8 LES 13	13,0 mm	433 Typ L8	C16142_HEKLA-SOCKET-K
Tridonic	SLE ADV8 LES 15	15,0 mm	433 Typ L8	C16142_HEKLA-SOCKET-K
Tridonic	SLE SNC8 LES 06	6,0 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
Tridonic	SLE SNC8 LES 09	9,8 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
Tridonic	SLE SNC8 LES 15	14,5 mm	433 Typ L8	C16142_HEKLA-SOCKET-K
VS Lighting	DMS 102 ***W	6,0 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
VS Lighting	DMS 124 ***W	9,0 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
VS Lighting	DMS 125 / 126 / 128 ***W	13,8 mm	433 Typ L8	C16142_HEKLA-SOCKET-K
VS Lighting	DMS 1208J	14,5 mm	433 Typ L8	C16142_HEKLA-SOCKET-K
VS Lighting	VCA 042	3,9 mm	486 Typ L8	C16142_HEKLA-SOCKET-K
VS Lighting	VCA2 122 / 123 / 124	9,1 mm	486 Typ L8	C16142_HEKLA-SOCKET-K
VS Lighting	VCA2 126 / 128	13,8 mm	477 Typ L8	C16142_HEKLA-SOCKET-K
VS Lighting	TW 1914 Tunable	13,8 mm	493 Typ L8	C16142_HEKLA-SOCKET-K
VS Lighting	WU-M-618 DimToWarm	9,8 mm	434 Typ L8	C16142_HEKLA-SOCKET-K

Mögliche Halter / COB Kombinationen / Holder / COB combinations LEDiL Hekla System

COB Hersteller COB Supplier	COB Typ COB Type	LES LES	Halter Holder	Adapter Base part
Xicato	XOB 04	4,5 mm	486 Typ L8	C16142_HEKLA-SOCKET-K
Xicato	XOB 06 (B)	6,0 mm	486 Typ L8	C16142_HEKLA-SOCKET-K
Xicato	XOB 09	9,8 mm	434 Typ L8	C16142_HEKLA-SOCKET-K
Xicato	XOB 14	14,5 mm	433 Typ L8	C16142_HEKLA-SOCKET-K

Mögliche Halter / COB Kombinationen / Holder / COB combinations LEDiL Lena

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Adapter Base part
Bridgelux	Vesta DTW 13/15mm Gen 1,2	491 Typ L2	C13868_LENA-STD-BASE-VERO13-18
Bridgelux	Vesta DTW 18mm Gen 1	505 Typ L3	C13867_LENA-STD-BASE-VERO29
Bridgelux	Vesta Tunable 13mm Gen 2	492 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Bridgelux	Vesta Tunable 15mm Gen 2	482 Typ L2	C13868_LENA-STD-BASE-VERO13-18
Bridgelux	Vesta Tunable 18mm Gen 2	483 Typ L3	C13867_LENA-STD-BASE-VERO29
Bridgelux	Vesta Tunable 22mm Gen 2	494 Typ L3	C13867_LENA-STD-BASE-VERO29
Citizen	CLU 028 / 02J / 02Q	434 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Citizen	CLU 038 / 03H / 03J / 03Q	433 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Citizen	CLU 048 / 04H / 04J / 04Q	431 Typ L3	C13867_LENA-STD-BASE-VERO29
Citizen	CLU 723	477 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Citizen	CLU 733	471 Typ L3	C13867_LENA-STD-BASE-VERO29
Citizen	LCN-C01B2 / C02B2 Tunable	481 Typ L2	C13868_LENA-STD-BASE-VERO13-18
Citizen	LCN-C04B2 / C05B2 Tunable	481 Typ L2	C13868_LENA-STD-BASE-VERO13-18
CREE	CMA 1825 / 1840	437 Typ L1	C13868_LENA-STD-BASE-VERO13-18
CREE	CMA 2550	439 Typ L3	C13867_LENA-STD-BASE-VERO29
CREE	CMA 3090	447 Typ L3	C13867_LENA-STD-BASE-VERO29
CREE	CMB 1818 / 1825	437 Typ L1	C13868_LENA-STD-BASE-VERO13-18
CREE	CMB 1840	457 Typ L1	C13868_LENA-STD-BASE-VERO13-18
CREE	CMB 2550	439 Typ L3	C13867_LENA-STD-BASE-VERO29
CREE	CMB 3090	447 Typ L3	C13867_LENA-STD-BASE-VERO29
CREE	CMT 1407 / 1412 / 1420	434 Typ L1	C13868_LENA-STD-BASE-VERO13-18
CREE	CMT 1922 / 1925 / 1930 / 1945	477 Typ L1	C13868_LENA-STD-BASE-VERO13-18
CREE	CMT 2850 / 2870 / 2890	471 Typ L3	C13867_LENA-STD-BASE-VERO29
CREE	CMU 1003 / 1006 / 1010 / 1013	434 Typ L1	C13868_LENA-STD-BASE-VERO13-18
CREE	CMU 1516 / 1519 / 1526 / 1532	433 Typ L1	C13868_LENA-STD-BASE-VERO13-18
CREE	CMU 2236 / 2239 / 2258 / 2287	471 Typ L3	C13867_LENA-STD-BASE-VERO29
CREE	CXB 1816 / 1820	437 Typ L1	C13868_LENA-STD-BASE-VERO13-18
CREE	CXB 1830	457 Typ L1	C13868_LENA-STD-BASE-VERO13-18
CREE	CXB 2530 / 2540	439 Typ L3	C13867_LENA-STD-BASE-VERO29
CREE	CXB 3050 / 3070	447 Typ L3	C13867_LENA-STD-BASE-VERO29
Edison	2PHE 03 / 06 / 09 / 13	434 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Edison	2PHE 15 / 18 / 24 / 30	433 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Edison	2PHE 55 / 60 / 83	431 Typ L3	C13867_LENA-STD-BASE-VERO29

Mögliche Halter / COB Kombinationen / Holder / COB combinations LEDiL Lena




COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Adapter Base part
Lextar	PB 06 / 09 / 13	434 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Lextar	PB 16 / 19 / 26	433 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Lextar	PB 38 / 54	431 Typ L3	C13867_LENA-STD-BASE-VERO29
Lumileds	Luxeon 1205HD	480 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Lumileds	Luxeon 1204 / 1205	432 Typ L2	C13868_LENA-STD-BASE-VERO13-18
Lumileds	Luxeon 1208 / 1210	432 Typ L2	C13868_LENA-STD-BASE-VERO13-18
Lumileds	Luxeon 1211	431 Typ L3	C13867_LENA-STD-BASE-VERO29
Lumileds	Luxeon 1213 / 1216 / 1812 / 1816	431 Typ L3	C13867_LENA-STD-BASE-VERO29
Lumileds	CS COB L02 / L04	434 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Lumileds	CS COB L06 / L08 / L10	433 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Lumileds	CS COB L11 / L13 / L16	431 Typ L3	C13867_LENA-STD-BASE-VERO29
Lumileds	CS COB R12 / R18	431 Typ L3	C13867_LENA-STD-BASE-VERO29
Lumileds	CX Plus L04Fx / L05Fx / L08Fx	437 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Luminus	CXM-11-xC	433 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Luminus	CGM/CIM/CLM/CXM-14-xC	433 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Luminus	CVM/CXM-18	453 Typ L2	C13868_LENA-STD-BASE-VERO13-18
Luminus	CXM-18 Gen6	431 Typ L3	C13867_LENA-STD-BASE-VERO29
Luminus	CGM/CIM/CLM/CXM-22-xC	431 Typ L3	C13867_LENA-STD-BASE-VERO29
Luminus	CDM-14/CDM-18 DtW	491 Typ L2	C13868_LENA-STD-BASE-VERO13-18
Luminus	CTM-14 TW	442 Typ L2	C13868_LENA-STD-BASE-VERO13-18
Luminus	CTM-18 Gen1 TW	442 Typ L2	C13868_LENA-STD-BASE-VERO13-18
Luminus	CTM-18 Gen2 TW	483 Typ L3	C13867_LENA-STD-BASE-VERO29
Luminus	CTM-22 TW	494 Typ L3	C13867_LENA-STD-BASE-VERO29
Luxtech	COB-WD-17-2420	491 Typ L2	C13868_LENA-STD-BASE-VERO13-18
Nichia	NF..L036B / NF..L048B	438 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Nichia	NF..L060B	438 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Nichia	NV..J048Z / NF..J108B	463 Typ L2	C13868_LENA-STD-BASE-VERO13-18
Nichia	NF..J130B	463 Typ L2	C13868_LENA-STD-BASE-VERO13-18
Nichia	NVCWJ024Z Tunable	498 Typ L2 HV	C13868_LENA-STD-BASE-VERO13-18
Philips	Fortimo SLM12xx .. 2024 G7	432 Typ L2	C13868_LENA-STD-BASE-VERO13-18
Philips	Fortimo SLM12xx .. 2828 G7	431 Typ L3	C13867_LENA-STD-BASE-VERO29
Philips	Fortimo SLM12xx .. 1313 G7N	434 Typ L1	C13868_LENA-STD-BASE-VERO13-18

Mögliche Halter / COB Kombinationen / Holder / COB combinations LEDiL Lena

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Adapter Base part
Philips	Fortimo SLM12xx .. 1919 G7N	433 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Philips	Fortimo SLM12xx .. 2828 G7N	431 Typ L3	C13867_LENA-STD-BASE-VERO29
Philips	Fortimo SLM13xx .. 2024 G8 UHE	432 Typ L2	C13868_LENA-STD-BASE-VERO13-18
Philips	Fortimo SLM13xx .. 2828 G8 UHE	431 Typ L3	C13867_LENA-STD-BASE-VERO29
Prolight Opto	PASB	434 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Prolight Opto	PASQ/PAPQ DimToWarm	434 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Prolight Opto	PDSR DimToWarm	432 Typ L2	C13868_LENA-STD-BASE-VERO13-18
Samsung	LC 020C / 030C / 040C	477 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Samsung	LC 003D / 006D	434 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Samsung	LC 009D / 013D	434 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Samsung	LC 016D / 019D	477 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Samsung	LC 026D / 033D	477 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Samsung	LC 040D / 060D / 080D	431 Typ L3	C13867_LENA-STD-BASE-VERO29
Samsung	LC010T Tunable	501 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Samsung	LC020T Tunable	501 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Samsung	LC035T Tunable	502 Typ L3	C13867_LENA-STD-BASE-VERO29
Seoul	SAW* 1062 / 1063	434 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Seoul	SAW* 1564 / 1565 / 1566	477 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Seoul	SAW* 22AA / 2296	431 Typ L3	C13867_LENA-STD-BASE-VERO29
Seoul	SAW* 2298 / 226A	431 Typ L3	C13867_LENA-STD-BASE-VERO29
Tridonic	SLE ADV8 LES 13	433 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Tridonic	SLE ADV8 LES 15	433 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Tridonic	SLE ADV8 LES 17	431 Typ L3	C13867_LENA-STD-BASE-VERO29
Tridonic	SLE ADV8 LES 21	431 Typ L3	C13867_LENA-STD-BASE-VERO29
Tridonic	SLE SNC8 LES 09	434 Typ L1	C13868_LENA-STD-BASE-VERO13-18
Tridonic	SLE SNC8 LES 15	433 Typ L1	C13868_LENA-STD-BASE-VERO13-18
VS Lighting	DMS 125 / 126 / 128 ***W	433 Typ L1	C13868_LENA-STD-BASE-VERO13-18
VS Lighting	DMS 120 ***W	431 Typ L3	C13867_LENA-STD-BASE-VERO29
VS Lighting	DMS 12C / 18B ***W	431 Typ L3	C13867_LENA-STD-BASE-VERO29
VS Lighting	DMS 1208J	433 Typ L1	C13868_LENA-STD-BASE-VERO13-18
VS Lighting	DMS 1212J / 1812J	431 Typ L3	C13867_LENA-STD-BASE-VERO29
VS Lighting	VCA2 126 / 128	477 Typ L1	C13868_LENA-STD-BASE-VERO13-18

Mögliche Halter / COB Kombinationen / Holder / COB combinations LEDiL Lena

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Adapter Base part
VS Lighting	VCA2 1211 / 1213	471 Typ L3	C13867_LENА-STD-BASE-VERO29
VS Lighting	TW 1914 Tunable	493 Typ L1	C13868_LENА-STD-BASE-VERO13-18
VS Lighting	TW 2820 Tunable	494 Typ L3	C13867_LENА-STD-BASE-VERO29
VS Lighting	WU-M-618 DimToWarm	434 Typ L1	C13868_LENА-STD-BASE-VERO13-18
Xicato	XOB 09	434 Typ L1	C13868_LENА-STD-BASE-VERO13-18
Xicato	XOB 14	433 Typ L1	C13868_LENА-STD-BASE-VERO13-18
Xicato	XOB 23	431 Typ L3	C13867_LENА-STD-BASE-VERO29

LEDiL®	PF-SOCKET SYSTEM	 BARBARA LES: max 14,5mm MIRELLA LES: max 14,5mm
Passende LEDiL Optik Suitable LEDiL optics	BARBARA MIRELLA	
LEDiL Adapter LEDiL adaptor	C13709_PF-SOCKET-VERO13-18	
Hersteller Webseite Manufacturer website	www.ledil.com	
LED Halter B+W LED Holder B+W	4xx / Typ L1 4xx / Typ L2	Für BARBARA-G2 und MIRELLA-G2 ist die passende Lösung unter LEDiL HEKLA aufgeführt Take care that BARBARA-G2 and MIRELLA-G2 requires a different solution available under LEDiL HEKLA
4xx Typ L1 	4xx Typ L2 	C13709_PF-SOCKET-VERO13-18 

Mögliche Halter / COB Kombinationen / Holder / COB combinations LEDiL PF-Socket

COB Hersteller COB Supplier	COB Typ COB Type	LES LES	Halter Holder	Adapter Base part
Bridgelux	V3 HD / V4 HD Gen 7,8	5 mm	460 Typ L1	C13709_PF-SOCKET-VERO13-18
Bridgelux	V6 HD Gen 7,8	7 mm	464 Typ L1	C13709_PF-SOCKET-VERO13-18
Bridgelux	V9 HD / V11 HD Gen 7,8	9 mm	496 Typ L1	C13709_PF-SOCKET-VERO13-18
Bridgelux	V6 Gen 8,9 (just 2 pads!)	9 mm	460 Typ L1	C13709_PF-SOCKET-VERO13-18
Bridgelux	V8 Gen 7,8,9 (4 pads)	9 mm	460 Typ L1	C13709_PF-SOCKET-VERO13-18
Bridgelux	V10 Gen 7,8,9	10 mm	486 Typ L1	C13709_PF-SOCKET-VERO13-18
Bridgelux	V13 Gen 7,8,9	15 mm	477 Typ L1	C13709_PF-SOCKET-VERO13-18
Bridgelux	V15 Gen 7,8,9	15 mm	456 Typ L2	C13709_PF-SOCKET-VERO13-18

Mögliche Halter / COB Kombinationen / Holder / COB combinations LEDiL PF-Socket

COB Hersteller COB Supplier	COB Typ COB Type	LES LES	Halter Holder	Adapter Base part
Bridgelux	Vesta DTW 6/9mm Gen 1,2	9 mm	490 Typ L1	C13709_PF-SOCKET-VERO13-18
Bridgelux	Vesta DTW 13/15mm Gen 1,2	16 mm	491 Typ L2	C13709_PF-SOCKET-VERO13-18
Bridgelux	Vesta Tunable 6mm Gen 2	6 mm	504 Typ L1	C13709_PF-SOCKET-VERO13-18
Bridgelux	Vesta Tunable 9mm Gen 2	10 mm	489 Typ L1	C13709_PF-SOCKET-VERO13-18
Bridgelux	Vesta Tunable 13mm Gen 2	15 mm	492 Typ L1	C13709_PF-SOCKET-VERO13-18
Bridgelux	Vesta Tunable 15mm Gen 2	16 mm	482 Typ L2	C13709_PF-SOCKET-VERO13-18
Citizen	CLU 028 / 02J / 02Q	10 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
Citizen	CLU 038 / 03H / 03J / 03Q	15 mm	433 Typ L1	C13709_PF-SOCKET-VERO13-18
Citizen	CLU 7L3 / 7S3	4 mm	467 Typ L1	C13709_PF-SOCKET-VERO13-18
Citizen	CLU 7R3	4 mm	485 Typ L1	C13709_PF-SOCKET-VERO13-18
Citizen	CLU 702 / 703 / 7A2 / 7A3 / 7B2	6 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
Citizen	CLU 712 / 713	9 mm	477 Typ L1	C13709_PF-SOCKET-VERO13-18
Citizen	CLU 723	11 mm	477 Typ L1	C13709_PF-SOCKET-VERO13-18
Citizen	LCN-C01B2 / C02B2 Tunable	15 mm	481 Typ L2	C13709_PF-SOCKET-VERO13-18
Citizen	LCN-C04B2 / C05B2 Tunable	15 mm	481 Typ L2	C13709_PF-SOCKET-VERO13-18
CREE	CHA 0304 / 0410 / 0612	3 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
CREE	CHA 0825	9 mm	433 Typ L1	C13709_PF-SOCKET-VERO13-18
CREE	CMA 1303 / 1306	6 mm	448 Typ L1	C13709_PF-SOCKET-VERO13-18
CREE	CMA 1516	9 mm	441 Typ L1	C13709_PF-SOCKET-VERO13-18
CREE	CMA 1825 / 1840	14 mm	437 Typ L1	C13709_PF-SOCKET-VERO13-18
CREE	CMB 1304 / 1306	6 mm	448 Typ L1	C13709_PF-SOCKET-VERO13-18
CREE	CMB 1507 / 1510 / 1516	9 mm	441 Typ L1	C13709_PF-SOCKET-VERO13-18
CREE	CMB 1818 / 1825	12 mm	437 Typ L1	C13709_PF-SOCKET-VERO13-18
CREE	CMB 1840	14 mm	457 Typ L1	C13709_PF-SOCKET-VERO13-18
CREE	CMT 1407 / 1412 / 1420	10 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
CREE	CMT 1922 / 1925 / 1930 / 1945	15 mm	477 Typ L1	C13709_PF-SOCKET-VERO13-18
CREE	CMU 1003 / 1006 / 1010 / 1013	10 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
CREE	CMU 1516 / 1519 / 1526 / 1532	15 mm	433 Typ L1	C13709_PF-SOCKET-VERO13-18
CREE	CXB 1304 / 1310	6 mm	448 Typ L1	C13709_PF-SOCKET-VERO13-18
CREE	CXB 1507 / 1512 / 1520	9 mm	441 Typ L1	C13709_PF-SOCKET-VERO13-18
CREE	CXB 1816 / 1820	12 mm	437 Typ L1	C13709_PF-SOCKET-VERO13-18
CREE	CXB 1830	14 mm	457 Typ L1	C13709_PF-SOCKET-VERO13-18
Edison	2PHE 03 / 06 / 09 / 13	10 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
Edison	2PHE 15 / 18 / 24 / 30	16 mm	433 Typ L1	C13709_PF-SOCKET-VERO13-18

Mögliche Halter / COB Kombinationen / Holder / COB combinations LEDiL PF-Socket




COB Hersteller COB Supplier	COB Typ COB Type	LES LES	Halter Holder	Adapter Base part
Lextar	PB 06 / 09 / 13	10 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
Lextar	PB 16 / 19 / 26	15 mm	433 Typ L1	C13709_PF-SOCKET-VERO13-18
Lumileds	Luxeon 1202s / 1202HD	7 mm	452 Typ L1	C13709_PF-SOCKET-VERO13-18
Lumileds	Luxeon 1202 / 1203 / 1204HD	9 mm	480 Typ L1	C13709_PF-SOCKET-VERO13-18
Lumileds	Luxeon 1205HD	11 mm	480 Typ L1	C13709_PF-SOCKET-VERO13-18
Lumileds	Luxeon 1204 / 1205	13 mm	432 Typ L2	C13709_PF-SOCKET-VERO13-18
Lumileds	Luxeon 1208 / 1210	15 mm	432 Typ L2	C13709_PF-SOCKET-VERO13-18
Lumileds	CS COB L02 / L04	10 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
Lumileds	CS COB L06 / L08 / L10	15 mm	433 Typ L1	C13709_PF-SOCKET-VERO13-18
Lumileds	CX Plus HD S01H4, S0xH6	6 mm	448 Typ L1	C13709_PF-SOCKET-VERO13-18
Lumileds	CX Plus HD S04H9	9 mm	4xx Typ L1	C13709_PF-SOCKET-VERO13-18
Lumileds	CX Plus S01Fx / S02Fx	5 mm	448 Typ L1	C13709_PF-SOCKET-VERO13-18
Lumileds	CX Plus M02Fx / M03Fx	9 mm	441 Typ L1	C13709_PF-SOCKET-VERO13-18
Lumileds	CX Plus L04Fx / L05Fx / L08Fx	14 mm	437 Typ L1	C13709_PF-SOCKET-VERO13-18
Luminus	CXM-3-xC	4 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
Luminus	CHM-4-BH / CXM-4-xC	5 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
Luminus	CHM-6-BH / CXM-6-xC	6 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
Luminus	CIM/CLM/CXM-9-xC	9 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
Luminus	CLM/CXM-9-xA	10 mm	461 Typ L1	C13709_PF-SOCKET-VERO13-18
Luminus	CHM-9-BH	9 mm	433 Typ L1	C13709_PF-SOCKET-VERO13-18
Luminus	CXM-11-xC	12 mm	433 Typ L1	C13709_PF-SOCKET-VERO13-18
Luminus	CGM/CIM/CLM/CXM-14-xC	15 mm	433 Typ L1	C13709_PF-SOCKET-VERO13-18
Luminus	CVM/CXM-18	18 mm	453 Typ L2	C13709_PF-SOCKET-VERO13-18
Luminus	CDM-6 / CDM-9Gen1 DtW	10 mm	490 Typ L1	C13709_PF-SOCKET-VERO13-18
Luminus	CDM-9 Gen2 DtW	9 mm	491 Typ L2	C13709_PF-SOCKET-VERO13-18
Luminus	CDM-14/CDM-18 DtW	17 mm	491 Typ L2	C13709_PF-SOCKET-VERO13-18
Luminus	CTM-6 / CTM-9 TW	10 mm	495 Typ L1	C13709_PF-SOCKET-VERO13-18
Luminus	CTM-14 TW	18 mm	442 Typ L2	C13709_PF-SOCKET-VERO13-18
Luminus	CTM-18 Gen1 TW	18 mm	442 Typ L2	C13709_PF-SOCKET-VERO13-18
Luxtech	COB-WD-10-1512	8 mm	479 Typ L1	C13709_PF-SOCKET-VERO13-18
Luxtech	COB-WD-17-2420	15 mm	491 Typ L2	C13709_PF-SOCKET-VERO13-18
Nichia	NV..S007Z / NF..T012B	7 mm	452 Typ L1	C13709_PF-SOCKET-VERO13-18

Mögliche Halter / COB Kombinationen / Holder / COB combinations LEDiL PF-Socket

COB Hersteller COB Supplier	COB Typ COB Type	LES LES	Halter Holder	Adapter Base part
Nichia	NF..S024B / NT..S024B	7 mm	452 Typ L1	C13709_PF-SOCKET-VERO13-18
Nichia	NJ..S024Z	7 mm	452 Typ L1	C13709_PF-SOCKET-VERO13-18
Nichia	NV..L016Z / NV..L024Z	9 mm	438 Typ L1	C13709_PF-SOCKET-VERO13-18
Nichia	NF..L036B / NF..L048B	12 mm	438 Typ L1	C13709_PF-SOCKET-VERO13-18
Nichia	NF..L060B	12 mm	438 Typ L1	C13709_PF-SOCKET-VERO13-18
Nichia	NV..J048Z / NF..J108B	15 mm	463 Typ L2	C13709_PF-SOCKET-VERO13-18
Nichia	NF..J130B	15 mm	463 Typ L2	C13709_PF-SOCKET-VERO13-18
Nichia	NJNWS012Z Tunable	6 mm	495 Typ L1 HV	C13709_PF-SOCKET-VERO13-18
Nichia	NJCWL024Z Tunable	7 mm	497 Typ L1 HV	C13709_PF-SOCKET-VERO13-18
Nichia	NVCWJ024Z Tunable	11 mm	498 Typ L2 HV	C13709_PF-SOCKET-VERO13-18
Philips	Fortimo SLM12xx .. 1215 G7	7 mm	452 Typ L1	C13709_PF-SOCKET-VERO13-18
Philips	Fortimo SLM12xx .. 1619 G7	9 mm	480 Typ L1	C13709_PF-SOCKET-VERO13-18
Philips	Fortimo SLM12xx .. 2024 G7	15 mm	432 Typ L2	C13709_PF-SOCKET-VERO13-18
Philips	Fortimo SLM12xx .. 1313 G7N	10 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
Philips	Fortimo SLM12xx .. 1919 G7N	15 mm	433 Typ L1	C13709_PF-SOCKET-VERO13-18
Philips	Fortimo SLM13xx .. 2024 G8 UHE	15 mm	432 Typ L2	C13709_PF-SOCKET-VERO13-18
Philips	Fortimo L06A 1313 G7N Tunable	7 mm	509 Typ L1	C13709_PF-SOCKET-VERO13-18
Philips	Fortimo L09A 1919 G7N Tunable	9 mm	501 Typ L1	C13709_PF-SOCKET-VERO13-18
Prolight Opto	PASB	10 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
Prolight Opto	PASQ/PAPQ DimToWarm	10 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
Prolight Opto	PDSQ DimToWarm	8 mm	490 Typ L1	C13709_PF-SOCKET-VERO13-18
Prolight Opto	PDSR DimToWarm	15 mm	432 Typ L2	C13709_PF-SOCKET-VERO13-18
Samsung	LC 010C	6 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
Samsung	LC 020C / 030C / 040C	12 mm	477 Typ L1	C13709_PF-SOCKET-VERO13-18
Samsung	LC 003D / 006D	10 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
Samsung	LC 009D / 013D	10 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
Samsung	LC 016D / 019D	16 mm	477 Typ L1	C13709_PF-SOCKET-VERO13-18
Samsung	LC 026D / 033D	16 mm	477 Typ L1	C13709_PF-SOCKET-VERO13-18
Samsung	LC010T Tunable	10 mm	501 Typ L1	C13709_PF-SOCKET-VERO13-18
Samsung	LC020T Tunable	13 mm	501 Typ L1	C13709_PF-SOCKET-VERO13-18
Seoul	SAW* 0661	6 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
Seoul	SAW* 1062 / 1063	10 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
Seoul	SAW* 1564 / 1565 / 1566	15 mm	477 Typ L1	C13709_PF-SOCKET-VERO13-18

Mögliche Halter / COB Kombinationen / Holder / COB combinations LEDiL PF-Socket

COB Hersteller COB Supplier	COB Typ COB Type	LES LES	Halter Holder	Adapter Base part
Tridonic	SLE ADV8 LES 04 / 06	9 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
Tridonic	SLE ADV8 LES 09	9 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
Tridonic	SLE ADV8 LES 13	13 mm	433 Typ L1	C13709_PF-SOCKET-VERO13-18
Tridonic	SLE ADV8 LES 15	15 mm	433 Typ L1	C13709_PF-SOCKET-VERO13-18
Tridonic	SLE SNC8 LES 06	6 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
Tridonic	SLE SNC8 LES 09	10 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
Tridonic	SLE SNC8 LES 15	15 mm	433 Typ L1	C13709_PF-SOCKET-VERO13-18
VS Lighting	DMS 102 ***W	6 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
VS Lighting	DMS 124 ***W	9 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
VS Lighting	DMS 125 / 126 / 128 ***W	14 mm	433 Typ L1	C13709_PF-SOCKET-VERO13-18
VS Lighting	DMS 1208J	15 mm	433 Typ L1	C13709_PF-SOCKET-VERO13-18
VS Lighting	VCA 042	4 mm	486 Typ L1	C13709_PF-SOCKET-VERO13-18
VS Lighting	VCA2 122 / 123 / 124	9 mm	486 Typ L1	C13709_PF-SOCKET-VERO13-18
VS Lighting	VCA2 126 / 128	14 mm	477 Typ L1	C13709_PF-SOCKET-VERO13-18
VS Lighting	TW 1914 Tunable	14 mm	493 Typ L1	C13709_PF-SOCKET-VERO13-18
VS Lighting	WU-M-618 DimToWarm	10 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
Xicato	XOB 04	5 mm	486 Typ L1	C13709_PF-SOCKET-VERO13-18
Xicato	XOB 06 (B)	6 mm	486 Typ L1	C13709_PF-SOCKET-VERO13-18
Xicato	XOB 09	10 mm	434 Typ L1	C13709_PF-SOCKET-VERO13-18
Xicato	XOB 14	15 mm	433 Typ L1	C13709_PF-SOCKET-VERO13-18

LEDiL®	SAGA	
LEDiL Linse LEDiL lense	CN13990_SAGA-HB-IP-WHT FCA14933_SAGA-S-WHT	
Hersteller Webseite Manufacturer website	www.ledil.com	
LED Halter B+W LED Holder B+W	4xx / Typ L6	
4xx Typ L6 		CN13990_SAGA-HB-IP-WHT 

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL Saga**

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Bridgelux	V3 HD / V4 HD Gen 7,8	460 Typ L6	CN13990_SAGA-HB-IP-WHT
Bridgelux	V6 HD Gen 7,8	464 Typ L6	CN13990_SAGA-HB-IP-WHT
Bridgelux	V9 HD / V11 HD Gen 7,8	496 Typ L6	CN13990_SAGA-HB-IP-WHT
Bridgelux	V6 Gen 8,9 (just 2 pads!)	460 Typ L6	CN13990_SAGA-HB-IP-WHT
Bridgelux	V8 Gen 7,8,9 (4 pads)	460 Typ L6	CN13990_SAGA-HB-IP-WHT
Bridgelux	V10 Gen 7,8,9	486 Typ L6	CN13990_SAGA-HB-IP-WHT
Bridgelux	V13 Gen 7,8,9	477 Typ L6	CN13990_SAGA-HB-IP-WHT
Bridgelux	V15 Gen 7,8,9	456 Typ L6	CN13990_SAGA-HB-IP-WHT
Bridgelux	Vesta DTW 6/9mm Gen 1,2	490 Typ L6	CN13990_SAGA-HB-IP-WHT
Bridgelux	Vesta Tunable 6mm Gen 2	504 Typ L6	CN13990_SAGA-HB-IP-WHT
Bridgelux	Vesta Tunable 9mm Gen 2	489 Typ L6	CN13990_SAGA-HB-IP-WHT
Bridgelux	Vesta Tunable 13mm Gen 2	492 Typ L6	CN13990_SAGA-HB-IP-WHT

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL Saga**

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Citizen	CLU 028 / 02J / 02Q	434 Typ L6	CN13990_SAGA-HB-IP-WHT
Citizen	CLU 038 / 03H / 03J / 03Q	433 Typ L6	CN13990_SAGA-HB-IP-WHT
Citizen	CLU 702 / 703 / 7A2 / 7A3 / 7B2	434 Typ L6	CN13990_SAGA-HB-IP-WHT
Citizen	CLU 712 / 713	477 Typ L6	CN13990_SAGA-HB-IP-WHT
Citizen	CLU 723	477 Typ L6	CN13990_SAGA-HB-IP-WHT
Citizen	LCN-C01B2 / C02B2 Tunable	481 Typ L6	CN13990_SAGA-HB-IP-WHT
Citizen	LCN-C04B2 / C05B2 Tunable	481 Typ L6	CN13990_SAGA-HB-IP-WHT
CREE	CHA 0825	433 Typ L6	CN13990_SAGA-HB-IP-WHT
CREE	CMA 1303 / 1306	448 Typ L6	CN13990_SAGA-HB-IP-WHT
CREE	CMA 1516	441 Typ L6	CN13990_SAGA-HB-IP-WHT
CREE	CMA 1825 / 1840	437 Typ L6	CN13990_SAGA-HB-IP-WHT
CREE	CMB 1304 / 1306	448 Typ L6	CN13990_SAGA-HB-IP-WHT
CREE	CMB 1507 / 1510 / 1516	441 Typ L6	CN13990_SAGA-HB-IP-WHT
CREE	CMB 1818 / 1825	437 Typ L6	CN13990_SAGA-HB-IP-WHT
CREE	CMB 1840	457 Typ L6	CN13990_SAGA-HB-IP-WHT
CREE	CMT 1407 / 1412 / 1420	434 Typ L6	CN13990_SAGA-HB-IP-WHT
CREE	CMT 1922 / 1925 / 1930 / 1945	477 Typ L6	CN13990_SAGA-HB-IP-WHT
CREE	CMU 1003 / 1006 / 1010 / 1013	434 Typ L6	CN13990_SAGA-HB-IP-WHT
CREE	CMU 1516 / 1519 / 1526 / 1532	433 Typ L6	CN13990_SAGA-HB-IP-WHT
CREE	CXB 1304 / 1310	448 Typ L6	CN13990_SAGA-HB-IP-WHT
CREE	CXB 1507 / 1512 / 1520	441 Typ L6	CN13990_SAGA-HB-IP-WHT
CREE	CXB 1816 / 1820	437 Typ L6	CN13990_SAGA-HB-IP-WHT
CREE	CXB 1830	457 Typ L6	CN13990_SAGA-HB-IP-WHT
Edison	2PHE 03 / 06 / 09 / 13	434 Typ L6	CN13990_SAGA-HB-IP-WHT
Lextar	PB 06 / 09 / 13	434 Typ L6	CN13990_SAGA-HB-IP-WHT
Lextar	PB 16 / 19 / 26	433 Typ L6	CN13990_SAGA-HB-IP-WHT
Lumileds	Luxeon 1202s / 1202HD	452 Typ L6	CN13990_SAGA-HB-IP-WHT
Lumileds	Luxeon 1202 / 1203 / 1204HD	480 Typ L6	CN13990_SAGA-HB-IP-WHT
Lumileds	Luxeon 1205HD	480 Typ L6	CN13990_SAGA-HB-IP-WHT
Lumileds	Luxeon 1204 / 1205	432 Typ L6	CN13990_SAGA-HB-IP-WHT
Lumileds	Luxeon 1208 / 1210	432 Typ L6	CN13990_SAGA-HB-IP-WHT
Lumileds	CS COB L02 / L04	434 Typ L6	CN13990_SAGA-HB-IP-WHT
Lumileds	CS COB L06 / L08 / L10	433 Typ L6	CN13990_SAGA-HB-IP-WHT

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL Saga**




COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Lumileds	CX Plus HD S01H4, S0xH6	448 Typ L6	CN13990_SAGA-HB-IP-WHT
Lumileds	CX Plus HD S04H9	4xx Typ L6	CN13990_SAGA-HB-IP-WHT
Lumileds	CX Plus M02Fx / M03Fx	441 Typ L6	CN13990_SAGA-HB-IP-WHT
Lumileds	CX Plus L04Fx / L05Fx / L08Fx	437 Typ L6	CN13990_SAGA-HB-IP-WHT
Luminus	CHM-6-BH / CXM-6-xC	434 Typ L6	CN13990_SAGA-HB-IP-WHT
Luminus	CIM/CLM/CXM-9-xC	434 Typ L6	CN13990_SAGA-HB-IP-WHT
Luminus	CLM/CXM-9-xA	461 Typ L6	CN13990_SAGA-HB-IP-WHT
Luminus	CHM-9-BH	433 Typ L6	CN13990_SAGA-HB-IP-WHT
Luminus	CXM-11-xC	433 Typ L6	CN13990_SAGA-HB-IP-WHT
Luminus	CGM/CIM/CLM/CXM-14-xC	433 Typ L6	CN13990_SAGA-HB-IP-WHT
Luminus	CDM-6 / CDM-9Gen1 DtW	490 Typ L6	CN13990_SAGA-HB-IP-WHT
Luminus	CDM-9 Gen2 DtW	491 Typ L6	CN13990_SAGA-HB-IP-WHT
Luminus	CTM-6 / CTM-9 TW	495 Typ L6	CN13990_SAGA-HB-IP-WHT
Luminus	CTM-14 RGBW	500 Typ L6	CN13990_SAGA-HB-IP-WHT
Luxtech	COB-WD-10-1512	479 Typ L6	CN13990_SAGA-HB-IP-WHT
Luxtech	COB-WD-17-2420	491 Typ L6	CN13990_SAGA-HB-IP-WHT
Luxtech	COB-DN-16-2420	442 Typ L6	CN13990_SAGA-HB-IP-WHT
Nichia	NV..S007Z / NF..T012B	452 Typ L6	CN13990_SAGA-HB-IP-WHT
Nichia	NF..S024B / NT..S024B	452 Typ L6	CN13990_SAGA-HB-IP-WHT
Nichia	NJ..S024Z	452 Typ L6	CN13990_SAGA-HB-IP-WHT
Nichia	NV..L016Z / NV..L024Z	438 Typ L6	CN13990_SAGA-HB-IP-WHT
Nichia	NF..L036B / NF..L048B	438 Typ L6	CN13990_SAGA-HB-IP-WHT
Nichia	NF..L060B	438 Typ L6	CN13990_SAGA-HB-IP-WHT
Nichia	NV..J048Z / NF..J108B	463 Typ L6	CN13990_SAGA-HB-IP-WHT
Nichia	NF..J130B	463 Typ L6	CN13990_SAGA-HB-IP-WHT
Nichia	NJNWS012Z Tunable	495 Typ L6 HV	CN13990_SAGA-HB-IP-WHT
Nichia	NJCWL024Z Tunable	497 Typ L6 HV	CN13990_SAGA-HB-IP-WHT
Nichia	NVCWJ024Z Tunable	498 Typ L6 HV	CN13990_SAGA-HB-IP-WHT
Philips	Fortimo SLM12xx .. 1215 G7	452 Typ L6	CN13990_SAGA-HB-IP-WHT
Philips	Fortimo SLM12xx .. 1619 G7	480 Typ L6	CN13990_SAGA-HB-IP-WHT
Philips	Fortimo SLM12xx .. 2024 G7	432 Typ L6	CN13990_SAGA-HB-IP-WHT
Philips	Fortimo SLM12xx .. 1313 G7N	434 Typ L6	CN13990_SAGA-HB-IP-WHT
Philips	Fortimo SLM12xx .. 1919 G7N	433 Typ L6	CN13990_SAGA-HB-IP-WHT

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL Saga**

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Philips	Fortimo SLM13xx .. 2024 G8 UHE	432 Typ L6	CN13990_SAGA-HB-IP-WHT
Philips	Fortimo L06A 1313 G7N Tunable	509 Typ L6	CN13990_SAGA-HB-IP-WHT
Philips	Fortimo L09A 1919 G7N Tunable	501 Typ L6	CN13990_SAGA-HB-IP-WHT
Prolight Opto	PASB	434 Typ L6	CN13990_SAGA-HB-IP-WHT
Prolight Opto	PASQ/PAPQ DimToWarm	434 Typ L6	CN13990_SAGA-HB-IP-WHT
Prolight Opto	PDSQ DimToWarm	490 Typ L6	CN13990_SAGA-HB-IP-WHT
Prolight Opto	PDSR DimToWarm	432 Typ L6	CN13990_SAGA-HB-IP-WHT
Prolight Opto	PDSJ Tunable	442 Typ L6	CN13990_SAGA-HB-IP-WHT
Samsung	LC 010C	434 Typ L6	CN13990_SAGA-HB-IP-WHT
Samsung	LC 020C / 030C / 040C	477 Typ L6	CN13990_SAGA-HB-IP-WHT
Samsung	LC 003D / 006D	434 Typ L6	CN13990_SAGA-HB-IP-WHT
Samsung	LC 009D / 013D	434 Typ L6	CN13990_SAGA-HB-IP-WHT
Samsung	LC010T Tunable	501 Typ L6	CN13990_SAGA-HB-IP-WHT
Samsung	LC020T Tunable	501 Typ L6	CN13990_SAGA-HB-IP-WHT
Seoul	SAW* 0661	434 Typ L6	CN13990_SAGA-HB-IP-WHT
Seoul	SAW* 1062 / 1063	434 Typ L6	CN13990_SAGA-HB-IP-WHT
Seoul	SAW* 1564 / 1565 / 1566	477 Typ L6	CN13990_SAGA-HB-IP-WHT
Tridonic	SLE ADV8 LES 04 / 06	434 Typ L6	CN13990_SAGA-HB-IP-WHT
Tridonic	SLE ADV8 LES 09	434 Typ L6	CN13990_SAGA-HB-IP-WHT
Tridonic	SLE ADV8 LES 13	433 Typ L6	CN13990_SAGA-HB-IP-WHT
Tridonic	SLE ADV8 LES 15	433 Typ L6	CN13990_SAGA-HB-IP-WHT
Tridonic	SLE SNC8 LES 06	434 Typ L6	CN13990_SAGA-HB-IP-WHT
Tridonic	SLE SNC8 LES 09	434 Typ L6	CN13990_SAGA-HB-IP-WHT
Tridonic	SLE SNC8 LES 15	433 Typ L6	CN13990_SAGA-HB-IP-WHT
VS Lighting	DMS 102 ***W	434 Typ L6	CN13990_SAGA-HB-IP-WHT
VS Lighting	DMS 124 ***W	434 Typ L6	CN13990_SAGA-HB-IP-WHT
VS Lighting	DMS 125 / 126 / 128 ***W	433 Typ L6	CN13990_SAGA-HB-IP-WHT
VS Lighting	DMS 1208J	433 Typ L6	CN13990_SAGA-HB-IP-WHT
VS Lighting	VCA2 122 / 123 / 124	486 Typ L6	CN13990_SAGA-HB-IP-WHT
VS Lighting	VCA2 126 / 128	477 Typ L6	CN13990_SAGA-HB-IP-WHT
VS Lighting	TW 1914 Tunable	493 Typ L6	CN13990_SAGA-HB-IP-WHT
VS Lighting	WU-M-618 DimToWarm	434 Typ L6	CN13990_SAGA-HB-IP-WHT

Mögliche Halter / COB Kombinationen / Holder / COB combinations LEDiL Saga

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Xicato	XOB 06 (B)	486 Typ L6	CN13990_SAGA-HB-IP-WHT
Xicato	XOB 09	434 Typ L6	CN13990_SAGA-HB-IP-WHT
Xicato	XOB 14	433 Typ L6	CN13990_SAGA-HB-IP-WHT

LEDiL®	STELLA (Type L1)	
STELLA-A		
Passende LEDiL Optik Suitable LEDiL optics		
LEDiL part numbers		
Hersteller Webseite Manufacturer website		
www.ledil.com		
LED Halter B+W LED Holder B+W		
4xx / Typ L1		
		STELLA-A
		

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL Stella (L1)**

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Bridgelux	V9 HD / V11 HD Gen 7,8	496 Typ L1	FN13323_STELLA-A
Bridgelux	V6 Gen 8,9 (just 2 pads!)	460 Typ L1	FN13323_STELLA-A
Bridgelux	V8 Gen 7,8,9 (4 pads)	460 Typ L1	FN13323_STELLA-A
Bridgelux	V10 Gen 7,8,9	486 Typ L1	FN13323_STELLA-A
Bridgelux	V13 Gen 7,8,9	477 Typ L1	FN13323_STELLA-A
Bridgelux	Vesta DTW 6/9mm Gen 1,2	490 Typ L1	FN13323_STELLA-A
Bridgelux	Vesta Tunable 9mm Gen 2	489 Typ L1	FN13323_STELLA-A
Bridgelux	Vesta Tunable 13mm Gen 2	492 Typ L1	FN13323_STELLA-A
Citizen	CLU 028 / 02J / 02Q	434 Typ L1	FN13323_STELLA-A
Citizen	CLU 038 / 03H / 03J / 03Q	433 Typ L1	FN13323_STELLA-A
Citizen	CLU 712 / 713	477 Typ L1	FN13323_STELLA-A

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL Stella (L1)**




COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Citizen	CLU 723	477 Typ L1	FN13323_STELLA-A
CREE	CHA 0825	433 Typ L1	FN13323_STELLA-A
CREE	CMA 1516	441 Typ L1	FN13323_STELLA-A
CREE	CMA 1825 / 1840	437 Typ L1	FN13323_STELLA-A
CREE	CMB 1507 / 1510 / 1516	441 Typ L1	FN13323_STELLA-A
CREE	CMB 1818 / 1825	437 Typ L1	FN13323_STELLA-A
CREE	CMB 1840	457 Typ L1	FN13323_STELLA-A
CREE	CMT 1407 / 1412 / 1420	434 Typ L1	FN13323_STELLA-A
CREE	CMT 1922 / 1925 / 1930 / 1945	477 Typ L1	FN13323_STELLA-A
CREE	CMU 1003 / 1006 / 1010 / 1013	434 Typ L1	FN13323_STELLA-A
CREE	CMU 1516 / 1519 / 1526 / 1532	433 Typ L1	FN13323_STELLA-A
CREE	CXB 1507 / 1512 / 1520	441 Typ L1	FN13323_STELLA-A
CREE	CXB 1816 / 1820	437 Typ L1	FN13323_STELLA-A
CREE	CXB 1830	457 Typ L1	FN13323_STELLA-A
Edison	2PHE 03 / 06 / 09 / 13	434 Typ L1	FN13323_STELLA-A
Edison	2PHE 15 / 18 / 24 / 30	433 Typ L1	FN13323_STELLA-A
Lextar	PB 06 / 09 / 13	434 Typ L1	FN13323_STELLA-A
Lextar	PB 16 / 19 / 26	433 Typ L1	FN13323_STELLA-A
Lumileds	Luxeon 1202 / 1203 / 1204HD	480 Typ L1	FN13323_STELLA-A
Lumileds	Luxeon 1205HD	480 Typ L1	FN13323_STELLA-A
Lumileds	CS COB L02 / L04	434 Typ L1	FN13323_STELLA-A
Lumileds	CS COB L06 / L08 / L10	433 Typ L1	FN13323_STELLA-A
Lumileds	CX Plus HD S04H9	4xx Typ L1	FN13323_STELLA-A
Lumileds	CX Plus M02Fx / M03Fx	441 Typ L1	FN13323_STELLA-A
Lumileds	CX Plus L04Fx / L05Fx / L08Fx	437 Typ L1	FN13323_STELLA-A
Luminus	CIM/CLM/CXM-9-xC	434 Typ L1	FN13323_STELLA-A
Luminus	CLM/CXM-9-xA	461 Typ L1	FN13323_STELLA-A
Luminus	CHM-9-BH	433 Typ L1	FN13323_STELLA-A
Luminus	CXM-11-xC	433 Typ L1	FN13323_STELLA-A
Luminus	CGM/CIM/CLM/CXM-14-xC	433 Typ L1	FN13323_STELLA-A
Luminus	CDM-6 / CDM-9Gen1 DtW	490 Typ L1	FN13323_STELLA-A
Luminus	CTM-6 / CTM-9 TW	495 Typ L1	FN13323_STELLA-A

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL Stella (L1)**

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Nichia	NV..L016Z / NV..L024Z	438 Typ L1	FN13323_STELLA-A
Nichia	NF..L036B / NF..L048B	438 Typ L1	FN13323_STELLA-A
Nichia	NF..L060B	438 Typ L1	FN13323_STELLA-A
Philips	Fortimo SLM12xx .. 1619 G7	480 Typ L1	FN13323_STELLA-A
Philips	Fortimo SLM12xx .. 1313 G7N	434 Typ L1	FN13323_STELLA-A
Philips	Fortimo SLM12xx .. 1919 G7N	433 Typ L1	FN13323_STELLA-A
Philips	Fortimo L09A 1919 G7N Tunable	501 Typ L1	FN13323_STELLA-A
Prolight Opto	PASB	434 Typ L1	FN13323_STELLA-A
Prolight Opto	PASQ/PAPQ DimToWarm	434 Typ L1	FN13323_STELLA-A
Samsung	LC 020C / 030C / 040C	477 Typ L1	FN13323_STELLA-A
Samsung	LC 003D / 006D	434 Typ L1	FN13323_STELLA-A
Samsung	LC 009D / 013D	434 Typ L1	FN13323_STELLA-A
Samsung	LC 016D / 019D	477 Typ L1	FN13323_STELLA-A
Samsung	LC 026D / 033D	477 Typ L1	FN13323_STELLA-A
Samsung	LC010T Tunable	501 Typ L1	FN13323_STELLA-A
Samsung	LC020T Tunable	501 Typ L1	FN13323_STELLA-A
Seoul	SAW* 1062 / 1063	434 Typ L1	FN13323_STELLA-A
Seoul	SAW* 1564 / 1565 / 1566	477 Typ L1	FN13323_STELLA-A
Tridonic	SLE ADV8 LES 04 / 06	434 Typ L1	FN13323_STELLA-A
Tridonic	SLE ADV8 LES 09	434 Typ L1	FN13323_STELLA-A
Tridonic	SLE ADV8 LES 13	433 Typ L1	FN13323_STELLA-A
Tridonic	SLE ADV8 LES 15	433 Typ L1	FN13323_STELLA-A
Tridonic	SLE SNC8 LES 09	434 Typ L1	FN13323_STELLA-A
Tridonic	SLE SNC8 LES 15	433 Typ L1	FN13323_STELLA-A
VS Lighting	DMS 124 ***W	434 Typ L1	FN13323_STELLA-A
VS Lighting	DMS 125 / 126 / 128 ***W	433 Typ L1	FN13323_STELLA-A
VS Lighting	DMS 1208J	433 Typ L1	FN13323_STELLA-A
VS Lighting	VCA2 122 / 123 / 124	486 Typ L1	FN13323_STELLA-A
VS Lighting	VCA2 126 / 128	477 Typ L1	FN13323_STELLA-A

Mögliche Halter / COB Kombinationen / Holder / COB combinations LEDiL Stella (L1)

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
VS Lighting	TW 1914 Tunable	493 Typ L1	FN13323_STELLA-A
VS Lighting	WU-M-618 DimToWarm	434 Typ L1	FN13323_STELLA-A
Xicato	XOB 09	434 Typ L1	FN13323_STELLA-A
Xicato	XOB 14	433 Typ L1	FN13323_STELLA-A

LEDiL®	STELLA (Type L4)	
Passende LEDiL Optik Suitable LEDiL optics	STELLA-HB STELLA-HB-WWW STELLA-FRESNEL STELLA-RS STELLA-G2-VSM LEDiL part numbers	
Hersteller Webseite Manufacturer website	www.ledil.com	
LED Halter B+W LED Holder B+W	4xx / Typ L4	
4xx / Typ L4		eg. STELLA-HB
		

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL STELLA (L4)**




COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Bridgelux	V18 Gen 7,8,9	462 Typ L4	see LEDiL website
Bridgelux	V22 Gen 7,8,9	431 Typ L4	see LEDiL website
Bridgelux	Vesta DTW 18mm Gen 1	505 Typ L4	see LEDiL website
Bridgelux	Vesta DTW 29mm Gen 1	506 Typ L4	see LEDiL website
Bridgelux	Vesta Tunable 18mm Gen 2	483 Typ L4	see LEDiL website
Bridgelux	Vesta Tunable 22mm Gen 2	494 Typ L4	see LEDiL website
Bridgelux	Vesta Tunable 29mm Gen 2	503 Typ L4	see LEDiL website
Citizen	CLU 048 / 04H / 04J / 04Q	431 Typ L4	see LEDiL website

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL STELLA (L4)**

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Citizen	CLU 058 / 05Q ..1825	458 Typ L4	see LEDiL website
Citizen	CLU 058 / 05H / 05Q ..3618	458 Typ L4 HV	see LEDiL website
Citizen	CLU 550 / 551	476 Typ L4 HV	see LEDiL website
Citizen	LCN-C07A2 Tunable	507 Typ L4	see LEDiL website
CREE	CMA 2550	439 Typ L4	see LEDiL website
CREE	CMA 3090	447 Typ L4	see LEDiL website
CREE	CMB 2550	439 Typ L4	see LEDiL website
CREE	CMB 3090	447 Typ L4	see LEDiL website
CREE	CMT 2850 / 2870 / 2890	471 Typ L4	see LEDiL website
CREE	CMU 2236 / 2239 / 2258 / 2287	471 Typ L4	see LEDiL website
CREE	CXB 2530 / 2540	439 Typ L4	see LEDiL website
CREE	CXB 3050 / 3070	447 Typ L4	see LEDiL website
CREE	CXB 3590	449 Typ L4	see LEDiL website
Edison	2PHE 55 / 60 / 83	431 Typ L4	see LEDiL website
Lextar	PB 38 / 54	431 Typ L4	see LEDiL website
Lumileds	Luxeon 1211	431 Typ L4	see LEDiL website
Lumileds	Luxeon 1213 / 1216 / 1812 / 1816	431 Typ L4	see LEDiL website
Lumileds	Luxeon 1321 / 1825	458 Typ L4	see LEDiL website
Lumileds	CS COB L11 / L13 / L16	431 Typ L4	see LEDiL website
Lumileds	CS COB R12 / R18	431 Typ L4	see LEDiL website
Luminus	CXM-18 Gen6	431 Typ L4	see LEDiL website
Luminus	CGM/CIM/CLM/CXM-22-xC	431 Typ L4	see LEDiL website
Luminus	CVM/CXM-27	454 Typ L4	see LEDiL website
Luminus	CVM/CXM-32	458 Typ L4	see LEDiL website
Luminus	CTM-18 Gen2 TW	483 Typ L4	see LEDiL website
Luminus	CTM-22 TW	494 Typ L4	see LEDiL website
Nichia	NF..H306B	488 Typ L4 HV	see LEDiL website
Philips	Fortimo SLM12xx .. 2828 G7	431 Typ L4	see LEDiL website

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL STELLA (L4)**

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Philips	Fortimo SLM12xx .. 2828 G7N	431 Typ L4	see LEDiL website
Philips	Fortimo SLM13xx .. 2828 G8 UHE	431 Typ L4	see LEDiL website
Samsung	LC 040D / 060D / 080D	431 Typ L4	see LEDiL website
Samsung	LC035T Tunable	502 Typ L4	see LEDiL website
Seoul	SAW* 22AA / 2296	431 Typ L4	see LEDiL website
Seoul	SAW* 2298 / 226A	431 Typ L4	see LEDiL website
Seoul	SAW* 33EA / 33GC	458 Typ L4 HV	see LEDiL website
Tridonic	SLE ADV8 LES 21	431 Typ L4	see LEDiL website
VS Lighting	DMS 12C / 18B ***W	431 Typ L4	see LEDiL website
VS Lighting	DMS 1212J / 1812J	431 Typ L4	see LEDiL website
VS Lighting	VCA2 1211 / 1213	471 Typ L4	see LEDiL website
VS Lighting	TW 2820 Tunable	494 Typ L4	see LEDiL website
Xicato	XOB 23	431 Typ L4	see LEDiL website
Xicato	XOB 32	458 Typ L4	see LEDiL website

LEDiL®	STELLA (Type Z1)	
Passende LEDiL Optik Suitable LEDiL optics Hersteller Webseite Manufacturer website LED Halter B+W LED Holder B+W	STELLA-T4 STELLA-VSM STELLA-DWC2 STELLA-G2-T2 STELLA-G2-T3 STELLA-G2-T4 LEDiL part numbers www.ledil.com 4xx / Typ Z1	
4xx Typ Z1 		eg. STELLA-DWC2 

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL STELLA (Z1)**

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Bridgelux	V9 HD / V11 HD Gen 7,8	496 Typ Z1	see LEDiL website
Bridgelux	V10 Gen 7,8,9	486 Typ Z1	see LEDiL website
Bridgelux	V13 Gen 7,8,9	477 Typ Z1	see LEDiL website
Bridgelux	V15 Gen 7,8,9	456 Typ Z1	see LEDiL website
Bridgelux	V18 Gen 7,8,9	462 Typ Z1	see LEDiL website
Bridgelux	V22 Gen 7,8,9	431 Typ Z1	see LEDiL website
Bridgelux	Vesta DTW 13/15mm Gen 1,2	491 Typ Z1	see LEDiL website
Bridgelux	Vesta DTW 18mm Gen 1	505 Typ Z1	see LEDiL website

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL STELLA (Z1)**

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Bridgelux	Vesta Tunable 9mm Gen 2	489 Typ Z1	see LEDiL website
Bridgelux	Vesta Tunable 13mm Gen 2	492 Typ Z1	see LEDiL website
Bridgelux	Vesta Tunable 15mm Gen 2	482 Typ Z1	see LEDiL website
Bridgelux	Vesta Tunable 18mm Gen 2	483 Typ Z1	see LEDiL website
Bridgelux	Vesta Tunable 22mm Gen 2	494 Typ Z1	see LEDiL website
Citizen	CLU 028 / 02J / 02Q	434 Typ Z1	see LEDiL website
Citizen	CLU 038 / 03H / 03J / 03Q	433 Typ Z1	see LEDiL website
Citizen	CLU 048 / 04H / 04J / 04Q	431 Typ Z1	see LEDiL website
Citizen	CLU 723	477 Typ Z1	see LEDiL website
Citizen	CLU 733	471 Typ Z1	see LEDiL website
Citizen	LCN-C01B2 / C02B2 Tunable	481 Typ Z1	see LEDiL website
Citizen	LCN-C04B2 / C05B2 Tunable	481 Typ Z1	see LEDiL website
CREE	CMA 1516	441 Typ Z1	see LEDiL website
CREE	CMA 1825 / 1840	437 Typ Z1	see LEDiL website
CREE	CMA 2550	439 Typ Z1	see LEDiL website
CREE	CMA 3090	447 Typ Z1	see LEDiL website
CREE	CMB 1507 / 1510 / 1516	441 Typ Z1	see LEDiL website
CREE	CMB 1818 / 1825	437 Typ Z1	see LEDiL website
CREE	CMB 1840	457 Typ Z1	see LEDiL website
CREE	CMB 2550	439 Typ Z1	see LEDiL website
CREE	CMB 3090	447 Typ Z1	see LEDiL website
CREE	CMT 1407 / 1412 / 1420	434 Typ Z1	see LEDiL website
CREE	CMT 1922 / 1925 / 1930 / 1945	477 Typ Z1	see LEDiL website
CREE	CMT 2850 / 2870 / 2890	471 Typ Z1	see LEDiL website
CREE	CMU 1003 / 1006 / 1010 / 1013	434 Typ Z1	see LEDiL website
CREE	CMU 1516 / 1519 / 1526 / 1532	433 Typ Z1	see LEDiL website
CREE	CMU 2236 / 2239 / 2258 / 2287	471 Typ Z1	see LEDiL website
CREE	CXB 1507 / 1512 / 1520	441 Typ Z1	see LEDiL website
CREE	CXB 1816 / 1820	437 Typ Z1	see LEDiL website
CREE	CXB 1830	457 Typ Z1	see LEDiL website
CREE	CXB 2530 / 2540	439 Typ Z1	see LEDiL website
CREE	CXB 3050 / 3070	447 Typ Z1	see LEDiL website
Edison	2PHE 03 / 06 / 09 / 13	434 Typ Z1	see LEDiL website
Edison	2PHE 15 / 18 / 24 / 30	433 Typ Z1	see LEDiL website

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL STELLA (Z1)**


COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Edison	2PHE 55 / 60 / 83	431 Typ Z1	see LEDiL website
Lextar	PB 06 / 09 / 13	434 Typ Z1	see LEDiL website
Lextar	PB 16 / 19 / 26	433 Typ Z1	see LEDiL website
Lextar	PB 38 / 54	431 Typ Z1	see LEDiL website
Lumileds	Luxeon 1202 / 1203 / 1204HD	480 Typ Z1	see LEDiL website
Lumileds	Luxeon 1205HD	480 Typ Z1	see LEDiL website
Lumileds	Luxeon 1204 / 1205	432 Typ Z1	see LEDiL website
Lumileds	Luxeon 1208 / 1210	432 Typ Z1	see LEDiL website
Lumileds	Luxeon 1211	431 Typ Z1	see LEDiL website
Lumileds	Luxeon 1213 / 1216 / 1812 / 1816	431 Typ Z1	see LEDiL website
Lumileds	CS COB L02 / L04	434 Typ Z1	see LEDiL website
Lumileds	CS COB L06 / L08 / L10	433 Typ Z1	see LEDiL website
Lumileds	CS COB L11 / L13 / L16	431 Typ Z1	see LEDiL website
Lumileds	CS COB R12 / R18	431 Typ Z1	see LEDiL website
Lumileds	CX Plus HD S04H9	4xx Typ Z1	see LEDiL website
Lumileds	CX Plus M02Fx / M03Fx	441 Typ Z1	see LEDiL website
Lumileds	CX Plus L04Fx / L05Fx / L08Fx	437 Typ Z1	see LEDiL website
Luminus	CIM/CLM/CXM-9-xC	434 Typ Z1	see LEDiL website
Luminus	CLM/CXM-9-xA	461 Typ Z1	see LEDiL website
Luminus	CHM-9-BH	433 Typ Z1	see LEDiL website
Luminus	CXM-11-xC	433 Typ Z1	see LEDiL website
Luminus	CGM/CIM/CLM/CXM-14-xC	433 Typ Z1	see LEDiL website
Luminus	CVM/CXM-18	453 Typ Z1	see LEDiL website
Luminus	CXM-18 Gen6	431 Typ Z1	see LEDiL website
Luminus	CGM/CIM/CLM/CXM-22-xC	431 Typ Z1	see LEDiL website
Luminus	CDM-9 Gen2 DtW	491 Typ Z1	see LEDiL website
Luminus	CDM-14/CDM-18 DtW	491 Typ Z1	see LEDiL website
Luminus	CTM-14 TW	442 Typ Z1	see LEDiL website
Luminus	CTM-14 RGBW	500 Typ Z1	see LEDiL website
Luminus	CTM-18 Gen1 TW	442 Typ Z1	see LEDiL website
Luminus	CTM-18 Gen2 TW	483 Typ Z1	see LEDiL website
Luminus	CTM-22 TW	494 Typ Z1	see LEDiL website
Luxtech	COB-WD-17-2420	491 Typ Z1	see LEDiL website

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL STELLA (Z1)**



COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Luxtech	COB-DN-16-2420	442 Typ Z1	see LEDiL website
Nichia	NV..L016Z / NV..L024Z	438 Typ Z1	see LEDiL website
Nichia	NF..L036B / NF..L048B	438 Typ Z1	see LEDiL website
Nichia	NF..L060B	438 Typ Z1	see LEDiL website
Nichia	NV..J048Z / NF..J108B	463 Typ Z1	see LEDiL website
Nichia	NF..J130B	463 Typ Z1	see LEDiL website
Nichia	NVCWJ024Z Tunable	498 Typ Z1 HV	see LEDiL website
Philips	Fortimo SLM12xx .. 1619 G7	480 Typ Z1	see LEDiL website
Philips	Fortimo SLM12xx .. 2024 G7	432 Typ Z1	see LEDiL website
Philips	Fortimo SLM12xx .. 2828 G7	431 Typ Z1	see LEDiL website
Philips	Fortimo SLM12xx .. 1313 G7N	434 Typ Z1	see LEDiL website
Philips	Fortimo SLM12xx .. 1919 G7N	433 Typ Z1	see LEDiL website
Philips	Fortimo SLM12xx .. 2828 G7N	431 Typ Z1	see LEDiL website
Philips	Fortimo SLM13xx .. 2024 G8 UHE	432 Typ Z1	see LEDiL website
Philips	Fortimo SLM13xx .. 2828 G8 UHE	431 Typ Z1	see LEDiL website
Philips	Fortimo L09A 1919 G7N Tunable	501 Typ Z1	see LEDiL website
Prolight Opto	PASB	434 Typ Z1	see LEDiL website
Prolight Opto	PASQ/PAPQ DimToWarm	434 Typ Z1	see LEDiL website
Prolight Opto	PDSR DimToWarm	432 Typ Z1	see LEDiL website
Prolight Opto	PDSJ Tunable	442 Typ Z1	see LEDiL website
Samsung	LC 020C / 030C / 040C	477 Typ Z1	see LEDiL website
Samsung	LC 003D / 006D	434 Typ Z1	see LEDiL website
Samsung	LC 009D / 013D	434 Typ Z1	see LEDiL website
Samsung	LC 016D / 019D	477 Typ Z1	see LEDiL website
Samsung	LC 026D / 033D	477 Typ Z1	see LEDiL website
Samsung	LC 040D / 060D / 080D	431 Typ Z1	see LEDiL website
Samsung	LC010T Tunable	501 Typ Z1	see LEDiL website
Samsung	LC020T Tunable	501 Typ Z1	see LEDiL website
Samsung	LC035T Tunable	502 Typ Z1	see LEDiL website
Seoul	SAW* 1062 / 1063	434 Typ Z1	see LEDiL website
Seoul	SAW* 1564 / 1565 / 1566	477 Typ Z1	see LEDiL website
Seoul	SAW* 22AA / 2296	431 Typ Z1	see LEDiL website

Mögliche Halter / COB Kombinationen / Holder / COB combinations LEDiL STELLA (Z1)

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Seoul	SAW* 2298 / 226A	431 Typ Z1	see LEDiL website
Tridonic	SLE ADV8 LES 04 / 06	434 Typ Z1	see LEDiL website
Tridonic	SLE ADV8 LES 09	434 Typ Z1	see LEDiL website
Tridonic	SLE ADV8 LES 13	433 Typ Z1	see LEDiL website
Tridonic	SLE ADV8 LES 15	433 Typ Z1	see LEDiL website
Tridonic	SLE SNC8 LES 09	434 Typ Z1	see LEDiL website
Tridonic	SLE SNC8 LES 15	433 Typ Z1	see LEDiL website
VS Lighting	DMS 124 ***W	434 Typ Z1	see LEDiL website
VS Lighting	DMS 125 / 126 / 128 ***W	433 Typ Z1	see LEDiL website
VS Lighting	DMS 120 ***W	431 Typ Z1	see LEDiL website
VS Lighting	DMS 12C / 18B ***W	431 Typ Z1	see LEDiL website
VS Lighting	DMS 1208J	433 Typ Z1	see LEDiL website
VS Lighting	DMS 1212J / 1812J	431 Typ Z1	see LEDiL website
VS Lighting	VCA2 122 / 123 / 124	486 Typ Z1	see LEDiL website
VS Lighting	VCA2 126 / 128	477 Typ Z1	see LEDiL website
VS Lighting	VCA2 1211 / 1213	471 Typ Z1	see LEDiL website
VS Lighting	TW 1914 Tunable	493 Typ Z1	see LEDiL website
VS Lighting	TW 2820 Tunable	494 Typ Z1	see LEDiL website
VS Lighting	WU-M-618 DimToWarm	434 Typ Z1	see LEDiL website
Xicato	XOB 09	434 Typ Z1	see LEDiL website
Xicato	XOB 14	433 Typ Z1	see LEDiL website
Xicato	XOB 23	431 Typ Z1	see LEDiL website

LEDiL®	WINNIE	
LEDiL Linse LEDiL lens Hersteller Webseite Manufacturer website LED Halter B+W LED Holder B+W	LEDiL part numbers www.ledil.com 4xx / Typ L5	

Für WINNIE-HLD_C ist die passende Lösung unter **LEDiL HEKLA** aufgeführt
Take care that WINNIE-HLD-C requires a different solution available under **LEDiL HEKLA**

4xx / Typ L5 	CN14xxx WINNIE-x 
--	---

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL WINNIE**

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Bridgelux	V3 HD / V4 HD Gen 7,8	460 Typ L5	see part numbers above
Bridgelux	V6 HD Gen 7,8	464 Typ L5	see part numbers above
Bridgelux	V9 HD / V11 HD Gen 7,8	496 Typ L5	see part numbers above
Bridgelux	V6 Gen 8,9 (just 2 pads!)	460 Typ L5	see part numbers above
Bridgelux	V8 Gen 7,8,9 (4 pads)	460 Typ L5	see part numbers above
Bridgelux	V10 Gen 7,8,9	486 Typ L5	see part numbers above
Bridgelux	V13 Gen 7,8,9	477 Typ L5	see part numbers above
Bridgelux	V15 Gen 7,8,9	456 Typ L5	see part numbers above
Bridgelux	V18 Gen 7,8,9	462 Typ L5	see part numbers above
Bridgelux	Vesta DTW 6/9mm Gen 1,2	490 Typ L5	see part numbers above
Bridgelux	Vesta DTW 13/15mm Gen 1,2	491 Typ L5	see part numbers above

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL WINNIE**

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Bridgelux	Vesta DTW 18mm Gen 1	505 Typ L5	see part numbers above
Bridgelux	Vesta Tunable 6mm Gen 2	504 Typ L5	see part numbers above
Bridgelux	Vesta Tunable 9mm Gen 2	489 Typ L5	see part numbers above
Bridgelux	Vesta Tunable 13mm Gen 2	492 Typ L5	see part numbers above
Bridgelux	Vesta Tunable 15mm Gen 2	482 Typ L5	see part numbers above
Bridgelux	Vesta Tunable 18mm Gen 2	483 Typ L5	see part numbers above
Citizen	CLU 028 / 02J / 02Q	434 Typ L5	see part numbers above
Citizen	CLU 038 / 03H / 03J / 03Q	433 Typ L5	see part numbers above
Citizen	CLU 702 / 703 / 7A2 / 7A3 / 7B2	434 Typ L5	see part numbers above
Citizen	CLU 712 / 713	477 Typ L5	see part numbers above
Citizen	CLU 723	477 Typ L5	see part numbers above
Citizen	LCN-C01B2 / C02B2 Tunable	481 Typ L5	see part numbers above
Citizen	LCN-C04B2 / C05B2 Tunable	481 Typ L5	see part numbers above
CREE	CHA 0825	433 Typ L5	see part numbers above
CREE	CMA 1303 / 1306	448 Typ L5	see part numbers above
CREE	CMA 1516	441 Typ L5	see part numbers above
CREE	CMA 1825 / 1840	437 Typ L5	see part numbers above
CREE	CMA 2550	439 Typ L5	see part numbers above
CREE	CMB 1304 / 1306	448 Typ L5	see part numbers above
CREE	CMB 1507 / 1510 / 1516	441 Typ L5	see part numbers above
CREE	CMB 1818 / 1825	437 Typ L5	see part numbers above
CREE	CMB 1840	457 Typ L5	see part numbers above
CREE	CMB 2550	439 Typ L5	see part numbers above
CREE	CMT 1407 / 1412 / 1420	434 Typ L5	see part numbers above
CREE	CMT 1922 / 1925 / 1930 / 1945	477 Typ L5	see part numbers above
CREE	CMU 1003 / 1006 / 1010 / 1013	434 Typ L5	see part numbers above
CREE	CMU 1516 / 1519 / 1526 / 1532	433 Typ L5	see part numbers above
CREE	CXB 1304 / 1310	448 Typ L5	see part numbers above
CREE	CXB 1507 / 1512 / 1520	441 Typ L5	see part numbers above
CREE	CXB 1816 / 1820	437 Typ L5	see part numbers above
CREE	CXB 1830	457 Typ L5	see part numbers above
CREE	CXB 2530 / 2540	439 Typ L5	see part numbers above
Edison	2PHE 03 / 06 / 09 / 13	434 Typ L5	see part numbers above
Edison	2PHE 15 / 18 / 24 / 30	433 Typ L5	see part numbers above

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL WINNIE**


COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Lextar	PB 06 / 09 / 13	434 Typ L5	see part numbers above
Lextar	PB 16 / 19 / 26	433 Typ L5	see part numbers above
Lumileds	Luxeon 1202s / 1202HD	452 Typ L5	see part numbers above
Lumileds	Luxeon 1202 / 1203 / 1204HD	480 Typ L5	see part numbers above
Lumileds	Luxeon 1205HD	480 Typ L5	see part numbers above
Lumileds	Luxeon 1204 / 1205	432 Typ L5	see part numbers above
Lumileds	Luxeon 1208 / 1210	432 Typ L5	see part numbers above
Lumileds	CS COB L02 / L04	434 Typ L5	see part numbers above
Lumileds	CS COB L06 / L08 / L10	433 Typ L5	see part numbers above
Lumileds	CX Plus HD S01H4, S0xH6	448 Typ L5	see part numbers above
Lumileds	CX Plus HD S04H9	4xx Typ L5	see part numbers above
Lumileds	CX Plus M02Fx / M03Fx	441 Typ L5	see part numbers above
Lumileds	CX Plus L04Fx / L05Fx / L08Fx	437 Typ L5	see part numbers above
Luminus	CHM-6-BH / CXM-6-xC	434 Typ L5	see part numbers above
Luminus	CIM/CLM/CXM-9-xC	434 Typ L5	see part numbers above
Luminus	CLM/CXM-9-xA	461 Typ L5	see part numbers above
Luminus	CHM-9-BH	433 Typ L5	see part numbers above
Luminus	CXM-11-xC	433 Typ L5	see part numbers above
Luminus	CGM/CIM/CLM/CXM-14-xC	433 Typ L5	see part numbers above
Luminus	CVM/CXM-18	453 Typ L5	see part numbers above
Luminus	CDM-6 / CDM-9Gen1 DtW	490 Typ L5	see part numbers above
Luminus	CDM-9 Gen2 DtW	491 Typ L5	see part numbers above
Luminus	CDM-14/CDM-18 DtW	491 Typ L5	see part numbers above
Luminus	CTM-6 / CTM-9 TW	495 Typ L5	see part numbers above
Luminus	CTM-14 TW	442 Typ L5	see part numbers above
Luminus	CTM-14 RGBW	500 Typ L5	see part numbers above
Luminus	CTM-18 Gen1 TW	442 Typ L5	see part numbers above
Luminus	CTM-18 Gen2 TW	483 Typ L5	see part numbers above
Luxtech	COB-WD-10-1512	479 Typ L5	see part numbers above
Luxtech	COB-WD-17-2420	491 Typ L5	see part numbers above
Luxtech	COB-DN-16-2420	442 Typ L5	see part numbers above
Nichia	NV..S007Z / NF..T012B	452 Typ L5	see part numbers above

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL WINNIE**



COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Nichia	NF..S024B / NT..S024B	452 Typ L5	see part numbers above
Nichia	NJ..S024Z	452 Typ L5	see part numbers above
Nichia	NV..L016Z / NV..L024Z	438 Typ L5	see part numbers above
Nichia	NF..L036B / NF..L048B	438 Typ L5	see part numbers above
Nichia	NF..L060B	438 Typ L5	see part numbers above
Nichia	NV..J048Z / NF..J108B	463 Typ L5	see part numbers above
Nichia	NF..J130B	463 Typ L5	see part numbers above
Nichia	NJNWS012Z Tunable	495 Typ L5 HV	see part numbers above
Nichia	NJCWL024Z Tunable	497 Typ L5 HV	see part numbers above
Nichia	NVCWJ024Z Tunable	498 Typ L5 HV	see part numbers above
Philips	Fortimo SLM12xx .. 1215 G7	452 Typ L5	see part numbers above
Philips	Fortimo SLM12xx .. 1619 G7	480 Typ L5	see part numbers above
Philips	Fortimo SLM12xx .. 2024 G7	432 Typ L5	see part numbers above
Philips	Fortimo SLM12xx .. 1313 G7N	434 Typ L5	see part numbers above
Philips	Fortimo SLM12xx .. 1919 G7N	433 Typ L5	see part numbers above
Philips	Fortimo SLM13xx .. 2024 G8 UHE	432 Typ L5	see part numbers above
Philips	Fortimo L06A 1313 G7N Tunable	509 Typ L5	see part numbers above
Philips	Fortimo L09A 1919 G7N Tunable	501 Typ L5	see part numbers above
Prolight Opto	PASB	434 Typ L5	see part numbers above
Prolight Opto	PASQ/PAPQ DimToWarm	434 Typ L5	see part numbers above
Prolight Opto	PDSQ DimToWarm	490 Typ L5	see part numbers above
Prolight Opto	PDSR DimToWarm	432 Typ L5	see part numbers above
Prolight Opto	PDSJ Tunable	442 Typ L5	see part numbers above
Samsung	LC 010C	434 Typ L5	see part numbers above
Samsung	LC 020C / 030C / 040C	477 Typ L5	see part numbers above
Samsung	LC 003D / 006D	434 Typ L5	see part numbers above
Samsung	LC 009D / 013D	434 Typ L5	see part numbers above
Samsung	LC 016D / 019D	477 Typ L5	see part numbers above
Samsung	LC 026D / 033D	477 Typ L5	see part numbers above
Samsung	LC010T Tunable	501 Typ L5	see part numbers above
Samsung	LC020T Tunable	501 Typ L5	see part numbers above
Seoul	SAW* 0661	434 Typ L5	see part numbers above
Seoul	SAW* 1062 / 1063	434 Typ L5	see part numbers above

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL WINNIE**

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Seoul	SAW* 1564 / 1565 / 1566	477 Typ L5	see part numbers above
Tridonic	SLE ADV8 LES 04 / 06	434 Typ L5	see part numbers above
Tridonic	SLE ADV8 LES 09	434 Typ L5	see part numbers above
Tridonic	SLE ADV8 LES 13	433 Typ L5	see part numbers above
Tridonic	SLE ADV8 LES 15	433 Typ L5	see part numbers above
Tridonic	SLE SNC8 LES 06	434 Typ L5	see part numbers above
Tridonic	SLE SNC8 LES 09	434 Typ L5	see part numbers above
Tridonic	SLE SNC8 LES 15	433 Typ L5	see part numbers above
VS Lighting	DMS 102 ***W	434 Typ L5	see part numbers above
VS Lighting	DMS 124 ***W	434 Typ L5	see part numbers above
VS Lighting	DMS 125 / 126 / 128 ***W	433 Typ L5	see part numbers above
VS Lighting	DMS 1208J	433 Typ L5	see part numbers above
VS Lighting	VCA2 122 / 123 / 124	486 Typ L5	see part numbers above
VS Lighting	VCA2 126 / 128	477 Typ L5	see part numbers above
VS Lighting	TW 1914 Tunable	493 Typ L5	see part numbers above
VS Lighting	WU-M-618 DimToWarm	434 Typ L5	see part numbers above
Xicato	XOB 06 (B)	486 Typ L5	see part numbers above
Xicato	XOB 09	434 Typ L5	see part numbers above
Xicato	XOB 14	433 Typ L5	see part numbers above

LEDiL®	ZORYA	
LEDiL Linse LEDiL lense	F15074_ZORYA-SC	
Hersteller Webseite Manufacturer website	www.ledil.com	
LED Halter B+W LED Holder B+W	4xx / Typ L7	

Alternativ zur direkten Montage kann ZORYA auch mit dem Adapter HEKLA montiert werden.
In addition to the direct mounting Zorya can be assembled with the LEDiL HEKLA adaptor

4xx / Typ L7	F15074_ZORYA-SC
	
	Bottom view

Mögliche Halter / COB Kombinationen / Holder / COB combinations LEDiL ZORYA			
COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Bridgelux	V9 HD / V11 HD Gen 7,8	496 Typ L7	F15074_ZORYA-SC
Bridgelux	V10 Gen 7,8,9	486 Typ L7	F15074_ZORYA-SC
Bridgelux	V13 Gen 7,8,9	477 Typ L7	F15074_ZORYA-SC
Bridgelux	V15 Gen 7,8,9	456 Typ L7	F15074_ZORYA-SC
Bridgelux	V18 Gen 7,8,9	462 Typ L7	F15074_ZORYA-SC
Bridgelux	V22 Gen 7,8,9	431 Typ L7	F15074_ZORYA-SC
Bridgelux	Vesta DTW 13/15mm Gen 1,2	491 Typ L7	F15074_ZORYA-SC
Bridgelux	Vesta DTW 18mm Gen 1	505 Typ L7	F15074_ZORYA-SC
Bridgelux	Vesta Tunable 9mm Gen 2	489 Typ L7	F15074_ZORYA-SC
Bridgelux	Vesta Tunable 13mm Gen 2	492 Typ L7	F15074_ZORYA-SC
Bridgelux	Vesta Tunable 15mm Gen 2	482 Typ L7	F15074_ZORYA-SC
Bridgelux	Vesta Tunable 18mm Gen 2	483 Typ L7	F15074_ZORYA-SC

Mögliche Halter / COB Kombinationen / Holder / COB combinations LEDiL ZORYA

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Bridgelux	Vesta Tunable 22mm Gen 2	494 Typ L7	F15074_ZORYA-SC
Citizen	CLU 028 / 02J / 02Q	434 Typ L7	F15074_ZORYA-SC
Citizen	CLU 038 / 03H / 03J / 03Q	433 Typ L7	F15074_ZORYA-SC
Citizen	CLU 048 / 04H / 04J / 04Q	431 Typ L7	F15074_ZORYA-SC
Citizen	CLU 723	477 Typ L7	F15074_ZORYA-SC
Citizen	CLU 733	471 Typ L7	F15074_ZORYA-SC
Citizen	LCN-C01B2 / C02B2 Tunable	481 Typ L7	F15074_ZORYA-SC
Citizen	LCN-C04B2 / C05B2 Tunable	481 Typ L7	F15074_ZORYA-SC
CREE	CMA 1516	441 Typ L7	F15074_ZORYA-SC
CREE	CMA 1825 / 1840	437 Typ L7	F15074_ZORYA-SC
CREE	CMA 2550	439 Typ L7	F15074_ZORYA-SC
CREE	CMA 3090	447 Typ L7	F15074_ZORYA-SC
CREE	CMB 1507 / 1510 / 1516	441 Typ L7	F15074_ZORYA-SC
CREE	CMB 1818 / 1825	437 Typ L7	F15074_ZORYA-SC
CREE	CMB 1840	457 Typ L7	F15074_ZORYA-SC
CREE	CMB 2550	439 Typ L7	F15074_ZORYA-SC
CREE	CMB 3090	447 Typ L7	F15074_ZORYA-SC
CREE	CMT 1407 / 1412 / 1420	434 Typ L7	F15074_ZORYA-SC
CREE	CMT 1922 / 1925 / 1930 / 1945	477 Typ L7	F15074_ZORYA-SC
CREE	CMT 2850 / 2870 / 2890	471 Typ L7	F15074_ZORYA-SC
CREE	CMU 1003 / 1006 / 1010 / 1013	434 Typ L7	F15074_ZORYA-SC
CREE	CMU 1516 / 1519 / 1526 / 1532	433 Typ L7	F15074_ZORYA-SC
CREE	CMU 2236 / 2239 / 2258 / 2287	471 Typ L7	F15074_ZORYA-SC
CREE	CXB 1507 / 1512 / 1520	441 Typ L7	F15074_ZORYA-SC
CREE	CXB 1816 / 1820	437 Typ L7	F15074_ZORYA-SC
CREE	CXB 1830	457 Typ L7	F15074_ZORYA-SC
CREE	CXB 2530 / 2540	439 Typ L7	F15074_ZORYA-SC
CREE	CXB 3050 / 3070	447 Typ L7	F15074_ZORYA-SC
Edison	2PHE 03 / 06 / 09 / 13	434 Typ L7	F15074_ZORYA-SC
Edison	2PHE 15 / 18 / 24 / 30	433 Typ L7	F15074_ZORYA-SC
Edison	2PHE 55 / 60 / 83	431 Typ L7	F15074_ZORYA-SC
Lextar	PB 06 / 09 / 13	434 Typ L7	F15074_ZORYA-SC
Lextar	PB 16 / 19 / 26	433 Typ L7	F15074_ZORYA-SC

Mögliche Halter / COB Kombinationen / Holder / COB combinations LEDiL ZORYA

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Lextar	PB 38 / 54	431 Typ L7	F15074_ZORYA-SC
Lumileds	Luxeon 1202 / 1203 / 1204HD	480 Typ L7	F15074_ZORYA-SC
Lumileds	Luxeon 1205HD	480 Typ L7	F15074_ZORYA-SC
Lumileds	Luxeon 1204 / 1205	432 Typ L7	F15074_ZORYA-SC
Lumileds	Luxeon 1208 / 1210	432 Typ L7	F15074_ZORYA-SC
Lumileds	Luxeon 1211	431 Typ L7	F15074_ZORYA-SC
Lumileds	Luxeon 1213 / 1216 / 1812 / 1816	431 Typ L7	F15074_ZORYA-SC
Lumileds	CS COB L02 / L04	434 Typ L7	F15074_ZORYA-SC
Lumileds	CS COB L06 / L08 / L10	433 Typ L7	F15074_ZORYA-SC
Lumileds	CS COB L11 / L13 / L16	431 Typ L7	F15074_ZORYA-SC
Lumileds	CS COB R12 / R18	431 Typ L7	F15074_ZORYA-SC
Lumileds	CX Plus HD S04H9	4xx Typ L7	F15074_ZORYA-SC
Lumileds	CX Plus M02Fx / M03Fx	441 Typ L7	F15074_ZORYA-SC
Lumileds	CX Plus L04Fx / L05Fx / L08Fx	437 Typ L7	F15074_ZORYA-SC
Luminus	CIM/CLM/CXM-9-xC	434 Typ L7	F15074_ZORYA-SC
Luminus	CLM/CXM-9-xA	461 Typ L7	F15074_ZORYA-SC
Luminus	CHM-9-BH	433 Typ L7	F15074_ZORYA-SC
Luminus	CXM-11-xC	433 Typ L7	F15074_ZORYA-SC
Luminus	CGM/CIM/CLM/CXM-14-xC	433 Typ L7	F15074_ZORYA-SC
Luminus	CVM/CXM-18	453 Typ L7	F15074_ZORYA-SC
Luminus	CXM-18 Gen6	431 Typ L7	F15074_ZORYA-SC
Luminus	CGM/CIM/CLM/CXM-22-xC	431 Typ L7	F15074_ZORYA-SC
Luminus	CDM-9 Gen2 DtW	491 Typ L7	F15074_ZORYA-SC
Luminus	CDM-14/CDM-18 DtW	491 Typ L7	F15074_ZORYA-SC
Luminus	CTM-14 TW	442 Typ L7	F15074_ZORYA-SC
Luminus	CTM-14 RGBW	500 Typ L7	F15074_ZORYA-SC
Luminus	CTM-18 Gen1 TW	442 Typ L7	F15074_ZORYA-SC
Luminus	CTM-18 Gen2 TW	483 Typ L7	F15074_ZORYA-SC
Luminus	CTM-22 TW	494 Typ L7	F15074_ZORYA-SC
Luxtech	COB-WD-17-2420	491 Typ L7	F15074_ZORYA-SC
Luxtech	COB-DN-16-2420	442 Typ L7	F15074_ZORYA-SC
Nichia	NV..L016Z / NV..L024Z	438 Typ L7	F15074_ZORYA-SC
Nichia	NF..L036B / NF..L048B	438 Typ L7	F15074_ZORYA-SC

Mögliche Halter / COB Kombinationen / Holder / COB combinations LEDiL ZORYA

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Nichia	NF..L060B	438 Typ L7	F15074_ZORYA-SC
Nichia	NV..J048Z / NF..J108B	463 Typ L7	F15074_ZORYA-SC
Nichia	NF..J130B	463 Typ L7	F15074_ZORYA-SC
Nichia	NVCWJ024Z Tunable	498 Typ L7 HV	F15074_ZORYA-SC
Philips	Fortimo SLM12xx .. 1619 G7	480 Typ L7	F15074_ZORYA-SC
Philips	Fortimo SLM12xx .. 2024 G7	432 Typ L7	F15074_ZORYA-SC
Philips	Fortimo SLM12xx .. 2828 G7	431 Typ L7	F15074_ZORYA-SC
Philips	Fortimo SLM12xx .. 1313 G7N	434 Typ L7	F15074_ZORYA-SC
Philips	Fortimo SLM12xx .. 1919 G7N	433 Typ L7	F15074_ZORYA-SC
Philips	Fortimo SLM12xx .. 2828 G7N	431 Typ L7	F15074_ZORYA-SC
Philips	Fortimo SLM13xx .. 2024 G8 UHE	432 Typ L7	F15074_ZORYA-SC
Philips	Fortimo SLM13xx .. 2828 G8 UHE	431 Typ L7	F15074_ZORYA-SC
Philips	Fortimo L09A 1919 G7N Tunable	501 Typ L7	F15074_ZORYA-SC
Prolight Opto	PASB	434 Typ L7	F15074_ZORYA-SC
Prolight Opto	PASQ/PAPQ DimToWarm	434 Typ L7	F15074_ZORYA-SC
Prolight Opto	PDSR DimToWarm	432 Typ L7	F15074_ZORYA-SC
Prolight Opto	PDSJ Tunable	442 Typ L7	F15074_ZORYA-SC
Samsung	LC 020C / 030C / 040C	477 Typ L7	F15074_ZORYA-SC
Samsung	LC 003D / 006D	434 Typ L7	F15074_ZORYA-SC
Samsung	LC 009D / 013D	434 Typ L7	F15074_ZORYA-SC
Samsung	LC 016D / 019D	477 Typ L7	F15074_ZORYA-SC
Samsung	LC 026D / 033D	477 Typ L7	F15074_ZORYA-SC
Samsung	LC 040D / 060D / 080D	431 Typ L7	F15074_ZORYA-SC
Samsung	LC010T Tunable	501 Typ L7	F15074_ZORYA-SC
Samsung	LC020T Tunable	501 Typ L7	F15074_ZORYA-SC
Samsung	LC035T Tunable	502 Typ L7	F15074_ZORYA-SC
Seoul	SAW* 1062 / 1063	434 Typ L7	F15074_ZORYA-SC
Seoul	SAW* 1564 / 1565 / 1566	477 Typ L7	F15074_ZORYA-SC
Seoul	SAW* 22AA / 2296	431 Typ L7	F15074_ZORYA-SC
Seoul	SAW* 2298 / 226A	431 Typ L7	F15074_ZORYA-SC
Tridonic	SLE ADV8 LES 04 / 06	434 Typ L7	F15074_ZORYA-SC
Tridonic	SLE ADV8 LES 09	434 Typ L7	F15074_ZORYA-SC

Mögliche Halter / COB Kombinationen / Holder / COB combinations **LEDiL ZORYA**

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder	Linse Lense
Tridonic	SLE ADV8 LES 13	433 Typ L7	F15074_ZORYA-SC
Tridonic	SLE ADV8 LES 15	433 Typ L7	F15074_ZORYA-SC
Tridonic	SLE SNC8 LES 09	434 Typ L7	F15074_ZORYA-SC
Tridonic	SLE SNC8 LES 15	433 Typ L7	F15074_ZORYA-SC
VS Lighting	DMS 124 ***W	434 Typ L7	F15074_ZORYA-SC
VS Lighting	DMS 125 / 126 / 128 ***W	433 Typ L7	F15074_ZORYA-SC
VS Lighting	DMS 120 ***W	431 Typ L7	F15074_ZORYA-SC
VS Lighting	DMS 12C / 18B ***W	431 Typ L7	F15074_ZORYA-SC
VS Lighting	DMS 1208J	433 Typ L7	F15074_ZORYA-SC
VS Lighting	DMS 1212J / 1812J	431 Typ L7	F15074_ZORYA-SC
VS Lighting	VCA2 122 / 123 / 124	486 Typ L7	F15074_ZORYA-SC
VS Lighting	VCA2 126 / 128	477 Typ L7	F15074_ZORYA-SC
VS Lighting	VCA2 1211 / 1213	471 Typ L7	F15074_ZORYA-SC
VS Lighting	TW 1914 Tunable	493 Typ L7	F15074_ZORYA-SC
VS Lighting	TW 2820 Tunable	494 Typ L7	F15074_ZORYA-SC
VS Lighting	WU-M-618 DimToWarm	434 Typ L7	F15074_ZORYA-SC
Xicato	XOB 09	434 Typ L7	F15074_ZORYA-SC
Xicato	XOB 14	433 Typ L7	F15074_ZORYA-SC
Xicato	XOB 23	431 Typ L7	F15074_ZORYA-SC



Buch 3 kompatibler Halter
Book 3 compatible holder

Zhaga Webseite
Zhaga website

www.zhagastandard.org

LED Halter B+W
LED Holder B+W

4xx / Typ Z1

Zertifikate / certificates

Ausweis-Nr.
40041342





File
E47294



Unsere Halter 4xx Typ Z1 entsprechen mit dem Aussendurchmesser und den Befestigungspunkten den Vorgaben von Zhaga Buch 3, aber durch die extrem flache Bauweise können sie nicht zertifiziert werden.

The shape and fixing points holders of our holders 4xx Type Z1 are compatible to Zhaga Book 3, but due to the thin design they cannot be certified.

4xx / Typ Z1



verfügbare Halter / available Holder

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder
Bridgelux	V3 HD / V4 HD Gen 7,8	460 Typ Z1
Bridgelux	V6 HD Gen 7,8	464 Typ Z1
Bridgelux	V9 HD / V11 HD Gen 7,8	496 Typ Z1
Bridgelux	V6 Gen 8,9 (just 2 pads!)	460 Typ Z1
Bridgelux	V8 Gen 7,8,9 (4 pads)	460 Typ Z1
Bridgelux	V10 Gen 7,8,9	486 Typ Z1
Bridgelux	V13 Gen 7,8,9	477 Typ Z1
Bridgelux	V15 Gen 7,8,9	456 Typ Z1
Bridgelux	V18 Gen 7,8,9	462 Typ Z1
Bridgelux	V22 Gen 7,8,9	431 Typ Z1
Bridgelux	Vesta DTW 6/9mm Gen 1,2	490 Typ Z1

verfügbare Halter / available Holder

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder
Bridgelux	Vesta DTW 13/15mm Gen 1,2	491 Typ Z1
Bridgelux	Vesta DTW 18mm Gen 1	505 Typ Z1
Bridgelux	Vesta Tunable 6mm Gen 2	504 Typ Z1
Bridgelux	Vesta Tunable 9mm Gen 2	489 Typ Z1
Bridgelux	Vesta Tunable 13mm Gen 2	492 Typ Z1
Bridgelux	Vesta Tunable 15mm Gen 2	482 Typ Z1
Bridgelux	Vesta Tunable 18mm Gen 2	483 Typ Z1
Bridgelux	Vesta Tunable 22mm Gen 2	494 Typ Z1
Citizen	CLU 028 / 02J / 02Q	434 Typ Z1
Citizen	CLU 038 / 03H / 03J / 03Q	433 Typ Z1
Citizen	CLU 048 / 04H / 04J / 04Q	431 Typ Z1
Citizen	CLU 702 / 703 / 7A2 / 7A3 / 7B2	434 Typ Z1
Citizen	CLU 712 / 713	477 Typ Z1
Citizen	CLU 723	477 Typ Z1
Citizen	CLU 733	471 Typ Z1
Citizen	LCN-C01B2 / C02B2 Tunable	481 Typ Z1
Citizen	LCN-C04B2 / C05B2 Tunable	481 Typ Z1
CREE	CHA 0825	433 Typ Z1
CREE	CMA 1303 / 1306	448 Typ Z1
CREE	CMA 1516	441 Typ Z1
CREE	CMA 1825 / 1840	437 Typ Z1
CREE	CMA 2550	439 Typ Z1
CREE	CMA 3090	447 Typ Z1
CREE	CMB 1304 / 1306	448 Typ Z1
CREE	CMB 1507 / 1510 / 1516	441 Typ Z1
CREE	CMB 1818 / 1825	437 Typ Z1
CREE	CMB 1840	457 Typ Z1
CREE	CMB 2550	439 Typ Z1
CREE	CMB 3090	447 Typ Z1
CREE	CMT 1407 / 1412 / 1420	434 Typ Z1
CREE	CMT 1922 / 1925 / 1930 / 1945	477 Typ Z1
CREE	CMT 2850 / 2870 / 2890	471 Typ Z1
CREE	CMU 1003 / 1006 / 1010 / 1013	434 Typ Z1
CREE	CMU 1516 / 1519 / 1526 / 1532	433 Typ Z1
CREE	CMU 2236 / 2239 / 2258 / 2287	471 Typ Z1

verfügbare Halter / available Holder

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder
CREE	CXB 1304 / 1310	448 Typ Z1
CREE	CXB 1507 / 1512 / 1520	441 Typ Z1
CREE	CXB 1816 / 1820	437 Typ Z1
CREE	CXB 1830	457 Typ Z1
CREE	CXB 2530 / 2540	439 Typ Z1
CREE	CXB 3050 / 3070	447 Typ Z1
Edison	2PHE 03 / 06 / 09 / 13	434 Typ Z1
Edison	2PHE 15 / 18 / 24 / 30	433 Typ Z1
Edison	2PHE 55 / 60 / 83	431 Typ Z1
Lextar	PB 06 / 09 / 13	434 Typ Z1
Lextar	PB 16 / 19 / 26	433 Typ Z1
Lextar	PB 38 / 54	431 Typ Z1
Lumileds	Luxeon 1202s / 1202HD	452 Typ Z1
Lumileds	Luxeon 1202 / 1203 / 1204HD	480 Typ Z1
Lumileds	Luxeon 1205HD	480 Typ Z1
Lumileds	Luxeon 1204 / 1205	432 Typ Z1
Lumileds	Luxeon 1208 / 1210	432 Typ Z1
Lumileds	Luxeon 1211	431 Typ Z1
Lumileds	Luxeon 1213 / 1216 / 1812 / 1816	431 Typ Z1
Lumileds	CS COB L02 / L04	434 Typ Z1
Lumileds	CS COB L06 / L08 / L10	433 Typ Z1
Lumileds	CS COB L11 / L13 / L16	431 Typ Z1
Lumileds	CS COB R12 / R18	431 Typ Z1
Lumileds	CX Plus HD S01H4, S0xH6	448 Typ Z1
Lumileds	CX Plus HD S04H9	4xx Typ Z1
Lumileds	CX Plus S01Fx / S02Fx	448 Typ Z1
Lumileds	CX Plus M02Fx / M03Fx	441 Typ Z1
Lumileds	CX Plus L04Fx / L05Fx / L08Fx	437 Typ Z1
Luminus	CHM-4-BH / CXM-4-xC	434 Typ Z1
Luminus	CHM-6-BH / CXM-6-xC	434 Typ Z1
Luminus	CIM/CLM/CXM-9-xC	434 Typ Z1
Luminus	CLM/CXM-9-xA	461 Typ Z1
Luminus	CHM-9-BH	433 Typ Z1

verfügbare Halter / available Holder

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder
Luminus	CXM-11-xC	433 Typ Z1
Luminus	CGM/CIM/CLM/CXM-14-xC	433 Typ Z1
Luminus	CVM/CXM-18	453 Typ Z1
Luminus	CXM-18 Gen6	431 Typ Z1
Luminus	CGM/CIM/CLM/CXM-22-xC	431 Typ Z1
Luminus	CDM-6 / CDM-9Gen1 DtW	490 Typ Z1
Luminus	CDM-9 Gen2 DtW	491 Typ Z1
Luminus	CDM-14/CDM-18 DtW	491 Typ Z1
Luminus	CTM-6 / CTM-9 TW	495 Typ Z1
Luminus	CTM-14 TW	442 Typ Z1
Luminus	CTM-14 RGBW	500 Typ Z1
Luminus	CTM-18 Gen1 TW	442 Typ Z1
Luminus	CTM-18 Gen2 TW	483 Typ Z1
Luminus	CTM-22 TW	494 Typ Z1
Luxtech	COB-WD-10-1512	479 Typ Z1
Luxtech	COB-WD-17-2420	491 Typ Z1
Luxtech	COB-DN-16-2420	442 Typ Z1
Nichia	NV..S007Z / NF..T012B	452 Typ Z1
Nichia	NF..S024B / NT..S024B	452 Typ Z1
Nichia	NJ..S024Z	452 Typ Z1
Nichia	NV..L016Z / NV..L024Z	438 Typ Z1
Nichia	NF..L036B / NF..L048B	438 Typ Z1
Nichia	NF..L060B	438 Typ Z1
Nichia	NV..J048Z / NF..J108B	463 Typ Z1
Nichia	NF..J130B	463 Typ Z1
Nichia	NJNWS012Z Tunable	495 Typ Z1 HV
Nichia	NJCWL024Z Tunable	497 Typ Z1 HV
Nichia	NVCWJ024Z Tunable	498 Typ Z1 HV
Philips	Fortimo SLM12xx .. 1215 G7	452 Typ Z1
Philips	Fortimo SLM12xx .. 1619 G7	480 Typ Z1
Philips	Fortimo SLM12xx .. 2024 G7	432 Typ Z1
Philips	Fortimo SLM12xx .. 2828 G7	431 Typ Z1
Philips	Fortimo SLM12xx .. 1313 G7N	434 Typ Z1
Philips	Fortimo SLM12xx .. 1919 G7N	433 Typ Z1

verfügbare Halter / available Holder

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder
Philips	Fortimo SLM12xx .. 2828 G7N	431 Typ Z1
Philips	Fortimo SLM13xx .. 2024 G8 UHE	432 Typ Z1
Philips	Fortimo SLM13xx .. 2828 G8 UHE	431 Typ Z1
Philips	Fortimo L06A 1313 G7N Tunable	509 Typ Z1
Philips	Fortimo L09A 1919 G7N Tunable	501 Typ Z1
Prolight Opto	PASB	434 Typ Z1
Prolight Opto	PASQ/PAPQ DimToWarm	434 Typ Z1
Prolight Opto	PDSQ DimToWarm	490 Typ Z1
Prolight Opto	PDSR DimToWarm	432 Typ Z1
Prolight Opto	PDSJ Tunable	442 Typ Z1
Samsung	LC 010C	434 Typ Z1
Samsung	LC 020C / 030C / 040C	477 Typ Z1
Samsung	LC 003D / 006D	434 Typ Z1
Samsung	LC 009D / 013D	434 Typ Z1
Samsung	LC 016D / 019D	477 Typ Z1
Samsung	LC 026D / 033D	477 Typ Z1
Samsung	LC 040D / 060D / 080D	431 Typ Z1
Samsung	LC010T Tunable	501 Typ Z1
Samsung	LC020T Tunable	501 Typ Z1
Samsung	LC035T Tunable	502 Typ Z1
Seoul	SAW* 0661	434 Typ Z1
Seoul	SAW* 1062 / 1063	434 Typ Z1
Seoul	SAW* 1564 / 1565 / 1566	477 Typ Z1
Seoul	SAW* 22AA / 2296	431 Typ Z1
Seoul	SAW* 2298 / 226A	431 Typ Z1
Tridonic	SLE ADV8 LES 04 / 06	434 Typ Z1
Tridonic	SLE ADV8 LES 09	434 Typ Z1
Tridonic	SLE ADV8 LES 13	433 Typ Z1
Tridonic	SLE ADV8 LES 15	433 Typ Z1
Tridonic	SLE SNC8 LES 06	434 Typ Z1
Tridonic	SLE SNC8 LES 09	434 Typ Z1
Tridonic	SLE SNC8 LES 15	433 Typ Z1

verfügbare Halter / available Holder

COB Hersteller COB Supplier	COB Typ COB Type	Halter Holder
VS Lighting	DMS 102 ***W	434 Typ Z1
VS Lighting	DMS 124 ***W	434 Typ Z1
VS Lighting	DMS 125 / 126 / 128 ***W	433 Typ Z1
VS Lighting	DMS 120 ***W	431 Typ Z1
VS Lighting	DMS 12C / 18B ***W	431 Typ Z1
VS Lighting	DMS 1208J	433 Typ Z1
VS Lighting	DMS 1212J / 1812J	431 Typ Z1
VS Lighting	VCA 042	486 Typ Z1
VS Lighting	VCA2 122 / 123 / 124	486 Typ Z1
VS Lighting	VCA2 126 / 128	477 Typ Z1
VS Lighting	VCA2 1211 / 1213	471 Typ Z1
VS Lighting	TW 1914 Tunable	493 Typ Z1
VS Lighting	TW 2820 Tunable	494 Typ Z1
VS Lighting	WU-M-618 DimToWarm	434 Typ Z1
Xicato	XOB 04	486 Typ Z1
Xicato	XOB 06 (B)	486 Typ Z1
Xicato	XOB 09	434 Typ Z1
Xicato	XOB 14	433 Typ Z1
Xicato	XOB 23	431 Typ Z1

**Wir helfen Ihnen gerne weiter.
Sprechen Sie uns einfach an!**

Please don't hesitate to contact us
for any further questions.

**BENDER
+ WIRTH**



Ihr Kontakt:
Your contact:

Michael Kritzler
Head of Engineering
+49 (0) 2359 / 669 - 184
kritzler@bender-wirth.de

Bender + Wirth GmbH & Co.
D-58566 Kierspe, Germany
+49 (2359) / 669 - 0
sales@bender-wirth.de
www.bender-wirth.de