

Low Forward Voltage Bridge Rectifiers

Part Number	Packages	Forward Voltage Drop $V_F(V)$ @ 25°C	Total Capacitance C_T (pF)	Max. Average Rectified Current I_O (A)	Peak Repetitive Reverse Voltage V_{RRM} (V)	Max. Peak Forward Surge Current I_{FSM} (A)	Max. Reverse Current I_R (μ A)
GBJ15JL	GBJ	0,9	137	15	600	200	10
GBJ15V10	GBJ	0,92	137	15	1000	400	5
GBJ25JL	GBJ	0,92	150	25	600	320	10
GBJ25L06	GBJ	0,92	150	25	600	320	10
GBJ25L08	GBJ	0,9	250	25	800	320	10
GBJ25V08	GBJ	0,92	168	25	800	600	5
GBJ35L06	GBJ	0,91	270	35	600	400	10
GBJ35S06	GBJ	0,93	240	35	600	400	10
GBJ40L06	GBJ	0,9	400	40	600	420	10
GBJ50S06	GBJ	0,93	400	50	600	500	10
GBP6L06	GBP	0,9	75	6	600	135	5
GBU15L08	GBU	0,9	160	15	800	250	10
KBJ15L06	KBJ	0,9	120	15	600	200	5
KBJ15L08	KBJ	0,9	165	15	800	200	5
KBJ20L06	KBJ	0,9	180	20	600	200	10
KBJL10L06	KBJL	0,9	95	10	600	180	10
KBJL15L06	KBJL	0,9	140	15	600	250	10
TT6JL	TTL	0,9	85	6	600	150	5
TT8L08	TTL	0,9	90	8	800	165	5